

Radio Fun

BULK RATE
U.S. POSTAGE
PAID
PERMIT #1
MANCHESTER, NH

\$2.00

"The beginner's guide
to the exciting world
of amateur radio."

in this issue

features

- 4 Editorial N1GPH
- 4 ARRL DX-QSL Bureau K6OHM
- 6 Collect Those QSL Cards 7J1AAL/KA2TNZ
- 8 Two Meter Quad WA6HNO
- 10 The "No Antennas" Antenna N9CAP
- 19 A Place to Put It All WB4NBI
- 20 A Buyer's and Repair Guide WB2BMH
- 26 Watts 'n' SWR KT2B
- 29 Ham Stories Staff

reviews

- 14 The OXO Transmitter Kit WB8ELK

departments

- 28 Flea Market Staff
- 5 Letters Staff
- 18 Radio Magic WB8VGE
- 1.4 Radio News Staff
- 12 The Tech Side KB1UM
- 24 Try Something New WB8ELK
- 22 Upgrade . . . Don't Stop Now! WB6NOA
- 16 What Next? WB2MGP

Southeastern Community College Rocket Flight

In mid-October, students at Southeastern Community College in Whiteville, North Carolina, plan to fly their 11-foot rocket into space. As part of their electronics course, the students built a 73-pound rocket which they plan to fly up to over 300,000 feet. To achieve this altitude, they will lift the rocket up to 80,000 feet via a large balloon and ignite it by a remote radio command. Since this is above most of the Earth's atmosphere, the rocket should fly to incredible heights.

The rocket will carry a 2 meter packet beacon on a frequency of 144.440 MHz FM. Listen for telemetry information on this frequency every 20 seconds during the flight. Also, two ATV (Amateur Television) transmitters should send back spectacular views from the edge of space from a color camcorder and a B/W miniature camera. Look for these on 439.25 MHz (AM standard TV)

and 1255 MHz (FM TV). Those of you who have cable-ready TV sets or VCRs can tune into the rocket video signals by tuning in cable channel 60 (be sure to attach an external antenna to your TV or VCR). Anyone living within 400 miles of Wilmington, North Carolina (the launch point), should receive the rocket signals during the balloon ascent. During the rocket flight to space, anyone within 700 miles may have a chance. An HF information net can be heard on 7.155 MHz during the flight. Lift-off is tentatively scheduled for 6 a.m. Eastern time. Announcements of the actual launch date will be issued on the AMSAT net (every Tuesday night at 9 p.m. Eastern on a frequency of 3.840 MHz) or the ATV net (every Tuesday night at 9 p.m. Eastern on 3.871 MHz). Look on your local packet BBSs for any updates as well. *Bill Brown WB8ELK, Editor.*

Photo. The Southeastern Community College Rocket. (l to r): Simms Spears, David Couvillon KC4WDW, and Ben Frink KD4BFG.



Radio Astronomy

Radio astronomy can be done on any frequency that's free of terrestrial radio signals. There are many types of celestial radio emitters which generate noise (generally wideband noise). At the lower frequencies the emissions are dominated by non-thermal mechanisms. For example, the planet Jupiter is a very strong emitter of radiation in the 5-39 MHz range. Indeed, much of the background noise you hear on HF is quite often dominated by these signals.

At higher frequencies, you get continuous emission from interactions between free electrons, again producing broadband noise. You also get spectral line emission from atomic recombination and molecular transitions.

If you have an OSCAR station, and you want to do a simple exper-

iment, try this: Point your 2 meter antenna straight south and up 30 or so degrees (if you're in the Northern Hemisphere). Tune your 2 meter rig to an unused frequency in your area and set the mode to SSB (or CW). Turn on your GaAsFET preamp and write down the S-meter reading of the background noise every half hour or so for a day, or as long as you want. If you notice the noise level going up and down from S-0 to S-6 or so with a 24-hour period, congratulations! You might also see another hump in your data at about local noon corresponding to the sun. The sun, however, is not nearly as strong as the galactic center at 144 MHz. *Story by U.S. Astronaut Ron Parise WA4SIR, courtesy SpaceNews, via "The Parking Ticket," June 1991.*

Students Track DOVE

Chaminade College Prep in West Hills, California, is one of the schools most active in satellite operation. Physics instructor Dave Reeves KF6PJ has developed a set of experiments to challenge his advanced students' knowledge of the fundamental concepts in physics. Laura Waggoner, one of his students who has been watching DOVE telemetry, has concluded that DOVE's spin rate has slowed considerably. Microsat command station operator Jim White WD0E, well-known for his Microsat motion studies, reports: "I have not been watching DOVE closely, and so cannot confirm Laura's observations. The question is not idle, because WEBER has slowed considerably, and while several theories are floating around, none can fully explain why. If DOVE has also slowed, it would be very valuable input to the mathematical models of spin rate several people are trying to build."

Teachers and students who would like to participate in satellite operation and other exciting OSCAR activities in their schools are advised to contact Rich Ensign N8IWJ, AMSAT Science Education Advisor, 421 N. Military, Dearborn MI 48124. TNX *Westlink Report*, Number 604.

WB2JKJ Classroom Net

For the last 11 years, radio amateurs have been meeting on the Classroom Net to share ideas regarding education, and to speak to young people, broadening their understanding of the world and increasing their desire to come to school. The Net meets on 7.238 MHz at 1100 UTC to 1230, then 1300 to 1900 UTC on 21.395 daily. With the addition of packet radio, EDUCOM will be a part of each Net, and discussed daily. The Net invites hams with a General Class license or higher to join Net discussions whether they are in a classroom or not. Novices, Techs, and SWLs are asked to listen and send in their questions and topics for discussion. If Net Control in NYC cannot be copied, look for one of the several relay stations around the country. TNX *Westlink Report*, Number 604.

NEW

2



DROP-IN
QUICK
CHARGER
AVAILABLE

INNOVATIVE
NI-CD BATTERY
DESIGN

40
MEMORY
CHANNELS



FULL SIZE

ILLUMINATED KEY PAD FOR EASY
OPERATION AND PROGRAMMING

**BIG SPEAKER —
GREAT SOUND**



LOW POWER



MID POWER



HIGH POWER

3 POWER SELECTIONS

ACTUAL SIZE

- DSQ
- TRANS-MESSAGE FUNCTION
- DUAL WATCH
- 4 AUTO DIALER CHANNELS
- 8 SCAN MODES
- REMOTE CONTROL WITH OPTIONAL EMS-8

DJ-F1T

ALINCO

ELECTRONICS INC.

**2 YEARS
LIMITED WARRANTY**



438 Amapola Avenue, Unit 130, Torrance, CA 90501, U.S.A.

Tel: (213) 618-8616 Fax: (213) 618-8758

SPECIFICATIONS AND FEATURES ARE SUBJECT TO CHANGE WITHOUT NOTICE OR OBLIGATION.



Technical Advice & Support readily available to all customers



WE SHIP WORLDWIDE

Barry Electronics Corp.

WORLD WIDE AMATEUR RADIO SINCE 1950
Your one source for all Radio Equipment!



Kitty and the Whole Gang Say
Welcome to the World of Ham Radio

KITTY SAYS: WE ARE NOW OPEN 7 DAYS A WEEK.
Saturday & Sunday 10 to 5 P.M.
Monday-Friday 9 to 6:00 PM
Come to Barry's for the best buys in town



DRSI

ONV Safety
belts-in stock

YAESU

FT-767GX, FT-757GXII, FT-747GX, FT-990,
FRG-8800, FT-736R, FT-1000D,
FT-5200, FT 212/712RH, FT-470

KENWOOD



ANTENNAS

A-S, AES, Cushcraft, Hy-Gain,
Hustler, KLM, METZ, Urban,
MODUBLOX, TONNA, Butternut
Multi-Band

TS440S/AT, R-5000, TS-850S, TM 241A/
441A, TM-2550A, TR-751A, Kenwood
Service Repair, TM-731A, TS-811A,
TH225A, TM-631A, TM-331A, TS140S,
TS680S, RZ-1, TS-790A, TS950SD,
TH-77A, TH27/47A, TM-941A.

AMPLIFIERS
STOCKED:
RF Concepts
Mirage
TE Systems

MARINE RADIOS
ICOM M5, M56, M700TY, M800
AVIATION PORTABLE ICOM A-20
KING KX-99

Budwig ANT. Products
FLUKE 77, 83, 85, 87 Multimeters

Philips DC 777
Shortwave Cassette Car Receiver

VoCom/Mirage/Alinco
Tokyo Hy-Power/TE SYSTEMS
Amplifiers & 5/8λ HT Gain
Antennas IN STOCK

G&G ELECTRONICS ART1,
Air Disk, SWL, Morse Coach

Professional
Soldering
Station
48 Watts
\$79

METRON
KW HF Mobile
Amplifier
Stocked

Alpha Delta
Products
Stocked

AEA Isopoles
(144, 220, 440
MHz), IsoLoop.



EIMAC
3-500Z
572B, 6JS6C
12BY7A &
6146B

BIRD
Wattmeters &
Elements
In Stock



AOR, AR-1000—wide range,
hand held scanners
Wide selection of SW & Amateur
Publications

Computer Interfaces
Stocked: MFJ-1270B,
MFJ-1274, MFJ-1224, AEA
PK-88, MFJ-1278T, PK-232 MBX
W/FAX, DRSI PRODUCTS



Panasonic

Shortwave Radios/Marine

DAIWA
DIGITAL
WATT
METERS

COMMERCIAL & HAM
REPEATERS
STOCKED.
WRITE FOR
QUOTES

MOTOROLA AUTHORIZED DEALER
KACHINA COMMUNICATIONS DEALER


AUTHORIZED SONY

DEALER
DIGITAL FREQUENCY COUNTERS
OPTOELECTRONICS model 1300 H/A, 0-1300MHz
2210 H, 0-2200 MHz, 2600H, UTC-3000

Long-range Wireless
Telephone for export in stock

BENCHER PADDLES,
BALUNS, LOW PASS FILTERS
IN STOCK

MIRAGE AMPLIFIERS
ASTRON POWER SUPPLIES
Belden Wire & Cable, Int'l Wire
OPTO KEYERS STOCKED



Kantronics
KAM, KPC II,
KPC IV, Data Engine,
DVR 2.2



JRC
NRD-525,
JST135,
NRD-535

Radios for Business,
Gov't, 2-way, etc.
Stocked & serviced,
call for great prices!

COMET ANTENNAS
STOCKED

HEIL
EQUIPMENT
IN STOCK

Media Mentors—
Amateur Radio Course



New TEN-TEC
PARAGON, OMNI V

IIX Towers, Antennas,
Mobile Radio mounts
stocked. Call.

AMERITRON AUTHORIZED DEALER

Hy-Gain Towers
will be shipped
direct to you
FREE of
shipping cost.

For the best buys in town call:
212-925-7000
Los Precios Mas Bajos en Nueva York
WE SHIP WORLDWIDE!




ICOM

IC-R71A, 751A, 781, 229H, R-7000,
IC-765, 275A/H, 3220A, 475A/H, 735,
IC-901, IC725, IC-2400A/2500A

SDI-50
Telephone Interconnect
CES

CES

Simplex Autopatch SDI-50 Will Patch FM
Transceiver To Your Telephone. Great For
Telephone Calls From mobile To Base. Simple
To use. SDI-50, SSI-68.



Connect Systems (CSI)
PRIVATE PATCH V, Duplex 8200,
CS700

TUNERS STOCKED:
NYE MBV-A 3 Kilowatt Tuner



MFJ-989C

Covercraft/Coaxseal Stocked

SHORTWAVE RECEIVERS
STOCKED

MAIL ALL ORDERS TO: BARRY ELECTRONICS CORP., 512 BROADWAY, NEW YORK CITY, NY 10012 (FOUR BLOCKS NORTH OF CANAL ST., BETWEEN SPRING AND BROOME ST.)

New York City's LARGEST STOCKING HAM DEALER
COMPLETE REPAIR LAB ON PREMISES

"Aqui Se Habla Espanol"

BARRY INTERNATIONAL TELEX 12-7670
MERCHANDISE TAKEN ON CONSIGNMENT
FOR TOP PRICES

Monday-Friday 9 A.M. to 6:00 P.M.
Saturday & Sunday 10 A.M. to 5 P.M. (Free Parking)

IRT/LEX—"Spring St. Station". Subways: BMT-
"Prince St. Station", IND—"F" Train-Bwy Station"

Bus: Broadway #6 to Spring St. Path-9th St./6th Ave.
Station.

COMMERCIAL RADIOS
STOCKED: ICOM, Motorola,
MAXON, Standard,
Yaesu. We serve municipa-
lities, businesses, Civil
Defense, etc. Portables,
mobiles, bases, re-
peaters...

ALL
SALES
FINAL

Technical help offered upon purchase

We Stock: AEA, ARRL, Ameco, Ameritron, Antenna Specialists, Astatic,
Astron, B&K, B&W, Benchner, Bird, Butternut, CDE, CES, Cushcraft, Daiwa,
Eimac, Henry, Heil, Hustler, Hy-Gain, Icom, KLM, Kantronics, Larsen, MFJ,
J.W. Miller, Mirage, Nye, Palomar, RF Products, Saxton, Shure, Tempo,
Ten-Tec, TUBES, Yaesu, Vibroplex, Duplexers, Repeaters, Scanners, Radio
Publications, Uniden, Kenwood, Maxon, RFC.

WE NOW STOCK COMMERCIAL COMMUNICATIONS SYSTEMS
HAM DEALER INQUIRES INVITED PHONE IN YOUR ORDER & BE REIMBURSED
COMMERCIAL RADIOS stocked & serviced on premises.

Amateur Radio Courses Given On Our Premises, Call
Export Orders Shipped Immediately. TELEX 12-7670

FAX: 212-925-7001

The response to the premier issue of *Radio Fun* was overwhelming! Frankly, we weren't ready for the number of subscription orders. In order to fulfill our promise, we had to print an extra 10,000 copies of the premier, just to send to pre-publication subscribers.

Judging from my mail, it seems that a magazine like *Radio Fun* is long overdue and much needed. Hundreds of you have taken the time to write and express your support. We love getting your letters, so don't stop writing. Remember . . . it's YOUR magazine. Let us know what you want to see. We can't be everything to everyone in every issue, but if a good idea comes along, we'll do our best to get it into a future issue.

Too Many Ads?

Several letters mentioned that *Radio Fun* seemed to be too full of ads. Actually, the premier issue was exactly 50/50—ads to editorial. This is considered the goal of any magazine, so we were kinda' surprised when about 8 or 10 readers thought we were

too ad heavy. I think the confusion comes from the fact that *Radio Fun* is a tabloid. Since a tabloid's pages are much larger than a regular size magazine (45% larger, to be exact), it allows us to get a bit more creative with the page layout. We tried laying out the pages like "standard" magazines—with whole pages of text and opposing pages of ads—but it looked awful. By using the extra space provided by a tabloid page and placing ads on editorial pages, the magazine looks a lot more exciting. It's not that there are more ads, it's just that we've spaced them out.

Don't worry. The more ads we get, the more editorial pages we'll run. The ratio will always hover around 50/50.

While We're On The Subject Of Ads

Don't forget . . . ads are what pay for a magazine—not subscribers. The subscribers attract the advertisers, so it's really a symbiotic relationship, but the income from ad sales is what pays most of the bills. So, the more advertisers we have, the more editorial pages we can print. An easy way to think of

it is this: every page of advertising buys a page of editorial.

This is where you come in. If you let advertisers know that you saw their ad in *Radio Fun*, they will keep advertising. If you let nonadvertisers know that you read *Radio Fun*, they will start advertising. If you like *Radio Fun* and want it to grow, make a special effort to support the advertisers . . . AND TELL THEM!

We've started including a reader service card in this issue. Right now, before you go any further, find the card and rip it out. Now, as you go through this issue, circle the reader service number of every advertiser whose products you are even mildly interested in. When you get to the end of the magazine, immediately drop the card in the mailbox. Don't wait. Do it now. Many of you are newcomers to amateur radio, so I know that you're just starting to set up your stations. Whether you're into HF, repeaters, satellites, microwaves, ATV . . . anything. You'll find products and retailers advertising in *Radio Fun* who want to send you information.

One of the biggest things influencing an advertiser is reader service response. If they get several hundred requests for information, they know their ad is working. If they get one or two requests, they'll probably start thinking of pulling their ad.

It's up to you.

Gotta' Question?

A lot of you have written with questions. We hope that all of you will feel free to write when you're puzzled by some aspect of ham radio.

To make things easier, try to address your query to a particular author or columnist. Technical questions should go to Michael ("The Tech Side" columnist). Questions about ATV should go to Bill. Questions about licensing should go to Gordon. Feel free to write to any of us, but the columnists already have a forum where they can answer questions: their columns.

We can't always promise a personal response, so your best bet is to address your questions to the person who you think will be able to answer it

quickly. Also . . . columnists are always looking for topics, and your question just might spark a whole column.

Send Photos

We sent out hundreds of free copies of the premier issue to radio clubs and licensing classes. So far I haven't seen a single photo!

We want to run as many photos as we can, so take a picture of your licensing class and send it in. Take a picture of your son/daughter/grandchild/wife/uncle/ holding their new license, and send it in. Take a picture of hams doing fun things and send 'em in.

Infrequent Editorials

You won't hear from me every month. I'd much rather have a construction article here than more racket-jawing from me. Unless I have something of at least minor importance or significance to say, I'll keep this space open for your letters and photos, news items or another article or review.

73 'till next time . . .

Rehab Radio Returns

Rehab Radio returned to Childrens Hospital in Orange County, California, on April 27, 1991. About a dozen young patients took part in the event in the hospital playroom. Using a UHF-to-10 meter link, the kids and their therapists were thrilled by contacts with Johnson Island, Saipan, and Perth, Australia. The young patients were also treated to some leisurely local contacts on 2 meters with KK6YE, N6ZSQ, and several others. TNX WA6OPS via *Westlink Report*, Number 604.

World's Youngest Ham?

Curt Harrington N5HME and his wife Ann N6YGP believe that their daughter Veronica may be the youngest ham licensed in the United States—if not the world. Veronica, age five, has been issued the callsign KC6TQR after passing her Novice test on March 17, 1991.

According to information provided to N5HMS by the ARRL (American Radio Relay League), since 1983 there have only been 11 Novice and one Technician Class licenses issued to kids five years of age or younger. No Novice licenses have been issued in this age group since 1983. This would suggest that Veronica Harrington is the youngest Novice in the United States, and possibly the youngest ham anywhere in the world. TNX *Westlink Report*, Number 603.

Young Hams Take Over!

Editor's Note: Did you QSO anyone on the Youth Net from 0001Z August 3 through 2359Z August 4? If you worked all three stations listed below, the Youth Net has a handsome certificate for you. Send three QSL cards, three contact numbers, and a 9"x12" SASE to Sammy Garrett AAØCR, P.O. Box 5832, St. Louis MO 63134. For one or two contacts, send your QSL cards and contact number(s) with a legal size SASE. Below is the story of how the Youth Net and August Special Event was formed. See the Premier issue of Radio Fun, page 28, for the story of Sammy AAØCR's appointment as the 1991 Westlink Report Young Ham of the Year.

In his *Westlink* column, Sammy AAØCR writes: "During one of my brainstorming sessions with my father, NØMAL, we came up with the idea of an HF Youth Net done for young hams by young hams.

"So I called upon last year's Young Ham of the Year, Mary Alestra KB2IGG, to ask for her comments and suggestions. After a short conversation, we came up with some ideas for the net, and we decided on what we think will be an outstanding kickoff event.

"Mary and I both felt that a Special Event Station celebrating youth in amateur radio would not only make people aware of the new Youth Net, but just might bring some young hams out of the woodwork with the hope of working someone their own age for a change . . . but our goal was also to give everyone, in all parts of the world, an opportunity to work the Special Event Station.

"Our solution: have stations in more than one area of the country. Mary could operate from New York City on the East Coast, and I could operate from St. Louis in the Midwest. But we needed someone else to operate from the West Coast. We turned to young Fullerton, California, DXer Darrel Craig KK6BB, and he enthusiastically agreed to be our third operator."

ARRL DX-QSL Bureau

by John Thompson K6OHM

I have been a volunteer for the ARRL DX-QSL Bureau for about two years, and in that time, I have noticed several things about DX QSLing which may be of help to the readers of *Radio Fun*. For cards being sent to DX stations through the foreign QSL bureaus, the following suggestions may bring success to the card getting to the right ham.

- 1) Fill out the card legibly. Remember the QSL will be read by someone who may not write the call letters the same as we do in the U.S., so be careful not to be sloppy in writing. I have many QSLs from foreign countries that I am still trying to decipher for this very reason.
- 2) Always write the ham's name as given to you in the QSO (first name only is OK) on the QSL card somewhere. I have been able to determine call letters on difficult-to-read QSLs by just seeing the person's name on the card, and being familiar with names and callsigns, I was able to direct the card to the right person.
- 3) Keep at least two envelopes and a couple of extra dollars for excess postage at the bureau for your section. My files are set up to handle at least five envelopes per station and it keeps the storage of cards waiting for envelopes to a minimum if you already have some on file.
- 4) Envelopes mailed to the bureau should be a number 35 or the equivalent 5" x 7 1/2". QSLs are too large for smaller envelopes and larger envelopes don't fit in our files.
- 5) Send envelopes to the bureau with at least the

minimum postage already on them (currently 29 cents). Because we don't know when cards will be received, many envelopes are sent out with five or fewer cards, and having the minimum postage saves the volunteer a lot of time in stamping these envelopes.

- 6) Some people prefer to wait until their envelope has enough cards in it to use the full amount of the postage, while others want any cards received to be mailed to them immediately. If you have a special request, please let the bureau know, and it will be acted upon accordingly.

I really enjoy my monthly volunteer work in distributing QSL cards and I spend about 12–15 hours each time to sort, package, and mail from 2000–3000 cards to more than 600 people. The one side benefit is seeing all the QSLs I missed (Hi!) and touching some rare DX QSLs. Some take a long time to get to the bureau (oldest I've seen was for a QSL 10 years ago!). I envy some operators who have been successful in contacting a sought-after DXpedition, but from seeing these cards, I also learn for my own information what times and frequencies the stations may be operating.

As in many areas of ham radio, Elmers, VECs, League officials, radio club officers, etc., our hobby exists because fellow hams take their personal time to volunteer their skills to the rest of the hams. Your volunteer efforts would be most appreciated in whatever area you feel could use the help the most.

RF

John Thompson K6OHM, 12292 Zig Zag Way, Tustin CA 92680.

Radio Fun

september 1991

issue #2

editor/publisher

Wayne Green W2NSD/1

associate publisher

David Cassidy N1GPH

managing editor

Bill Brown WB8ELK

production editor

Hope Currier

senior editor

Linda Reneau KA1UKM

associate editor

Joyce Sawtelle

contributing editors

Mike Bryce WB8VGE

Michael Geier KB1UM

Carole Perry WB2MGP

Gordon West WB6NOA

advertising sales representatives

Dan Harper

Louise O'Sullivan

account services

Sue Colbert

1-603-525-4201

1-800-225-5083

FAX (603) 525-4423

production manager

William H. Heydolph

art director

Alice Scofield

desktop page make-up

Susan Allen

graphic services

Dale Williams

Terry Verville

graphics photographer

Dan Croteau

wge publishing inc.

chief financial officer

Tim Pelkey

circulation manager

Harvey Chandler

circulation coordinator

Viki Van Valen

editorial offices

Radio Fun

Forest Road, Hancock NH 03449


603-525-4201, FAX (603) 525-4423

Write to Radio Fun WGE Center, Forest Road, Hancock NH 03449.

RADIO FUN (ISSN 1055-887X) is published monthly by Radio Fun, a division of Out to Launch Communications, Inc., Forest Road, Hancock NH 03449. Charter Subscriptions: \$9.95 per year. Canada add \$7.00 plus 70¢ GST. Foreign add \$12.00 surface, \$32.00 airmail. Second class postage pending at Hancock NH and additional mailing offices.

POSTMASTER: Send address corrections to RADIO FUN, P.O. Box 4926, Manchester NH 03108.

Entire contents ©1991 by Radio Fun. No part of this publication may be reproduced without written permission from the publisher.



letters

Larry Woram VE3WLN, Ogdensburg NY I would like to take this opportunity to thank you for your excellent magazine, 73, and for having the insight to publish *Radio Fun*. I look forward to receiving my subscription to it as well.

As a recently elected member of the executive [part] of the Ottawa Valley Mobile Radio Club, the other members and I are actively working towards promoting amateur radio as a hobby for all ages, with emphasis on youth. We also recognize the need to provide support to those who are newly licensed, to ensure that they are not left on their own and lose interest. We feel that *Radio Fun* may be just the vehicle to help accomplish these goals.

Frank Coop KA0QQR, Newton KS I found *Radio Fun* interesting and informative. Congratulations—a publication such as this was long overdue. But why so many ads? Do you really need all of them?

When you publish a photo of a person's shack, why not also add a note calling out the main items of gear? I'm sure many hams would find it very useful. I know I would. Besides, it would save me from having to count knobs and dials! I even get a tad touchy when the photo isn't distinct enough for counting.

Frank, advertisers not only serve readers by keeping them informed on what's available in the market, they also pay for most of the costs of publishing a magazine. To pay for itself, a magazine generally needs to be about half ads, half editorial. Or would you rather pay a few hundred dollars (maybe more) for a subscription to a magazine without ads?—Eds.

Doug KL4RSL, Athens GA Thanks for the always fantastic 73, and thanks for what looks like a future winner—*Radio Fun*! In case you're looking for suggestions, how about some articles on nets (both code and voice) and how to get involved?

Warren Rowe N5TFL, Temple TX I received the premier issue of *Radio Fun* just recently. I am IMPRESSED! It is exactly like you advertised it to be: for the Novice/Technician class license operators. I applaud your efforts, and will support this magazine as long as it's in print.

I have two ideas for upcoming articles in *Radio Fun*. One is to explain the procedure by which licenses are given out. The second idea is to maybe come up with a special segment for "Elmer of the Month." And how about an article on storm-spotting and weather nets?

Jerry Haislip, Roanoke VA Just received my premier issue of *Radio Fun*. Needless to say, I was excited to get the first issue, and have read it from cover to cover, enjoying each page. After waiting 30 years to get the time and means, I have now decided to give amateur radio a try. The code might have been a deterrent in my younger days, but I've started my new hobby with the code tapes anyway. I like the

idea of the no-code Technician license, and it's likely what guided my interest back to amateur radio after all these years. I'm looking forward to each issue of *Radio Fun* and having a call-sign to put behind my name.

Vernon Heglund KB0IGS/KT I thank the good Lord for people like you, Wayne Green and staff, for remembering us new hams, and publishing a magazine for us. I met my wife Barbara on the 2 meter band in Minneapolis 37 years ago when I visited a friend who was a ham (W00FY). We tuned up his rig one night, and heard these two ladies on the band—talked with them, and then went over to see what kind of ham rig they had. I ended up marrying Barbara 6 1/2 months later. Barbara was visiting a friend who was a ham (W0PYC), too.

After our marriage, we got busy building a home together and raising a family, and made a few attempts to get our Novice tickets, but just didn't have the right timing. Just before retirement this year, I was challenged by a ham at work, and after six months of study, on and off, I purchased Gordon West's Radio Shack materials and found an elmer. I should have my General class by year's end. I feel like you folks have welcomed my wife and me to ham radio with your first issue of *Radio Fun*.

Andrew Eschenauer I'd like to say that one can't have enough product reviews in a magazine. I love reading reviews. And anything about antennas, feedlines, connectors. I'd like to see a nice article on attaching various connectors (F, BNC, TNC, PL, etc.) to various coax cables. And I've never seen an informative article on exactly how much signal loss there is when using connector adapters. Or a comparison of standard vs gold adapters. If you could come up with an article like that, heck, I'd eat it up!

Dellena Montano KC6TIO, Downey CA I just received my no-code Tech license in February. One older ham made a sour face when I told her that I'm no-code, but it didn't hurt my feelings. Anyway, I'm studying code and really enjoying it. I probably never would have gotten into the hobby the old way because I thought code was too hard (my husband has an advanced license). But my 15-year-old daughter and I went to Gordon West's class and enjoyed it so much (and passed) that I really got interested. I passed the General theory in March, and am now beating my brains out learning the code. I have the Advanced theory book, too.

I have my first issue of *Radio Fun* and wanted to share my ideas with you. I would really like to see a page for women in radio (I'm 47, no previous technical interests), a page all about the kids who have become hams, and some articles on "the most fun I've had as a ham." Maybe "Ham Pals" (like penpals). Funny stories would be good, too. Pictures, diagrams, and charts of ham shacks would be great.

RF

MFJ's world famous Ham Radio Accessories

Why do more hams throughout the world use MFJ accessories than any other brand? Because they are value packed and carry MFJ's one year unconditional guarantee!

MFJ Speaker Mics

Compact or miniature models for all popular HTs

Compact Speaker Mics, \$24.95 each:

Once you try an MFJ Speaker Mic you'll never want to be without it. You'll be able to carry your handheld on your belt and never have to remove it to monitor calls or talk.

You'll never have to turn up your audio annoyingly loud to monitor calls because it's handy lapel/pocket clip lets you keep it close to your ear for easy listening.

And you'll never have to clumsily remove your handheld from your belt holder to talk because you can conveniently take the speaker mic in one hand, press the push to talk button and talk. Measure 1 1/4" x 2" x 3"


They come with a lightweight retractable cord that eliminates the dangling cord problem. They feature excellent audio on both transmit and receive. MFJ-284 for Icom or Yaesu; MFJ-286 for Kenwood.

Miniature Speaker Mics, \$24.95 each:

New miniature speaker mics pack all the features of the compact models into a tiny 2" x 1 1/4" x 1/4" package. The lapel pocket clip swivels for even more convenient positioning. Also features transmit LED. Choose from regular or "L" shaped connector. Order MFJ-285 or MFJ-285L for Icom or Yaesu, MFJ-287 or MFJ-287L for Kenwood. MFJ-283 for dual plug Alinco.

MFJ-284 or MFJ-286

\$24.95



MFJ-283, MFJ-285, MFJ-285L, MFJ-287 or MFJ-287L

\$24.95



Deluxe 300 W Tuner



MFJ-949D

\$149.95

MFJ-949D is the world's most popular 300 watt PEP tuner. It covers 1.8-30 MHz, gives you a new peak and average reading Cross-Needle SWR/Wattmeter, built-in dummy load, 6 position antenna switch and 4:1 balun -- in a compact 10 x 3 x 7 inch cabinet. Meter lamp uses 12 VDC or 110 VAC with MFJ-1312, \$12.95.

SWR Analyzer

MFJ-207

\$99.95

MFJ's innovative new SWR Analyzer gives you a complete picture of your antenna SWR over an entire band -- without a transmitter, SWR meter or any other equipment!

Simply plug your antenna into the coax connector, set your SWR Analyzer to the frequency you want and read your SWR. You can instantly find your antenna's true resonant frequency, something a noise bridge can't do. Covers 1.8-30 MHz (or choose MFJ-208, \$89.95 for 2 Meters). Use 9 V battery or 110 VAC with MFJ-1312, \$12.95.

VHF SWR/Wattmeter

MFJ-812B

\$29.95

Covers 2 Meters and 220 MHz. 30 or 300 Watt scales. Also reads relative field strength 1-170 MHz and SWR above 14 MHz. 4 1/2 x 2 1/4 x 3 in.


MFJ Multiple DC Outlet

MFJ-1112

\$29.95

New MFJ DC Power Outlet saves you space and money. Hook it to your 12 VDC power supply and get 6 DC outlets for connecting your accessories. RF bypassing keeps RF out of power supply from DC line outlet. 13 1/2 x 2 3/4 x 2 1/2 in.

12/24 Hour LCD Clocks



\$19.95 MFJ-108B \$9.95 MFJ-107B

Huge 5/8 inch bold LCD digits let you see the time from anywhere in your shack. Choose from the dual clock that has separate UTC/local time display or the single 24 hour ham clock.

Mounted in a brushed aluminum frame. Easy to set. The world's most popular ham clocks for accurate logs. MFJ-108B 4 1/2 x 1 x 2; MFJ-107B 2 1/4 x 1 x 2 in.

MFJ Cross-Needle SWR/Wattmeter

MFJ-815B

\$69.95

MFJ Cross-Needle SWR/Wattmeter has a new peak reading function! It shows you SWR, forward and reflected power in 2000/500 and 200/50 watt ranges. Covers 1.8-30 MHz.

Mechanical zero adjusts for movement. SO-239 connectors. Lamp uses 12 VDC or 110 VAC with MFJ-1312, \$12.95.

Deluxe Code Practice Oscillator

MFJ-557

\$24.95

MFJ-557 Deluxe Code Practice Oscillator has a Morse key and oscillator unit mounted together on a heavy steel base so it stays put on your table. Portable because it runs on a 9-volt battery (not included) or an AC adapter (\$12.95) that plugs into a jack on the side.

Tone and Volume controls for a wide range of sound. Speaker, earphone jack. Key has adjustable contacts and can be hooked to transmitter. 8 1/2 x 2 1/4 x 3 3/4 in.

Nearest Dealer/Orders: 800-647-1800

MFJ ENTERPRISES, INC.

Box 494, Miss. State, MS 39762

(601) 323-5869; FAX: (601) 323-6551

TELEX: 53 4590 MFJ STKV

• One year unconditional guarantee • 30 day money back guarantee (less s/h) on orders from MFJ • Add \$5.00 each s/h • FREE catalog

MFJ... making quality affordable

Collect Those QSL Cards—

Decorate Your Shack with Awards

by Frank L. Striegl 7J1AAL/KA2TNZ

Collecting awards is interesting and fun. Literally hundreds of clubs and radio organizations worldwide offer thousands of different certificates,

a little, and state that you meet the requirements for a particular award when in reality you don't. Nobody else would know, but you have to live

specific geographical or political region by working members of a club, working stations within a specified time period, or by spelling out a certain phrase with first/last letters of the calls of stations worked. Some of these awards are very easy to get, while others are more challenging. How about working the same five DXCC stations each on five different bands, for a total of 25 contacts? Try it. It takes time. Or spell "Amateurfunk Bruecke zur Welt" with the tail letters of QSLs you have. Work five HL9s in the same mode. Work stations in countries through which Marco Polo passed en route to China. Work Jordan's King Hussein (JY1) and 10 other Arab nations, and you can receive a beautiful certificate. Help three hams put up their antennas and you can get an award for it. Spell out your callsign with the

you closer to the awards you are chasing.

Applying: Once you have met the

confirmed. This is your GCR. Have two fellow amateurs certify that you have the cards in your possession by signing and dating the form on the bottom. Some awards directories (K1BV, for example) have a form already made up for you, and all you have to do is make copies and fill them out.

Be careful: For a few awards (DXCC, WPX), you must send the QSLs in for verification. For other awards, DO NOT send your cards in un-



plaques, trophies, pennants, and other ham memorabilia if you meet the requirements of their specific award. An award may be easy to get, by simply working and confirming a few stations, or it may take years to achieve because that one last QSL is long in coming.

The premiere award for hams worldwide is the DXCC. But did you know that when you meet the requirements for this award, you also become eligible for several other awards? 73's DX Dynasty Award, a beautiful certificate, is one among several others you can get for just working and confirming 100 or 101 countries: 101 Award (LU), United Nations Award (USA), etc.

Interested? You can start by working DX. Work lots of DX, and religiously QSL all your contacts. As the months go by, you'll start filling up your shoebox.

Proof of contacts: Almost all awards (with few exceptions, such as the ARRL Golden Jubilee Award in 1987) require you to actually have in your possession the QSLs you are using to claim the award. The fact that you have the QSLs must be certified, in most cases by two fellow hams. This practice is known as the General Certification Rule, or GCR. In the case of a few awards, the GCR list must be certified by your national radio organization, i.e., the ARRL. Award rules usually state the requirements quite clearly.

Honor: Like fishing, it seems it would be possible to stretch the truth

with yourself. It's simply dishonest to falsely claim an award you don't deserve.

Requirements: Generally, you can get awards for working stations in a

tail letters of ham and SWL stations and get a certificate. Collect 10 different awards and you can receive an award for that, too!

Keeping track: The list goes on and on. But how can you remember which awards you are following? If you are only chasing a few, there is little problem. Since getting interested in awards two years ago, I tracked my progress on over 100 awards, and have found that a loose leaf notebook, with a separate sheet for each award being tracked, is very useful. A brief note about the requirements for the award, along with a list of the stations worked (in pencil) and confirmed (in ink) will keep you up to date on how close you are to applying for the award. When your QSLs come in, you just make ink entries of your QSLs on the appropriate awards page to see which ones will bring

Tony Rycko
53 Buckingham Drive
Jackson, New Jersey 08527
U.S.A.

Ocean County

KAZUFO

QSO WITH	CONFIRMING QSO						
	MONTH	DAY	YEAR	GMT	MC.	RST	2 WAY

73 Amateur Radio Today

DX DYNASTY AWARD

Number 2

This certifies that Amateur Radio Station
WB2DIN


Has submitted evidence of confirmed contact via Amateur Radio with **350** countries as defined by the DX Dynasty Countries List.

Signed: *Wayne Grew*

Date issued: *12 July 1991*

Endorsements: *1st Award for 350 countries*

Bob Reed WB2DIN has managed 73's DXDA Awards Dynasty for more than five years!



less the rules specifically tell you that you must. Usually a GCR will suffice. If you must send the QSLs (and these took you months, maybe years, to accumulate, remember?), be sure to send them by registered mail, and to include enough payment for return postage so that you can count on them being returned to you.

Sending in the award application: Usually there is a nominal fee for each award. IRCs are the easiest method of payment, and the number required for the award (anywhere from 5 to 10) is noted in the award rules. Green stamps also work for payment in some countries. When I am out of IRCs, green stamps work fine, although it is riskier to send them through the mail, and even illegal in some countries. With your GCR statement, payment, and a brief cover letter, you can now mail your application. Sometimes a sticker with your mailing address on it, if large enough, will also help the awards manager in getting your application processed sooner. If you are sending payment to a country where you think the reliability of the postal system is questionable, you are better off sending your application packet by registered mail. You can even have the post office send you a postcard advising you when the letter was delivered. This is called an "avis de reception" (A.R.) in many countries.

For some obscure awards, especially the overseas ones, you might find it a good investment to check with the award manager by postcard, just to

XE3EB

MEXICO

ITU ZONE 10
CQ ZONE 6
GRID EL51

CONFIRMING QSO WITH	DATE	UTC	MHz	RST	MODE 2x

PSE QSL 73.

Emilio Berny P.O. Box 309 Mérida, Yuc., 97000

TURKEY

TA1AC

ISTANBUL - EUROPE

ZONE: 20

confirm that the award is still available and that he/she is still the current manager. Information becomes quickly out of date in award directories.

Waiting: Award managers are hams, and receive no pay for their efforts. They also have to work for a living, have families, friends, and all the other concerns that we all have in our daily routines. What this means is that they will do their level best to get your award out to you as soon as possible, although sometimes it takes a while to get the awards signed (you wouldn't want an unsigned one, would you?) and prepared for mailing. After all, ham radio is just a hobby. Delays are sometimes inevitable. If this happens, be patient. If there is still no news (some DX awards can take up to six months), a follow-up letter would be in order.

Sources of information: The *K1BV DX Awards Directory* is the most comprehensive I have seen. Published annually, the 1991 edition contains over 1700 awards available worldwide, many of them from exotic DXCC QTHs. In an effort to keep entries current, award managers who do not reply to inquiries after a few tries are dropped from the listing. For U.S. addresses especially, it's well worth the \$17.50 charged. The cost for Europe, Africa and S. America is \$22 airmail; for Asia, Oceania and the USSR the price is \$25 airmail. Shipment to any DX location by sea is \$16. There are 243 pages. Write K1BV DX Awards Directory, Ted Melinosky, K1BV, P.O. Box 960, Keene NH 03431-0960.

A unique type of directory is *The International Awards Guide Book*, published by YBØWR. Cost is rather steep



at \$37 by air, but then all pages are in color, with illustrations of almost all of the 750 awards it lists. Mr. Lumban Gaol is a printer by profession, so I am sure that publishing this 422-page directory is a labor of love. The International Awards Guide Book, M.S. Lumban Gaol, YBØWR, Jl. Garuda No. 62, Jakarta 10620, INDONESIA.

The Radio Society of Great Britain (RSGB) publishes *Amateur Radio Awards*, listing some of the major awards available. Area maps, as well as illustrations of the awards, are given. Cost was \$12, but I have no idea what the current price is. ISBN: 0 900612 49 5, 80 pages. Write Amateur Radio Awards, RSGB, 35 Doughty Street, London WC1N 2AE, ENGLAND.

The Award Hunter's Guide, published by the Japanese *CQ Ham Radio* magazine, is worth noting here because it lists many Japanese awards

that most hams in the world don't know about. Over 500 awards are listed, many illustrated in color. Although an excellent guide, it is, unfortunately, 95% in Japanese. It costs the current equivalent of about \$12, plus about

\$8 for airmail (\$3.50 for surface) postage. If you cannot get a copy of this guide locally, contact me at my callbook address, and I will try to help you. 212 pages.

Another interesting source of information is the "DXNS" series of pamphlets published by Geoff Watts, editor of the "DX News Sheet" from 1962-1982. Geoff has four very comprehensive lists: the CQ and ITU Zones Guide, USSR Oblast Guide, DXCC Countries Guide, and Radio Amateur Prefix-Country-Zone List. The ITU zones list is useful in that it will help you keep track of which zones you have confirmed for the ITU WAZ award. Write DXNS Guides, Geoff Watts, 62 Belmore Road, Norwich, NR70PU, ENGLAND.

Now, what are you waiting for? Start working DX and get started on those QSLs! **RF**

Frank L. Striegl, 4-39-7-503 Kaminoge, Setagaya-ku, Tokyo 158 JAPAN.

TNT The No-Tune Windom Antennas

complete, assembled, ready to use

No pruning.
TNT is No-Tune on 80 cw, 40, 20, 17, 12, 10. TNT/2 is No-tune on 40, 20, 10. Work other bands w/ tuner. DX & Gain rise w/ frequency. Ready to Use Now
Includes Custom 99 ft. RG-8x feedline
Plans, patterns, data: WindomTechNote #126 \$6.95 ppd USA
Tech Supt: 801-373-8425

No tuning.
Kink-Proof Wx-Sealed Low Noise

No knobs to twist.
No Traps or Resistors Insulated to 3000 V Rated 500 Watts

AntennasWest
Box 50062F, Provo, UT 84605

TNT Windom \$89.95 +\$8 P&H
135 ft. long

TNT/2 Windom \$79.95 +\$7 P&H
67 ft. long

Order Hotline 800-926-7373

The TNT secret? Feed a resonant antenna off center at a constant impedance point. Result: broad, low SWR curves, & No-tune band-switching on harmonically related bands.

New: Custom 2KW TNTs--add \$70

CIRCLE 5 ON READER SERVICE CARD

AEA
ASTRON
BUTTERNUT
CALLBOOK
COMET
DIAMOND
HUSTLER
KANTRONICS
LASER
COMPUTERS
MFJ
RADIO SHACK
SMILEY
ANTENNAS
TEN-TEC
VALOR
ANTENNAS
& more.

Small town
service with
discount prices.
DANDYS
120 N. Washington
Wellington, KS 67152
(316) 326-6314

CIRCLE 130 ON READER SERVICE CARD

• B & W • BENCHER • BUTTERNUT • CUSHCRAFT • DIAMOND • HUSTLER • HYGAIN • ICOM • KANTRONICS •

Michigan Radio

SALES SERVICE

15000 E. 9 MILE RD. EAST DETROIT, MI 48021
OPEN MON-FRI 10-6, SATURDAY 10-4

KENWOOD

HT'S MODEL	DESCRIPTION	LIST	OURS
TH-205A	2M 2.5W AFFORDABLE	314.95	CALL
TH-225A	2M 5W SCANNING DEL	399.95	CALL
TH-26AT	2M 2.5W MINI 15MEM	369.95	CALL
TH-27A	2M 2.5W MICRO 40ME	419.95	CALL
TH-47A	70CM 2.5W MICRO	429.95	CALL
TH-415	70CM 2W SCANNING DEL	419.95	CALL
TH-77A	2M/70CM DEL DUAL B	599.95	CALL

MOBILE VHF/UHF MODEL	DESCRIPTION	LIST	OURS
TM-241A	2M 45W PROG MIC	469.95	CALL
TM-2530A	2M 25W DELUXE	499.95	CALL
TM-2550A	2M 45W DELUXE	519.95	CALL
TM-331A	220MHZ 25W PROG MIC	469.95	CALL
TM-441A	440MHZ 25W PROG MIC	479.95	CALL
TM-631A	2M/220MHZ DUAL BAND	749.95	CALL
TM-731A	2M/440MHZ DUAL BAND	749.95	CALL
TM-941	2M/440M/1.2 TRI-BAN	1199.95	CALL
TM-751A	2M 25W ALL-MODE	699.95	CALL
TM-851A	70CM 25W ALL-MODE	771.95	CALL
TS-711A	2M 25W ALLMODE BASE	1059.95	CALL
TS-790A	2M/70CM SATELLITE	1999.95	CALL

HF EQUIPMENT MODEL	DESCRIPTION	LIST	OURS
TS-140S	HF COMP GEN COV	949.95	CALL
TS-690S	HF/6M COMP GEN COV	1549.95	CALL
TS-450S	HF DELUXE COMP	1349.95	CALL
TS-440/AT	HFDEL COMP TUNR	1549.95	CALL
TS-850S	HF 12V DEL DDS	1699.95	CALL
TS-850/AT	HF 12V DEL TUNR	1899.95	CALL
TS-950S	HF BASIC VERSION	3299.95	CALL
TS-950SD	HF THE DX MACHINE!	4399.95	CALL

WE STOCK A FULL LINE OF ACCESSORIES
FOR THE KENWOOD LINES. CALL FOR OUR DISCOUNTED PRICES!
1-800-TRU-HAMS

TERMS:
Prices Do Not Include Shipping.
Price and Availability Subject to
Change Without Notice
Most Orders Shipped The Same Day
COD's Welcome (\$4.00 + shipping)

ICOM

HT'S MODEL	DESCRIPTION	LIST	OURS!
IC-02AT	2M 5W 10MEM DTMF	409.00	CALL
IC-2GAT	2M 7W 15MEM DTMF	429.00	CALL
IC-2SAT	2M 2.5W DEL MICRO	439.00	CALL
IC-24AT	2M/70CM DEL MICRO	499.95	CALL
IC-32AT	2M/70CM 6W 20MEM	629.00	CALL
IC-3SAT	220M 2.5W MICRO	449.00	CALL
IC-4SAT	70CM 2.5W MICRO	449.00	CALL
IC-4GAT	70CM 7W 15MEM DTMF	449.00	CALL
IC-W2A	2M/70CM DUAL MICRO	629.00	CALL

MOBILE VHF/UHF MODEL	DESCRIPTION	LIST	OURS!
IC-229A	2M FM, 25W 20MEM	449.00	CALL
IC-229H	2M FM, 45W 20MEM	479.00	CALL
IC-3220A	2M/70CM 25W 40MEM	659.00	CALL
IC-3220H	2M/70CM 45W 40MEM	699.00	CALL
IC-2410	2M/70CM 45W DEL.	TBA	CALL

HF EQUIPMENT MODEL	DESCRIPTION	LIST	OURS!
IC-725	HF COMPACT GEN COV	949.00	CALL
IC-726	HF/6M COMP GEN COV	1299.00	CALL
IC-735	HF DELUXE COMPACT	1149.00	CALL
IC-751A	HF 12V BASE TXCR	1699.00	CALL
IC-765	HF DELUXE TNR, PS	3149.00	CALL
IC-781	HF DX'ERS DELIGHT	6149.00	CALL

WE STOCK A FULL LINE OF ACCESSORIES
FOR THE ICOM LINES. CALL FOR OUR DISCOUNTED PRICES!
1-800-TRU-HAMS

**ORDERS
IN-STATE
SERVICE
FAX SERVICE**

**1-800-TRU-HAMM
1-313-771-4711
1-313-771-4712
1-313-771-6546**

WANTED: QUALITY USED GEAR, CASH OR TRADE



YAESU

HT'S MODEL	DESCRIPTION	LIST	OURS
FT-411E	2M 2.5W 50MEM CTCSS	405.00	CALL
FT-811	70CM 2.5W 50MEM	405.00	CALL
FT-470	2M/70CM 2.5W 50MEM	491.00	CALL
FT-26	2M-5W WITH/DTMS PAGING	349.00	CALL
FT-76	440MHZ-5W WITH/DTMS PAGING	359.00	CALL

MOBILE VHF/UHF MODEL	DESCRIPTION	LIST	OURS
FT-290RH	2M 25W ALL-MODE	610.00	CALL
FT-4700RH	2M/70CM REMOTE HEAD	799.00	CALL
FT-736R	2M/70CM 220/1.2 SAT	1922.00	CALL
FT-5200	2M/70CM DUAL BAND	749.00	CALL
FT-6200	70CM/1.2 DUAL BAND	899.00	CALL
FT-2400H	2M 50W, LCD, CTCSS	419.00	CALL

HF EQUIPMENT MODEL	DESCRIPTION	LIST	OURS
FT-747GX	HF LGTWTG MOBILE	889.00	CALL
FT-757GXII	HF COMP GEN COV	1089.00	CALL
FT-767GX	HF 21/220/70C TUNR	2299.00	CALL
FT-990	HF 12V DEL TUNR +	2399.00	CALL
FT-1000B	HF BASIC VERSION	3399.00	CALL
FT-1000D	HF QSL CATCHER!!	4399.00	CALL

WE STOCK A FULL LINE OF ACCESSORIES
FOR THE YAESU LINES. CALL FOR OUR DISCOUNTED
PRICES! 1-800-TRU-HAMS

TEN-TEC


HF EQUIPMENT—AMERICAN MADE MODEL	DESCRIPTION	LIST	OURS
OMNI IV	HF 9 BAND TXCVR	2245.00	CALL
PARAGON	HF GEN COV TXCVR	2245.00	CALL

AEA • ALINCO • ASTRON • ALPHA-DELTA • AMERITRON • ANTENNA SPEC

KENWOOD • LARSEN • MFJ • MIRAGE/KLM • RF CONCEPTS • TEN-TEC • YAESU

• BUTTERNUT • CUSHCRAFT • KENWOOD • LARSEN • MFJ • AEA • ALINCO • TEN-TEC • YAESU • ICOM •

THE GREAT MOBILE PEAR



THE TEXAS BUGCATCHER HF Mobile Antenna System

- Hi Q air-wound coils
- Minimum SWR—excellent performance on all HF bands
- Easy assembly to meet almost any configuration
- Fits standard 3/8-24 SAE mounts
- Various length base masts & whips available

Henry Allen WB5TYD
214-388-4724 8 am-4 pm weekdays
903-527-4163 evenings & weekends

Send for free brochure!

GLA Systems
PO Box 425

Caddo Mills, TX 75005

COMET

CPR-5800

Dual-Bander 146/446MHz
Gold plated center conductor
for excellent electrical efficiency!

Wave Length: 146MHz 7/8 Wave
446MHz 5/8 Wx3

Gain: 146MHz 5.0dB
446MHz 7.6dB

Impedance: 50 ohms

VSWR: 1.5:1 or less

Max. Power: 120 watts

Length: 5'

Connector: UHF

Two Meter Quad

Or any meter, for that matter . . .

by Joel Fream WA6HNO

The quad antenna is cheap, clean, easy and effective. Many of the problems that the amateur must deal with when building an antenna system do not exist with the quad. No impedance matching is required, and the spacing of the elements is not critical, yet the performance is as good as or better than other systems of similar size.

The driven element is one wavelength long. This is true for any band you want to operate on. On 80 meters, it's a little hard to hold up—264 feet

a more reasonable 82 inches long, or 20.5 inches on each side. Keep in mind that the driven element is one wavelength, and that you can build a quad for any frequency you choose. The formula is $L_{FT} = 984 \div F_{MHz}$.

The driven element is the element of the antenna that connects directly to the feedline. In our quad, the driven element is fed with 50 ohm coax, which is really nice for the modern ham with his commercial radio designed for 50 ohms. Therefore, no

Element spacing will, however, affect the impedance of the array. SWR (standing wave ratio) adjustments can be made by changing the spacing. For 2 meters, an element spacing of 14 inches should provide an acceptable match at 50 ohms.

Directors

You can add directors to the array with little trouble. Directors are elements added in front of the driven element. Sometimes they are called

"parasitic" elements. The purpose of directors is to increase radiation.

They should be spaced like the directors on yagi antennas—slightly closer than the reflector—and they should be 5% shorter in length than the driven element.

A Round Quad?

Although you might imagine a quad to be square or diamond-shaped, it can also be round. A round quad is called a "loop" antenna. The loop




Figure 1. Overall view of the 2-element quad for 2 meters. The feedline attachment point is a female connector (SO-239 or BNC) mounted on the bottom of the driven element cross piece as shown.

is one wavelength long. impedance matching is required. You can construct the elements out of small copper tubing or large, solid copper wire, and mount them on a 1" x 1" (for 2 meters) wooden frame.

The reflector

The reflector is one wavelength plus 5%, or $82 \times 1.05 = 86$. If you're quick with math and can see that the answer is really 86.1, remember that the quad is a noncritical, broadband antenna, and you don't need to be accurate to that degree.

The Reflector

The reflector is not connected to anything; it is a closed loop hanging

is one wavelength long.

Feeding the Quad

The polarization of a quad is determined by the feedpoint placement. If it's fed on the side, it will have vertical polarization; if fed on the top or bottom (as shown in the figure), it will have horizontal polarization.

Most communications on the HF Novice bands use horizontal polarization. On VHF and UHF, most communications use vertical polarization, especially when working through a repeater.

As with all other factors of the quad,




Figure 2. Detailed view of the quad's coax feedpoint (driven element).

in free space. But you must make sure that it forms a complete loop. It must have a good electrical connection where it is connected to itself. You can solder it or use screws.

Spacing

The spacing is not critical, either. It does not greatly affect gain. Normally, the spacing will be from 0.15 to 0.25 wavelengths.

polarization is forgiving. Long-path fading due to a change in polarization is much less of a problem than it can be with other antennas.

The quad is a fun antenna. Enjoy it!

RF

Joel Fream WA6HNO at P.O.B. 1893, Broken Arrow OK 74013. Reprinted from the November 1990 issue of Ham News Outlet.

Don't Climb!

Launch antennas the easy way.

QRV-QL Quick-Launch Antenna Installation System

One person installs in minutes.

Info \$1

Re-usable Ready for Action Fast & Easy to Use Eliminates Climbing

\$29.95 add \$5 UPS Ship

1-800-926-7373 Order Hotline

AntennasWest
Box 50062E, Provo, UT 84605

CIRCLE 90 ON READER SERVICE CARD



AMSAT

Dedicated to Keeping Amateur Radio in Space!

AMSAT—The Radio Amateur Satellite Corporation is an organization of Radio Amateurs who design, build and launch satellites for use by Radio Amateurs around the world.

Your new Amateur Radio License will be your ticket to a whole world of exciting opportunities. Why not expand your horizons even further by becoming a member of AMSAT and participating in space aged Amateur Radio?

Join the Excitement! Join the Fun! Join AMSAT!

Yearly Membership dues: \$30 U.S., \$36 Canada/Mexico, \$45 Elsewhere JOIN NOW!

Name _____ Call _____


Address _____

City _____ State _____ Zip _____

\$15 of membership dues goes toward a subscription to *The AMSAT Journal*

Post Office Box 27, Washington, DC 20044
Telephone 301-589-6062 Fax 301-608-3410

RAMSEY ELECTRONICS



COM-3
\$279500

2 WAY RADIO SERVICE MONITOR

COM-3, the world's most popular low-cost service monitor. For shops big or small, the COM-3 delivers advanced capabilities for a fantastic price—and our new lease program allows you to own a COM-3 for less than \$3.00 a day. Features •Direct entry keyboard with programmable memory •Audio & transmitter frequency counter •LED bar graph frequency/error deviation display •0.1–10,000 µV output levels •High receive sensitivity, less than 5 µV •100 kHz to 999.9995 MHz •Continuous frequency coverage •Transmit protection, up to 100 watts •CTS tone encoder, 1 kHz and external modulation.



RSG-10
\$249500

SYNTHESIZED SIGNAL GENERATOR

Finally, a low-cost lab quality signal generator—a true alternative to the \$7,000 generators. The RSG-10 is a hard working, but easy to use generator ideal for the lab as well as for production test. Lease it for less than \$3.00 a day. Features •100 kHz to 999 MHz •100 Hz resolution to 500 MHz, 200 Hz above •–130 to +10 dBm output range •0.1 dB output resolution •AM and FM modulation •20 programmable memories •Output selection in volts, dB, dBm with instant conversion between units •RF output reverse power protected •LED display of all parameters—no analog guesswork!

FREQUENCY COUNTERS

CT-70 7 DIGIT 525 MHz



CT-90 9 DIGIT 600 MHz



CT-125 9 DIGIT 1.2 GHz



Ramsey Electronics has been manufacturing electronic test gear for over 10 years and is recognized for its lab quality products at breakthrough prices. All of our counters carry a full one-year warranty on parts and labor. We take great pride in being the largest manufacturer of low-cost counters in the entire U.S.A. Compare specifications. Our counters are full-featured, from audio to UHF, with FET high impedance input, proper wave shaping circuitry, and durable high quality epoxy glass plated-thru PC board construction. All units are 100% manufactured in the U.S.A. All counters feature 1.0 ppm accuracy.


NEW CT-250 2.5 GHz

ACCESSORIES FOR COUNTERS

Telescopic ship antenna—BNC plug, WA-10 \$11.95
High impedance probe, light loading, HP-1 \$16.95
Low-pass probe, audio use, LP-1 \$16.95
Direct probe, general purpose use, DC-1 \$16.95
Tilt bail, elevates counter for easy viewing, TB-70 \$9.95
Rechargeable internal battery pack, BP-4 \$9.95
CT-90 oven timebase, 0.1 ppm accuracy, OV-1 \$9.95


ALL COUNTERS ARE FULLY WIRED & TESTED

MODEL	FREQ. RANGE	SENSITIVITY	DIGITS	RESOLUTION	PRICE
CT-50	20 Hz–600 MHz	<25 mV to 500 MHz	8	1 Hz, 10 Hz	\$189.95
CT-70	20 Hz–550 MHz	<50 mV to 150 MHz	7	1 Hz, 10 Hz, 100 Hz	\$139.95
CT-90	10 Hz–600 MHz	<10 mV to 150 MHz <150 mV to 600 MHz	9	0.1 Hz, 10 Hz, 100 Hz	\$169.95
CT-125	10 Hz–1.25 GHz	<25 mV to 50 MHz <15 mV to 500 MHz <100 mV to 1 GHz	9	0.1 Hz, 1 Hz, 10 Hz	\$189.95
CT-250	10 Hz–2.5 GHz typically 3.0 GHz	<25 mV to 50 MHz <10 mV to 1 GHz <50 mV to 2.5 GHz	9	0.1 Hz, 1 Hz, 10 Hz	\$239.95
PS10B Prescaler	10 MHz–1.5 GHz, divide by 1000	<50 mV	Convert your existing counter to 1.5 GHz		\$89.95



SPEEDY
SPEED RADAR
\$89.95
complete kit
SG-7

New low-cost microwave Doppler radar kit "clocks" cars, planes, boats, horses, bikes or any large moving object. Operates at 2.6 GHz with up to 1/4 mile range. LED digital readout displays speed in miles per hour, kilometers per hour or feet per second! Earphone output allows for listening to actual doppler shift. Uses two 1-lb coffee cans for antenna (not included) and runs on 12 VDC. Easy to build—all microwave circuitry is PC stripline. Kit includes delivery. ABS plastic case with speedy graphics for a professional look. A very useful and full-of-fun kit.




**BROADBAND
PREAMP**

Boost those weak signals to your scanner, TV, shortwave radio or frequency counter. Flat 25 dB gain, 1 to 1000 MHz. 3 dB NF. BNC connectors. Runs on 12 VDC or 110 VAC. PR-2, wired, includes AC adapter \$59.95

2M POWER AMP

Easy to build power amp has 8 times power gain, 1W in, 8W out, 2W in, 16W out, 5W is for 40W out. Same amp as featured in many ham magazine articles. Complete with all parts, less case and T-R relay. PA-1, 40W pwr amp kit \$29.95
TR-1, RF sensed T-R relay kit \$8.95



**FM WIRELESS
MIKE KITS**

Pick the unit that's right for you. All units transmit stable signal in 88–108 MHz FM band up to 300' except for hi power FM-4 that goes up to 1/2 mile.
FM-1, basic unit \$5.95
FM-2, as above but with added mike preamp \$7.95
FM-4, long range, high power with very sensitive audio section, picks up voices 10' away \$14.95
FM-3, complete unit includes case, battery, switch, antenna, and built-in condenser mike. Excellent fidelity, very small, kit \$16.95
FM-3WT, as above, but fully wired and tested \$19.95
SMC, miniature sensitive mike cartridge for FM-1, 2, 4 \$2.95

MICROWAVE INTRUSION ALARM

A real microwave Doppler sensor that will detect a human as far as 10 feet away. Operates on 1.3 GHz, and is not affected by heat, light, or vibrations. Drives up to 100 mA output, normally open or closed, runs on 12 VDC. Complete kit MD-3 \$16.95

MUSIC MACHINE

Neat kit that will produce 25 different classical and popular tunes, plus 3 doorbells, shop, or store entrances, car horn, music boxes, etc. Runs on 9V battery or wall transformer. Excellent speaker volume and adjustable tempo and pitch. Add our case set for a handsome finished look. Complete kit, MM-5 \$24.95
Case + knob set, CMM-5 \$12.95

PACKET RADIO

Commodore C64/128 packet radio interface. Uses famous German Digicom software. Features EXAR IC chip set for reliable operation—runs HF or VHF tones. Includes FREE disk software. PC board, all necessary parts and full documentation. Complete kit, PC-1 \$49.95

LO NOISE PREAMPS

Make that receiver come ALIVE! Small size for easy installation with Hi-Q tuned input for peak performance. Excellent gain and noise figure—guaranteed to improve reception! Specify band: 2M—PR-10, 220 MHz—PR-20, 440 MHz—PR-40. Each kit \$17.95

TONE DECODER

A complete tone decoder on a single PC board. Features: 400–5000 Hz adjustable range via 20-turn pot, voltage regulation, 567 IC. Useful for touch-tone burst detection, FSK, etc. Can also be used as a stable tone encoder. Runs on 5 to 12 volts. Complete kit, TD-1 \$5.95

VOICE ACTIVATED SWITCH

Voice activated switch kit provides switched output with current capability up to 100 mA. Can drive relays, lights, LED, or even a tape recorder motor. Runs on 9 VDC. VS-1 kit \$6.95

TELEPHONE TRANSMITTER

Mini-sized with professional performance. Self-powered from phone line, transmits in FM broadcast band up to 1/4 mile. Installs easily anywhere on phone line or inside phone! PB-1 kit \$14.95

TICKLE STIK

A shocking kit! Blinking LED attracts victims to tickle up innocent-looking can—you watch the fun! Ideal for office desks, parties, nosey know-it-alls! TS-4 kit \$9.95

TV TRANSMITTER

Transmit your VCR or TV camera throughout your house. Stable quality signal, tunable Ch 4–6. Accepts standard video and audio inputs. Complete kit, JM-7 \$14.95

COLOR ORGAN

See music come alive! 3 different lights flicker with music. One light each for high, mid-range, and lows. Each individually adjustable and drives up to 300 W. Runs on 110 VAC. ML-1 kit \$8.95

LIGHT BEAM COMMUNICATORS

Transmits audio over infrared beam up to 30'—use simple lenses to go up to 1/4 mile! Hum free, uses 30 kHz carrier. Great for wireless earphones or undetectable "bug". Transmitter + receiver set, LB56 \$19.95

FM RADIO

Full-fledged superhet, microvolt sensitivity, IC detector and 10.7 MHz IF. Tunes Std. FM broadcast band as well as large portions on each end. Ideal for "bug" receiver, hobby experiments or even as FM radio! FR-1 kit \$14.95

SUPER SLEUTH

A super sensitive amplifier which will pick up a pin drop at 15 feet! Great for monitoring baby's room or as general purpose amplifier. Full 2W rms output. Runs on 6 to 15 volts, uses 8–45 ohm speaker. BN-9 kit \$5.95

BROADBAND PREAMP

Very popular sensitive all-purpose preamp. Ideal for scanner, TVs, VHF/UHF rigs, counters. Lo noise, 20 dB gain, 100 kHz–1 GHz, 9V–12 VDC operation. SA-7 kit \$14.95



FANTASTIC 2M FM TRANSCEIVER SYNTHESIZED—NO CRYSTALS TO BUY!



\$129⁹⁵


Ramsey breaks the price barrier on 2 meter rigs! Here's the ideal rig for field days, hamfests, vacations, second cars and packet (it even has dedicated packet connections). Six expandable diode-programmed channels, 5W RF output, sensitive dual conversion receiver and EASY assembly. Why pay more for a secondhand old rig when you can make your own for less. Have some fun with your own truly AMERICAN-MADE FM rig! This kit comes complete except for the case, mike and speaker—ICOM or equal speaker-mikes plug right in. Add our own beautiful case set for a professional factory look.

FTR-146 kit \$129.95
FTR-146-C aluminum case & knob set \$24.95

2 M & 220 BOOSTER AMP


Here's a great booster for any 2 meter or 220 MHz hand-held unit. These power boosters deliver over 30 watts of output, allowing you to hit the repeater's full quieting while the low noise preamp remarkably improves reception. Ramsey Electronics has sold thousands of 2 meter amp kits, but now we offer completely wired and tested 2 meter, as well as 220 MHz, units. Both have all the features of the high-priced boosters at a fraction of the cost.

PA-10 2 MTR POWER BOOSTER (10 X power gain)
Fully wired & tested \$79.95
PA-20 220 MHz POWER BOOSTER (8 X power gain)
Fully wired & tested \$79.95



QRP TRANSMITTERS HAM RECEIVERS

20, 30, 40, 80M CW TRANSMITTERS



Join the fun on QRP! Thousands of these mini-rigs have been sold and tons of DX contacts have been made. Imagine working Eastern Europe with a \$30 transmitter—that's ham radio at its best! These CW rigs are ideal mates to the receivers at right. They have two-position variable crystal control (one popular QRP XTAL included), one watt output and built-in antenna switch. Runs on 12VDC. Add our matching case and knob set for a handsome finished look.
Your choice of bands \$29.95
(Specify band: QRP-20, 30, 40 or 80)
Matching case & knob set, CQRP \$12.95

20, 30, 40, 80M All Mode RECEIVERS

Build your own mini ham station. Sensitive all-mode AM, CW, SSB receivers use direct conversion design with NE602 IC as featured in QST and ARRL handbooks. Very sensitive varactor tuned over entire band. Plenty of speaker volume. Runs on 9V battery. Very EASY to build, lots of fun and educational—ideal for beginner or old pro. New 30-page manual. Add the case set for well-fitted professional look.
Your choice of bands \$27.95
(Specify band: HR-20, HR-30, HR-40, HR-80)
Matching case & knob set, CHR \$12.95

E-Z KEY CMOS KEYS

Send perfect CW within an hour of receiving this kit! Easy-to-build kit has sidetone oscillator, speed control and keys most any transmitter. Runs for months on a 9V battery. 28-page manual gives ideas on making your own key for extra savings. Add our matching case set for complete station look.
CW-7 kit \$24.95
Matching case knob set, CCW \$12.95

ACTIVE ANTENNA

Cramped for space? Get longwire performance with this desktop antenna. Properly designed unit has dual HF and VHF circuitry and built-in whip antenna, as well as external jack. RF gain control and 9V operation makes unit ideal for SWLs, traveling hams or scanner buffs who need hotter reception. The matching case and knob set gives the unit a hundred dollar look!
AA-7 Kit \$24.95
Matching case & knob set, CAA \$12.95

SPEECH SCRAMBLER


Communicate in total privacy over phone or radio. Kit features full duplex operation using frequency inversion. Both mike and speaker or line in/out connections. Easy hookup to any radio, and telephone use requires no direct connection! Easy to build 2 IC circuit. Can also be used to descramble many 2-way radio signals. Finish your kit off with the handsome case & knob set.
SS-7 kit \$29.95
Matching case & knob set, CSS \$12.95

SHORTWAVE RECEIVER



Fantastic receiver that captures the world with just a 12" antenna! Can receive any 2 MHz portion from 4–11 MHz. True superhet has smooth varactor tuning, AGC, RF gain control, plenty of speaker volume and runs on a 9V battery. Fascinating Scout, school or club project provides hours of fun for even the most serious DXer. For the car, consider our shortwave converter. Two switchable bands (in 3–22 MHz range), each 1 MHz wide—tunable on your car radio dial. Add some interest to your drive home!
Shortwave receiver kit, SRI \$27.95
Shortwave converter kit, SCI \$24.95
Matching case set for SRI, CSR \$12.95
Matching case set for SCI, CSC \$12.95

2, 6, 10 MTR, 220 FM RECEIVERS



Keep an ear on the local repeater gang; monitor the cops, check out the weather or just plain listen around. These sensitive superhet receivers are just the ticket. They tune any 5 MHz portion of the band and have smooth varactor tuning, dual conversion with ceramic IF filters, AFC, adjustable squelch and plenty of speaker volume. Runs on 9V battery and performance that rivals the big rigs! For a complete finished pro look, add our matching case and knob set with screened graphics.
FM communications receiver kit \$29.95
Specify band: FR 146 (2m), FR6 (6m), FR10 (10m), FR-220 (220 MHz)
Matching case & knob set, CFR \$12.95


FM STEREO TRANSMITTER

STEREO



Run your own stereo FM station! Transmit a stable signal in the standard FM broadcast band throughout the house, dorm or neighborhood. Connects easily to line outputs on CD player, tape decks, etc. Runs on 9V battery, has internal whip antenna and external antenna jack. Add our case set for a "station" look!
FM-10 kit \$29.95
Matching case set, CFM \$12.95

AIRCRAFT RCVR



Hear exciting aircraft communications—pick up planes up to 100 miles away! Receives 110–136 MHz AM air band, smooth varactor tuning superhet with AGC, ceramic filter, adjustable squelch, excellent sensitivity and lots of speaker volume. Runs on 9V battery. Great for air shows or just hanging around the airport! New 30-page manual details pilot talk, too. Add case set for "pro" look.
AR-1 kit \$24.95
Matching case set, CAR \$12.95

TERMS: Satisfaction guaranteed: examine for 10 days. If not pleased, return in original form for refund. *Add 7% (up to a maximum of \$10) for shipping, handling and insurance. *For foreign orders, add 15% for surface mail. *COD (USA only), add \$4.50. *Orders under \$20, add \$3.00. *NY residents, add 7% sales tax. *90-day parts warranty on kits. *1 year parts & labor warranty on wired units.



PHONE ORDERS CALL
716-924-4560
FAX 716-924-4555

RAMSEY ELECTRONICS, INC. 793 Canning Parkway, Victor, NY 14564

The "No Antennas" Antenna

One woman's solution to problems with pesky landlords.

by Jacquelyn J. McGlothlin N9CAP

Are you one of the unfortunate few who happen to be an apartment-dweller ham? And is your landlord or apartment manager one who forbids outdoor antennas of any sort? If so, this article may be for you. The problem of erecting an antenna in a "no antennas outdoors" situation is a tricky one, indeed. This limits you to indoor ant-

tennas, the logic being that what is not seen will not be noticed.

After experimenting with many different types of indoor antennas, all with disastrous results and much TVI, I finally came upon a coaxial dipole suggested by a fellow ham friend. This antenna appealed to me because of its greatly attenuated harmonics, thus lessening the TVI problem. Unlike a conventional dipole, this antenna is very broadband, covering from 500 kHz to 1 MHz, depending on the band used, and with an SWR of under 2:1 at the band edges.

Its broadband characteristics are due, in part, to the feedline being matched to the antenna and the electrical incorporation of its own balun, with the result that no add-on antenna tuner or balun is required. The coaxial dipole has a slight amount of gain over a conventional dipole, and since the vinyl jacket covers the entire antenna, it reduces static charge buildup considerably,

which causes a popping noise in the receiver when discharged. Thus, the coaxial dipole is a very "quiet" antenna with slightly stronger signal punch than a conventional dipole.

The antenna is simple to construct. You may use either RG-8/U or RG-58A/U coax. The latter is lighter and easier to work with. Maximum legal power can be used with either choice of coax. For antenna lengths, see Figure 1. The 40 meter antenna will be used as an example.

Where to Begin

Begin construction by removing 2.5 cm (1") of vinyl jacket (1/2" each side of the center) at the center of the antenna. Cut the shield in the center all the way around the coax. Care must be used so that you do not cut the dielectric or the center conductor. Next, form two leads with

the shield, as shown in Figure 2. This is the feedpoint of the antenna.

From this center feedpoint, measure out each side of center 5.1 meters (16'9") and cut the coax at that point. Remove approximately 2.5 cm of vinyl jacket from each of the ends and fold back the shield so that the dielectric is exposed. Cut and remove about 2.5 cm of this insulation, being careful not to cut the center conductor. Then twist the shield and center conductor together and solder. This must be done at both ends and forms the 52 ohm matching section and balun.

Next, cut two lengths of coax, each 4.4 meters (14'9") long. Then remove 2.5 cm of vinyl jacket from all four ends, fold back the shield, remove the center insulation, and twist the shield and center conductor together as before. This forms the end sections of the antenna. Attach one of these end sections to one end of the matching section by twisting together the prepared ends and soldering. In the same manner, solder the remaining end section to the other end of the matching section. Waterproof these joints as best you can. Waterproofing of the ends will be done later, for they may need cutting for tuning purposes.

Attaching the Feedline

Any random length of coax will do for the feedline, but it must be of the same type used for construction of the antenna. Remove approximately 2.5 cm of vinyl jacket from the end of the

AAIA SIDEKICK ANTENNAS



\$79.95 + 5.00 shipping/handling

- More Gain-Very Efficient
- Rugged Construction-Tested at Sea
- Self Mounting to Tower or Mast
- Extended Double Zapp 84" @ 144
- Broadband - Tunes Outside Band
- SO-239 Feed - Very Low Loss
- Stainless Elements
- All New Innovative Design
- Customers Report Very Positive

144 - 220
440 Mhz.
Models

Order Direct 1-800-874-2880
VISA-MC OK No Extra Charge
BROADCAST TECHNICAL SERVICES
11 Walnut St., Marshfield, MA 02050

48 HOUR SHIPPING

ELENCO & HITACHI PRODUCTS AT DISCOUNT PRICES

Hitachi RSO Series
(Portable Real-time Digital Storage Oscilloscopes)
VC-6023 - 20MHz, 20MS/s \$99/mo*
VC-6024 - 50MHz, 20MS/s \$120/mo*
VC-6025 - 50MHz, 20MS/s \$135/mo*
VC-6045 - 100MHz, 40MS/s \$125/mo*
VC-6145 - 100MHz, 100MS/s \$200/mo*

RSO's from Hitachi feature roll mode, averaging, save memory, smoothing, interpolation, pretriggering, cursor measurements. These scopes enable more accurate, simpler observation of complex waveforms, in addition to such functions as hardcopy via a plotter interface and waveform transfer via the RS-232C interface. Enjoy the comfort of analog and the power to digital.

20MHz Elenco Oscilloscope
\$375
MO-1251
• Dual Trace
• Component Tester
• 6" CRT
• X-Y Operation
• TV Sync
• 2 P-1 Probes

All scopes include probes, schematics, operators manual and 3 year (2 yrs for Elenco scopes) world wide warranty on parts & labor. Many accessories available for all Hitachi scopes. Call or write for complete specifications on these and many other fine oscilloscopes.

48 HOUR SHIPPING

LEASING AVAILABLE
For all Hitachi Scopes - Call for details
* Based on 24 months except V-1150, VC-6045, VC-6145 (36 months)

Hitachi Portable Scopes
DC to 50MHz, 2-Channel, DC offset function, Alternate magnifier function
V-525 - CRT Readout, Cursor Meas. \$1,025
V-523 - Delayed Sweep \$995
V-522 - Basic Model \$895
V-422 - 40MHz \$795
V-223 - 20MHz delayed sweep \$695
V-212 - 20MHz \$425

HITACHI COMPACT SERIES SCOPES
This series provides many new functions such as CRT Readout, Cursor measurements (V-1085/1085/665), Frequency Ctr (V-1085), Sweep Time Autoring, Delayed sweep and Trigger Lock using a 6-inch CRT. You don't feel the compactness in terms of performance and operation.

V-660 - 60MHz, Dual Trace \$1,195
V-665 - 60MHz, DT, w/cursor \$1,345
V-1060 - 100MHz, Dual Trace \$1,425
V-1065 - 100MHz, DT, w/cursor \$1,060/mo*
V-1085 - 100MHz, QT, w/cursor \$1,250/mo*
V-1100A - 100MHz, Quad Trace \$1,250/mo*
V-1150 - 150MHz, Quad Trace \$1,150/mo*

Elenco 35MHz Dual Trace
Good to 50MHz **\$495**
MO-1252
• High luminance 6" CRT
• 1mV Sensitivity
• 6KV Acceleration Voltage
• 10ms Rise Time
• X-Y Operation + Z Axis
• Delayed Triggering Sweep
• Includes 2 P-1 Probes

B & K TEST EQUIPMENT
All Models Available
Call for special price

FLUKE MULTIMETERS
All Models Available
Call for special price

Digital Capacitance Meter
CM-1550B
\$58.95
9 Ranges
1p1-20,000pF
5% basic acy.
Zero control w/ Case
Big 1" Display

Digital LCR Meter
LC-1801
\$125
Measures:
Coils 1uH-200H
Caps 1p1-200uF
Res. 01-20M

Multimeter with Capacitance & Transistor Tester
CM-1500B
\$55
Reads Volts, Ohms
Current, Capacitors,
Transistors and
Diodes w/ case

Soldering Station
Temperature Controlled
SL-30 \$99
Digital Display
Temp Range:
300F-900F
Grounded Tip
Overheat Protect

Color Convergence Generator
SG-200
\$179
Finest in the industry
10 rock steady patterns **\$69.95**

Four-Function Frequency Counters
F-100 120MHz \$179
F-1000 1.2GHz \$259
Frequency, Period, Totalize,
Self Check with High Stabilized Crystal
Oven Oscillator, 8 digit LED display

Function Generator
Blox #9600
\$28.95
Provides sine, triangle,
square wave from 1Hz to
1MHz AM or FM capability

AM/FM Transistor Radio Kit with Training Course
Model AM/FM 108
\$26.95
14 Transistors + 5 Diodes
Makes a great school project

True RMS 4 1/2 Digit Multimeter
M-7000
\$135
05% DC Accuracy
1% Resistance
with Freq. Counter
and Deluxe Case

GF-8016 Function Generator with Freq. Counter
Sine, Square, Triangle
Pulse, Ramp, 2 to 20MHz
Freq. Counter, 1 - 10MHz
\$249

GF-8015 without Freq. Meter \$179

Learn to Build and Program Computers with this Kit
Includes: All Parts, Assembly and Lesson Manual
Model MM-9000
\$129.00

Starting from scratch you build a complete system. Our Micro-Master trainer teaches you to write into RAM, ROMs and run a 8085 microprocessor, which uses similar machine language as IBM PC.

Robotics Kit for above (MM8010) \$119.95

WE WILL NOT BE UNDERSOLD!
UPS Shipping: 48 States 5%
(\$3 Min \$10 Max) Shipping
IL Res.: 7% Tax FAX: 708-520-0085

Wide Band Signal Generators

First TWIN BAND HT made for the U.S. market!

STANDARD C228A TRUE TWIN BAND 144 and 220 MHz HT
Now there's a new STANDARD in Amateur Radio
Two friendly bands in ONE HT, 144 and 220 MHz
The best combination now and in the future

CALL FOR PRICING

- Direct frequency input via the keyboard or dial in the frequency with the rotary channel selector.
- Large easy to read TWIN frequency display.
- Variable scanning modes let you locate the station quickly.
- Includes high density 700 mAh battery and charger.
- 5.0 watts (high power) when operated from 12 VDC transmitter output power both bands with three programmed power settings.
- Optional Accessories include a complete line of Batteries, Dash Charger, Headset with PTT and Water Resistant case.
- 1 Year Warranty

Call for pricing

NEW TWIN BAND MOBILE 2M/440MHz
Call for pricing

C & S SALES INC.
1245 Rosewood, Deerfield, IL 60015
(800) 292-7711 (708) 541-0710

15 Day Money Back Guarantee
2 Year Warranty
Prices Subject to Change
WRITE FOR FREE CATALOG




Figure 1. Antenna lengths.




Figure 2. Feedpoint connection.

feedline, fold back the shield, and remove the center insulation. Form two leads with the shield and center conductor. At the feedpoint of the antenna, connect the feedline by soldering the feedline center conductor to one of the feedpoint leads. Then solder the feedline shield to the remaining lead. You may wish to waterproof this area, making sure that the feedpoint leads do not touch each other and short out. Follow this procedure for antennas on other bands.

If you have access to an attic or crawl space in the roof of your apartment building, so much the better. Using monofilament fishing line as anchor ties, a series of half hitches along the vinyl jacket ends of the antenna will do nicely for anchoring the antenna. The monofilament line will bite into the vinyl as it is pulled taut.

If you are not fortunate enough to have access to an attic, the antenna may be stapled to a living room or bedroom ceiling using plastic cable ties or any other non-conducting material as support. Wrap the cable ties around the antenna at intervals and staple the free ends of the ties to the ceiling. Do not staple directly through the antenna itself.

This antenna can be used as a dipole or inverted-vee. If used as a dipole, try to erect as much of it as possible in a straight line, keeping it as far away from large metal objects as feasible. The ends may hang down as long as they don't touch any nearby metal objects. More than one antenna may be erected in the same area, providing they are run at angles to each other rather than being parallel. The reason for this is that the inactive antenna could absorb some signal from the active antenna, thereby attenuating the signal output.

After erecting the antenna, check SWR and trim the ends if necessary. Be sure to twist the ends of the antenna as before (shield to center conductor), then recheck SWR. The antenna will interact with any hidden wiring in walls, so a considerable amount may have to be trimmed from each end. Once you have gotten the SWR down to an acceptable level, solder the ends of the antenna and waterproof them if you wish. This completes construction.

Finishing Up

Aside from a low-pass filter, no other add-on's are needed, the filter being only a safety precaution. And, since the antenna is basically omnidirectional, orientation can be determined by the space available at your location.

Once you start enjoying the pleasures of operating from your apartment with this antenna, you will be amazed at what you can work, and the signal reports you get with it. I have used coaxial dipoles on 10, 15, 20 and 40 meters from an apartment, and all are stapled to a ceiling in "inverted-U" fashion rather than inverted-vee. Signal reports received vary from S6 to 60 dB over S9. TVI is minimal, considering my TV is only a mere 10 feet from the antenna and I run 200 watts PEP.


With these coaxial dipoles in use for over two years now, I have gotten Worked All Continents, Worked All States, and DXCC with 121 countries worked to date. So there's no telling what you can do with this antenna and you may be pleasantly surprised at the results. It sure beats non-operating just because you live in an apartment! Happy DXing!

RF

Reprinted from 73 Magazine, May 1981, with permission of the author, whose name and call sign at that time was Jacquelyn Schoewe WA9BBX. See Jacquelyn's article, "Indoor 10 Meter Beam" in the September 1991 issue of 73. You may reach Jacquelyn J. McGlothlin N9CAP at 2761A So. Logan Ave., Milwaukee WI 53207.


Hams Stricken by Mysterious Ailment

Hams have become victim of a strange sickness, medical researchers say (see photo). The first case was reported as a 27-year-old amateur radio operator was found sitting upright at his equipment, one hand suspended above the straight key, the other on the receiver dial. He seemed lifeless, and failed to react to outside stimuli. While this is a common condition of hams, it was unusual in this case because there was no reaction to a DX call. The diagnosis was "rig-mortis," a catatonic state brought on by continuous exposure to CW. Advanced cases result in complete disorientation, high SWR, and even burned out finals. If you know anyone experiencing these symptoms, please send information to "STIFF," c/o Lishnus General Medical Center, Mount Vermin OH 45323. TNX "GEARVAKf Bulletin," Vol. 30, No.1. 1990.



ASTRON CORPORATION

9 Autry
Irvine, CA 92718
(714) 458-7277




MODEL VS-50M

SL SERIES




RS-L SERIES



RM SERIES


MODEL RM-35M

RS-A SERIES



MODEL RS-7A

RS-M SERIES




MODEL RS-35M

VS-M AND VRM-M SERIES



MODEL VS-35M

RS-S SERIES



MODEL RS-12S

ASTRON POWER SUPPLIES

• HEAVY DUTY • HIGH QUALITY • RUGGED • RELIABLE •

SPECIAL FEATURES

- SOLID STATE ELECTRONICALLY REGULATED
- FOLD-BACK CURRENT LIMITING Protects Power Supply from excessive current & continuous shorted output
- CROWBAR OVER VOLTAGE PROTECTION on all Models except RS-3A, RS-4A, RS-5A, RS-4L, RS-5L
- MAINTAIN REGULATION & LOW RIPPLE at low line input Voltage
- HEAVY DUTY HEAT SINK • CHASSIS MOUNT FUSE
- THREE CONDUCTOR POWER CORD except for RS-3A
- ONE YEAR WARRANTY • MADE IN U.S.A.

PERFORMANCE SPECIFICATIONS

- INPUT VOLTAGE: 105-125 VAC
- OUTPUT VOLTAGE: 13.8 VDC \pm 0.05 volts (Internally Adjustable: 11-15 VDC)
- RIPPLE Less than 5mv peak to peak (full load & low line)
- All units available in 220 VAC input voltage (except for SL-11A)

MODEL	Colors Gray Black	Continuous Duty (Amps)	ICS* (Amps)	Size (IN) H x W x D	Shipping Wt. (lbs.)
• LOW PROFILE POWER SUPPLY					
SL-11A	• •	7	11	2 3/4 x 7 1/2 x 9 3/4	11
MODEL		Continuous Duty (Amps)	ICS* (Amps)	Size (IN) H x W x D	Shipping Wt. (lbs.)
• POWER SUPPLIES WITH BUILT IN CIGARETTE LIGHTER RECEPTACLE					
RS-4L		3	4	3 1/2 x 6 1/2 x 7 1/4	6
RS-5L		4	5	3 1/2 x 6 1/2 x 7 1/4	7
MODEL		Continuous Duty (Amps)	ICS* (Amps)	Size (IN) H x W x D	Shipping Wt. (lbs.)
• 19" RACK MOUNT POWER SUPPLIES					
RM-12A		9	12	5 1/4 x 19 x 8 1/4	16
RM-35A		25	35	5 1/4 x 19 x 12 1/2	38
RM-50A		37	50	5 1/4 x 19 x 12 1/2	50
RM-60A		50	55	7 x 19 x 12 1/2	60
• Separate Volt and Amp Meters					
RM-12M		9	12	5 1/4 x 19 x 8 1/4	16
RM-35M		25	35	5 1/4 x 19 x 12 1/2	38
RM-50M		37	50	5 1/4 x 19 x 12 1/2	50
RM-60M		50	55	7 x 19 x 12 1/2	60
MODEL	Colors Gray Black	Continuous Duty (Amps)	ICS* (Amps)	Size (IN) H x W x D	Shipping Wt. (lbs.)
RS-3A	• •	2.5	3	3 x 4 3/4 x 5 3/4	4
RS-4A	• •	3	4	3 3/4 x 6 1/2 x 9	5
RS-5A	• •	4	5	3 3/4 x 6 1/2 x 7 1/4	7
RS-7A	• •	5	7	3 3/4 x 6 1/2 x 9	9
RS-7B	• •	5	7	4 x 7 1/2 x 10 3/4	10
RS-10A	• •	7.5	10	4 x 7 1/2 x 10 3/4	11
RS-12A	• •	9	12	4 1/2 x 8 x 9	13
RS-12B	• •	9	12	4 x 7 1/2 x 10 3/4	13
RS-20A	• •	16	20	5 x 9 x 10 1/2	18
RS-35A	• •	25	35	5 x 11 x 11	27
RS-50A	• •	37	50	6 x 13 3/4 x 11	46
MODEL		Continuous Duty (Amps)	ICS* (Amps)	Size (IN) H x W x D	Shipping Wt. (lbs.)
• Switchable volt and Amp meter					
RS-12M		9	12	4 1/2 x 8 x 9	13
• Separate volt and Amp meters					
RS-20M		16	20	5 x 9 x 10 1/2	18
RS-35M		25	35	5 x 11 x 11	27
RS-50M		37	50	6 x 13 3/4 x 11	46
MODEL		Continuous Duty (Amps)	ICS* (Amps)	Size (IN) H x W x D	Shipping Wt. (lbs.)
• Separate Volt and Amp Meters • Output Voltage adjustable from 2-15 volts • Current limit adjustable from 1.5 amps to Full Load					
		@13.8VDC @10VDC @5VDC	ICS* (Amps) @13.8V		
VS-12M		9 5 2	12	4 1/2 x 8 x 9	13
VS-20M		16 9 4	20	5 x 9 x 10 1/2	20
VS-35M		25 15 7	35	5 x 11 x 11	29
VS-50M		37 22 10	50	6 x 13 3/4 x 11	46
• Variable rack mount power supplies					
VRM-35M		25 15 7	35	5 1/4 x 19 x 12 1/2	38
VRM-50M		37 22 10	50	5 1/4 x 19 x 12 1/2	50
MODEL	Colors Gray Black	Continuous Duty (Amps)	ICS* (Amps)	Size (IN) H x W x D	Shipping Wt. (lbs.)
• Built in speaker					
RS-7S	• •	5	7	4 x 7 1/2 x 10 3/4	10
RS-10S	• •	7.5	10	4 x 7 1/2 x 10 3/4	12
RS-12S	• •	9	12	4 1/2 x 8 x 9	13
RS-20S	• •	16	20	5 x 9 x 10 1/2	18

*ICS—Intermittent Communication Service (50% Duty Cycle 5min. on 5 min. off)

Sold the Linear?

That's right. Never been happier, either. It all started when I wanted to crash the DX party on 40 CW. First I put up a HalfSquare aiming NE. I found I could work Europeans barefoot when the rotary beam KWs couldn't even hear 'em. So I put up another aimed NW, sold the linear, and bought the YL a new coat. Best trade I ever made. When you order add \$5 P&H

10 M \$39.95 15 M \$44.95 20 M \$49.95 40 M \$69.95
Antennas West Order Hot Line:
 Box 50062F, Provo, UT 84605 800-926-7373
 Plans, patterns, technical details in TechNote #122B \$5.95 ppd USA.

CIRCLE 89 ON READER SERVICE CARD

National Tower Company

P.O. Box 15417 Shawnee Mission, KS. 66215
 Hours 8:30-5:00 M-F Price Subject to Change Without Notice

ORDER TOLL FREE
 800-762-5049

Local 913-888-8864

ROHN TOWERS

25G	10' section	\$59.50
45G	10' section	\$140.00
55G	10' section	\$180.00
BX-40	40' self supporting 6 sq ft	\$215.50
BX-48	48' self supporting 6 sq ft	\$274.50
BX-56	56' self supporting 6 sq ft	\$368.50
BX-64	64' self supporting 6 sq ft	\$474.50
HXB-40	40' self supporting 10 sq ft	\$249.50
HXB-48	48' self supporting 10 sq ft	\$338.90
HXB-56	56' self supporting 10 sq ft	\$432.00
HXB-64	64' self supporting 10 sq ft	\$533.00
HDBX-48	48' self supporting 18 sq ft	\$423.50

Base stubs for BX series towers IN STOCK!

3/16EHS	500' galvanized 7 strand	\$45.00
1/4EHS	500' galvanized 7 strand	\$55.00

HYGAIN-TELEX & LARSEN ANTENNAS CALL FOR PRICES

CUSHCRAFT ANTENNAS

AOP-1	complete Oscar Link system	\$186.00
A8B	8band 1/4 wave vertical	\$172.00
A3S	3 element triband beam	\$299.00
A3WS	12-17 mtr HF yagi	\$236.00
A103	Adds 30 mtr to A3WS	\$95.00
A743	7 & 10 MHz add on kit for A3	\$95.00
R5	10-12-15-17-20 mtrs	\$245.00
R7	10-12-15-17-20-30-40 mtrs	\$334.00
R57K	adds 30-40 mtrs to R5	\$220.00
A4S	4 element triband beam	\$351.00
ARX2B	2 mtr. Ringo Ranger	\$43.50
ARX450B	450 MHz Ringo Ranger	\$43.50
AR270	144-148 435-450MHz duo Ringo	\$54.00
A147-11	11 element 146-148 MHz beam	\$57.00
A50-5S	50-54MHz 5 element yagi	\$108.00
215WB	15 element 2 mtr. 'Boomer'	\$82.00
10-4CD	4 element 10 mtr. 'Skywalker'	\$176.00
15-4CD	4 element 15 mtr. 'Skywalker'	\$209.00
13B2	2 meter, 13 elements	\$88.00
17B2	2 meter, 17 elements	\$148.00

Full Line of Cushcraft in STOCK - CALL

HUSTLER ANTENNAS

48TV	40-10 mtr vertical	\$84.00
58TV	80-10 mtr vertical	\$109.00
68TV	6 band trp vertical	\$129.00

ROTORS

Alliance	U110	\$49.00
	H073	\$139.90

TELEX - CD45H HAM IV & T2X - CALL

CAROL

CABLE

[2-18 & 6-22]	4080 - per foot	\$0.25
[2-16 & 6-20]	4090 - per foot	\$0.35
1108	RG8U Mini 8 low loss foam per foot	\$0.22
1198	RG8U Columbia superflex 100'	\$31.00
1180	RG8U Low loss 100% bonded foil shield	
	88% tin copper braided shield - per foot	\$0.42
1176	RG213 Columbia - per foot	\$0.38

CELWAVE CELLFLEX

FLC1250J	1/2" copper (per foot)	\$2.15
FLC7850J	7/8" copper (per foot)	\$5.40
1/2" connector	\$28.80	7/8" connector \$69.00

TENNA PHASE III POWER SUPPLIES

PS4	Fully regulated, with surge protection, overload protection w/instant auto reset	\$21.90
PS7	Fully regulated, low ripple, protects against dangerous voltage surges	\$27.90
PS12	Fully regulated, electronic overload protection	\$39.90
PS20	Fully regulated low ripple short circuit protection	\$74.90
PS25	Regulated, instant auto reset, dual meter for current & voltage	\$94.90

ASTRON Power Supplies

Model	AMPS	ICS	Price
RS7A	5	7	\$51.00
RS12A	9	12	\$73.00
RS20A	16	20	\$90.00
RS20M	16	20	\$110.00
RS35A	25	35	\$144.00
RS35M	25	35	\$165.00

OTHER ASTRONS AVAILABLE
 CALL FOR PRICES

uniden



BC147XL \$89.90

16 Ch 10 band, weather, programmable, delay, review, priority, memory backup, channel lockout, direct ch access, track tuning, AC/DC, external speaker & antenna jacks.

BC560XLT \$94.90

16 Ch 10 band mobile, 2 digit LED display, scan delay, memory backup, channel lockout, direct ch access, weather search, squelch, channel review, track tuning, external speaker jack.

BC800XLT \$234.90

40 CH 12 band w/800MHz & cellular telephone, track tuning, instant weather, scan delay, ch lockout, direct ch access, AC/DC.



BC55XLT	10 Ch 10 band hand held	\$114.90
BC70XLT	20 Ch 10 band w/batt pack	\$149.90
BC100XLT	100 Ch 11 band hand held	\$184.90
BC200XLT	200 Ch 12 band, hand held, 800MHz	\$239.90
BC177XLT	16 Ch 11 band w/aircraft	\$129.90
BC210XLT	40 Ch 11 band aircraft & weather	\$169.90
BC855XLT	40 Ch 12 band w/800MHz base	\$189.90
BC590XLT	100 Ch 11 band mobile weather	\$199.90
BC760XLT	100 Ch 12 band w/800MHz mobile	\$254.90



SUPER AMP \$54.90
 Compact per-amp designed to work w/hand held scanners & amplify the reception of VHF/UHF bands from 100MHz to 1GHz as high as 20dB, adjustable gain control, bypass switch

9001 \$74.90
 Super converter is designed to receive frequencies between 810MHz and 912MHz and convert them down to 410MHz through 512MHz, requires 9 volt battery or AC adapter.

8002 \$79.90
 Hand held converter, same features as 9001, has bypass switch that allows user to go back to 400MHz without disconnecting the unit, BNC connectors.


ASTATIC

Silver Eagle \$69.90
 Chrome plated base station amateur microphone, factory wired to be easily converted to electronic or relay operation, adjustable gain for optimum modulation.



MAXON \$26.95

Model 49SA - 49 MHz, FM 2-WAY RADIO hands free operation, voice activated transmit up to 1/2 mile. Batteries optional



model 49F5 \$49.90
 5 Ch FM 2-way, with Earphone mic, offers hands free voice activated or push-to-talk TX, VOX activated by Hi-Med-Low mic sensitivity switch, 5 1/4x2 1/4x1.



EXCALIBUR Vehicle Security System



AL9006TX \$99.90

1 or 2 car operation from key chain transmitter, effective up to 170 ft away, with shock/glass sensors, pin switching & circuit sensing. Full time panic alert, full LED status, passive and/or active arming, last door arming, trunk release, 1150b electronic siren.

10 METER TRANSCEIVERS
RCI 2950 RANGER AR3500/100
 CALL FOR PRICES

CIRCLE 91 ON READER SERVICE CARD



the tech side

by Michael Jay Geier KB1UM

The tools of the trade.

Welcome Back!

Welcome to the second installment of "The Tech Side." I'm glad you've decided to check the technical side of the hobby out. I promise you'll learn a lot and have tons of fun doing it! But before you start building or fixing anything, you're going to need some tools. Luckily, everything you need can be found at your local Radio Shack store, so you don't have to go hunting around or mail-ordering to get started.

If you go into the hamshacks of a few technical-type hams, you'll find quite a wide range of tools and test equipment. Some may have a large, expensive array resembling a small research laboratory. Others may only have a few simple pieces of test gear and some basic hand tools. Either can be an effective trouble-shooter and builder, although naturally the more complete setup will allow its owner to do some things not possible with the smaller one.

How Much Do I Need?

Well, that's up to you and your wallet. If you're just getting started, I recommend you start small, because you can always grow later. If you buy lots of gear now, you might not make great choices, and you may find the equipment intimidating. Besides, I want you to have some money left over for ham gear. Even if you decide to build some of your station, you probably don't want to try to make your own 2 meter walkie! But then again, maybe you will. . . . I'm working on a super-low-cost 2 meter walkie construction project. When it's done, we'll publish it either here in *RF* or in *73*, and I'll bet you will want to build one, even if you already have a fancy commercial unit.

But I digress. . . . Let's start deciding what tools to buy to set up shop. The tools used in troubleshooting and building are basically the same, so the choice isn't difficult.

Gimme a Hand

Electronics definitely is a hands-on experience, so you will need some basic hand tools. Although some large tools can be handy, you'll spend most of your time working with rather small parts and assemblies, so let's concentrate on small tools for now. Go out and buy these:

A pair of diagonal cutters, needle-nose pliers, a miniature "jeweler's" screwdriver set (be sure you get both flat-head and Phillips head), a few medium-sized screwdrivers, some regular pliers, a small hex key set, and a flashlight. These ought to keep you satisfied for most jobs. Oh, and while you're at it, pick up some TV tuner or contact cleaner, a roll of plastic electrical tape, and a roll of #22 gauge stranded hookup wire.

Some Like It Hot

There is one tool you'll wind up spending most of your time with: your soldering iron. Get a decent one; avoid those \$4 "pencil" types. There really isn't much to a soldering iron, but you want to get one with a handle that stays cool (the cheap ones don't) and, naturally, you want the iron to last a long time. Typically, you will fire the iron up at the start of a session and shut it down at the end—it's not like using one of those trigger-operated guns, which are way too big and hot for our purposes anyway. Your iron may stay on for eight or ten hours at a clip. Time really flies when you work on electronics, and it's easy to get so engrossed that you don't even

notice that the sun has gone down (or risen!).

Watt's What

Soldering irons are rated in terms of how much electricity they use (in watts), because that's proportional to how much heat they put out. Get an iron in the 30 to 50 watt range. Lower than that, and you may have trouble getting some connections hot enough. Higher, and you might fry printed circuit traces and small components.

Many irons offer the option of affixing different-sized tips. Get a medium or medium-small one. The larger tips just won't fit into some of the nooks and crannies you'll be encountering, and the smaller ones don't have enough surface area to transfer the heat required to join larger connections.

If the iron doesn't already come with a stand, get one. It is very bad practice to lay an iron on the table; you'll burn the table and maybe even start a fire! Besides, a hot iron can burn the blades out of you and free-floating ones tend to roll around and get in your way. Also, get a tip cleaning sponge. Soaked with water, this will let you clean the hot tip in a jiffy, and a clean tip is *essential* to making proper connections.

Expect to pay \$20 to \$40 for a good iron. I know it sounds like a lot for what is basically a heater but, believe me, you'll be glad you got a quality iron.

Hey, don't forget the solder! Your nifty new iron isn't much good without it. Solder is a bit more expensive than it used to be, but the general rule of thumb is still: The more you buy, the cheaper it is per pound. Tiny rolls actually wind up costing you more in the long run because, believe me, you will go through lots of solder. Get at least a 1/2-pound roll. A one-pounder is even better, and will last you at least a year. Naturally, you want to get the kind of solder used for electronics work, which is all Radio Shack and most mail-order outfits carry anyway. (There are other kinds, such as plumbing solder, and you must *never* use them, because they are corrosive and will ruin your circuits.) Solder comes in various diameters; 0.032" is about right.

Getting Testy

Whether you build, repair, or both, you need some way to see what is happening in whatever circuit you are fiddling with. Unfortunately, electrons are invisible, so you need an instrument of some kind which can measure the circuit's voltage, current or resistance. There are two basic kinds: fast and slow. The champion of fast instruments is the oscilloscope, which basically is a fast electronic graphing machine. Although its principles of operation are simple, actually using one takes some practice and a level of understanding you may not yet have.

Another example of a fast instrument is the frequency counter, whose name is pretty self-explanatory. Want to know if your rig is on frequency? Just transmit near the counter's probe and you'll see the frequency displayed in common numbers. The counter has other uses, one of which is very valuable: To tell if an oscillator is functioning at all when there is no oscilloscope handy, or when the oscillator's frequency is too high for the scope to detect.

Slow instruments generally fall into two categories: analog and digital. The most common analog slow instrument is the VOM, or Volt-Ohm-Milliammeter. This very useful box can read AC and DC volts, ohms (usually out to about 1 million ohms or so), and amps (current). Typically, the current range is limited to less than one amp, but some meters can read as high as 10 amps, which is a lot. Most circuits you work on will draw perhaps a few

hundred milliamps (thousandths of an amp). Actually, the most common use for a VOM is to read voltage; next is resistance (ohms). Current comes in a distant third, primarily because taking a current reading involves breaking a circuit connection, which often may be difficult or impossible in a given circuit.

Digital VOMs, or DVMs (digital volt meters), do essentially the same thing as the analog variety, but have a numeric readout instead of a meter needle. Although they once were quite expensive and exotic, DVMs have become so common that they now cost about the same as VOMs. The principle advantage the DVM offers over the VOM is its precision and accuracy. Even a cheap DVM tells the truth better than any VOM. So why would you possibly want a VOM? Well, it, too, has advantages. The biggest one is that slowly changing readings are shown as a moving or wavering needle. With time, you can get very good at interpreting that waver, and it can reveal all kinds of things. With a DVM, a slowly changing input is shown merely as a moving series of numbers, which is hard to analyze by eye. Also, DVMs sample at discrete intervals, and you may miss something between samples. There are DVMs which have a multi-segment bar graph in the display to show changing signals, but even they don't compare to true analog meters.

Meter Halfway

Which should you get? Both. Buy a decent VOM, but don't get a real expensive one. About \$30-\$40 should do it. Then get a DVM for under \$50. Radio Shack has one for \$37 (catalog number 22-188) that should do just fine. If you can't afford both, and your primary use for it will be trouble-shooting, go with the VOM first and save to get the DVM later. Most of the time, the improved graphic display of the analog meter is more valuable than the increased accuracy of the DVM. If you intend to do much home-brewing, though, you may find the DVM more useful, because you can calibrate voltages a lot more accurately with it.

Supply Side Electronics

OK, you've got your basic tools. Now, if you have any money left, you might want to stock up on some basic components. Keeping a stock of parts is more important if you plan to home-brew, and not just repair, gear, but it can be handy in repairs, too. There are literally thousands of types of electronic components, so there's no way you can have even a representative sampling of all the different kinds. Some parts, however, are very commonly used, and also find their way into lots of construction projects. Here are some you might want to get:

Resistors: Get a supply of common 1/4 watt, 5 percent tolerance resistors. These are the normal kind with four color bands on them. The last band is gold, which specifies the 5 percent tolerance. That means that the true value of the resistor is within 5 percent of the stated value. Radio Shack has an assortment of them in a bag, catalog number 271-308. At \$2.99, you can't go wrong.

Capacitors: There are so many kinds of capacitors that you really can only have a small sampling. The "picofarad pack," Radio Shack catalog number 272-806, is nice if you're planning to build any RF circuitry. If not, don't bother with it. For repairs, you're better off buying capacitors as you need them because you'll find you never have on hand the one you need anyway.

Transistors: Get some 2N2222 (or PN2222) transistors; and some 2N3904 and 2N3906 transistors, also. These transistors find their way into just about everything and can also be used to replace some other parts which have different numbers. Radio Shack used to carry assortments of them at about 15 for \$2, but I don't see them in the latest catalog. They still sell the 2222s in singles, though. Note that the 2N4401 is essentially the same as the 2N3904.

We'll continue this next time, and we'll also look at how to solder correctly. Till then, 73 from KB1UM.

RF

You may write Michael Geier KB1UM in care of 73 Magazine, Forest Rd., Hancock NH 03449.

The Care and Feeding of Your Pet Ham

The pet ham is one of the most intelligent of pets, often seeming almost human. The following is a short guide to some of the most important things you should know about in caring for your pet ham.

Living Area: Your pet ham should have a private area of its own where it will not be disturbed. It will spend many happy hours alone there with its collection of treasures (boxes, wires, bits of metal, glass, paper, plastic, etc.). It should be encouraged to confine

its activities to this nest room to protect the rest of the house from its natural tendencies toward noise, clutter, and making holes in the walls.

Expenses: Raising your pet ham can be an expensive hobby. However, unlike most pets, the pet ham can be trained to work outside the home for short periods of time and bring in enough money to cover part or all of its expenses.

Feeding: The well-behaved pet ham will be able to eat with the family on occasion, but it feels more comfortable and secure taking many of its meals in the privacy of its nest room.

Housekeeping: Pet hams can be trained to use the family bathroom facilities, but it may be difficult to train them to pick up after themselves in the kitchen.

Obedience Training: Most pet hams can be trained to respond to a few simple commands. The easiest to teach are "sit" and "speak." Once your pet ham has learned these behaviors, it will sometimes practice them on its own for hours at a time.

Note: Variations of the above have appeared in many ham newsletters from all over the country at different times. We do not know who the original author is. Do any of you?




STARTEK INTERNATIONAL INC FREQUENCY COUNTERS GREAT NEW MODELS - SUPER LOW PRICES

10 HZ to 3.5 GHZ

- StarCab™ ALUMINUM CABINET
- 8 RED LED DIGITS
- 3 GATE TIMES
- DISPLAY HOLD
- MMIC AMPLIFIERS
- 3-5 HR BATTERY
- NI-CAD'S & ADP
- YEAR WARRANTY
- MADE IN USA

THE NEW MODEL 3500
FROM THE ORIGINATOR OF THE "HAND HELD" COUNTERS IN THE StarCab™ STYLE CABINETS, WITH EXPERIENCE PRODUCING OVER TWO DOZEN SUCCESSFUL FREQUENCY COUNTER MODELS SINCE 1975, FRED HUFFT-W4PLM HAS DESIGNED THE 3500 WITH UNPRECEDENTED FREQUENCY RANGE, FEATURES AND QUALITY IN A VERY AFFORDABLE "POCKET SIZED" COUNTER.

COMPUTER DESIGN AND STATE OF THE ART COMPONENTS PROVIDE UNCOMPROMISED RELIABILITY AND PERFORMANCE.



A VERY SPECIAL OFFER

MODEL 1500A

\$66*

* Buy this quality 1500 MHz Counter for only \$66. when purchased with the following items:

- 1500A FREQ COUNTER \$89.00 66.00
- INSTALLED NI-CAD PACK 20.00
- 110VAC ADP/CHARGER 9.00
- 12VDC AUTO ADP/CHGR 9.00
- VINYL CARRY CASE 12.00
- TELESCOPING ANTENNA 12.00

#SO-15 \$151.00 128.00

ONLY \$128. FOR ALL 6 ITEMS

TO SUBSTITUTE MODEL 1500HS ORDER #SO-HS \$175.
2500 #SO-25 225.
3500 #SO-35 265.

1.6 GHZ PRESCALER - AMP & SIGNAL BAR GRAPH

Extend range of any counter capable of counting 16 MHz or higher to 1600 MHz with super sensitivity of 1-5 mV typ. 10 segment LED BAR GRAPH displays RF signal strength. StarCab™ aluminum cabinet. 110 VAC adaptor included.

MODEL AP-90
FACTORY ASSEMBLED
1 YEAR WARRANTY

\$99

FIND FREQUENCIES FAST with any of these great pocket sized counters, available for immediate delivery from STARTEK. Absolutely the best values in the industry, from the 1500A, now only \$89., to the new 2500 & 3500. These new full range counters feature a 1 megohm input 10 Hz to 12 MHz, a 50 ohm RF input 10 MHz to 2.4 GHz / to 3.5 GHz for the 3500. The 2500 & 3500 both feature MMIC amplifiers for maximum sensitivity, three gate times for maximum display resolution of .1 Hz to 12 MHz and 10 Hz to 2400 & 3500 MHz, a DISPLAY HOLD switch and LED indicator to hold a reading and suspend gating until turned off. Our DISPLAY HOLD switch works properly, it does not change the GATE selection when turned off, like some competitive units. All of our counters use LSI circuitry, sub-miniaturized components and low power design for portable operation of 3-5 hours from internal 600 mA/Hr NiCad batteries. For ULTRA HIGH SENSITIVITY the 1500HS can't be beat with typical sensitivity of <.5 to <1 mV RMS from 10 MHz to 500 MHz. Our 1500A offers great quality and performance at minimal cost. All counters have a full year parts & labor limited warranty. Check out our VERY SPECIAL OFFER for any model packaged with several of our most popular accessories.

1500A ECONOMY MODEL	1500 HS ULTRA HIGH SENSITIVITY	2500 FULL RANGE +HI-Z INPUT	3500 EXT RANGE +HI-Z INPUT
1-1500 MHZ	1 MHZ- 1500 MHZ	10 HZ- 2400 MHZ	10 HZ- 3500 MHZ
2 GATE TIMES	2 GATE TIMES	3 GATE TIMES	3 GATE TIMES
LESS NI-CADS & AC ADP	DISPLAY HOLD	DISPLAY HOLD	DISPLAY HOLD
\$89.	\$159.	\$210.	\$250.

- **OPTIONS for the 1500A**
- #BP-15 NiCads for 1500A (installed) \$20.00
 - #AC-15 110 VAC adp/chgr for 1500A 9.00
 - **ACCESSORIES for all models**
 - #TA-90 Telescoping BNC antenna 12.00
 - #RD-800 800 MHZ Rubber Duck-BNC 29.00
 - #CC-90 Black vinyl zipper carry case 12.00
 - #DC-690 12VDC Auto adaptor/charger 9.00


- **PROBES**
- #LP-22 Probe, Low Pass/Audio \$22.00 use with 2500 & 3500. Attenuates RF noise.
 - #P-110 Probe, freq counter or scope use, 1X, 10X. 39.00 200 MHZ scope use.

NEED MORE INFO - CALL
HAL MANDERY-KK4UN
SALES ENGINEER

ORDERS ONLY - TOLL FREE
800-638-8050

INFORMATION (305) 561-2211

TERMS: Shipping-handling charges for Florida add \$4 + tax, US & Canada add 5% (\$4 min, \$8 max), all others add 10% of total. COD fee \$3.75. Payment by VISA, MC, DISCOVER, COD for CASH or MO. Prices and specifications are subject to change without notice. CIRCLE 247 ON READER SERVICE CARD



STARTEK INTERNATIONAL INC

398 NE 38th ST., FT. LAUDERDALE, FL 33334

FAX (305) 561-9133

LOGicTM
professional
quality
ham radio
software!


Welcome to the exciting world of amateur radio! We would like to introduce you to our ham radio software -- **LOGic Jr.** for quality at a low price, and **LOGic II** for the ultimate in features and flexibility.

Good software can add more to the enjoyment of your hobby than any other accessory. You will want to keep records of interesting conversations, contacts with exotic places, third-party messages, QSL cards, etc. Wherever your interests may lead--DXing, contesting, traffic handling, rag chewing, or awards chasing, the LOGic family can handle it.

And LOGic does much more than keep records! Please ask for our free 10-page illustrated info pack. You will find our software has the most features -- like tracking for nearly any award. Auto scoring for nearly any contest. Interfacing to most computerized radios and antenna rotors. Customizable logging screen with streamlined data entry and fast, flexible, easy data retrieval.

While these products' advanced features satisfy the most experienced operator, self-explanatory menus, online help, a superb manual, & telephone support let the beginner master the basic functions quickly.


You will find LOGic is an inexpensive yet valuable addition to your station. For IBM PC, Amiga, and Atari ST. Coming for Mac.



Personal Database Applications

Dept RF
2616 Meadow Ridge Dr
Duluth, GA 30136-6037
☎ 404-242-0887

TM



Advertise in

Radio Fun

CALL

1-800-225-5083

RF review

The OXO Transmitter Kit

by Bill Brown WB8ELK

- In the U.S.: Kanga US c/o Bill Kelsey N8ET, 3521 Spring Lake Dr., Findlay, Ohio 45840.
- In the U.K. or overseas: Kanga Products, 3 Limes Road, Folkestone, Kent CT19 4AU, Great Britain.

Price: \$19.95 + \$3 shipping U.S.

For those of you new to the HF frequencies, let me introduce you to the thrills of QRP (low-power) operation. With just a watt or two of power, you can make some great contacts worldwide if conditions are right. One of the big advantages of running QRP (QRP is generally regarded as using anything less than 5 watts) is that your transmitter is going to be very small and allow you to easily operate with just a small battery. With a companion miniature receiver, you can have a blast operating portable from just about anywhere. (Two good candidates are the Simple SuperRX in the April 1991 issue of 73 and the "Sudden" receiver which will appear in the October 1991 issue of 73).

The OXO

The OXO transmitter by Kanga Products fits the bill for a very affordable and extremely easy-to-build kit. The original circuit by George Burt GM3OXX appeared in *SPRAT* (The Journal of the G-QRP Club). It was a popular circuit, so with George's kind permission, Kanga Products added it to their line-up of fine QRP kits and accessories.

Easy Beginner's Kit

The OXO was designed for the beginning kit-builder in mind. Even though the board is reasonably compact, I found it was laid out for very easy assembly. Large solder pads, with parts placed well apart, made this a breeze to put together. No need for a magnifying glass here, as all components have plenty of "breathing room."

The kit comes complete including a crystal for the QRP calling frequency for the band of your choice (160m, 80m, 40m, 30m or 20m). A crystal in the 80m Novice segment is also available.

Assembly

I found the instructions to be brief but straightforward. The parts placement diagram was easy to follow (once I determined the orientation of the circuit board) and helped make sure I got everything in its correct location.

Only one step takes a bit of patience. The RF choke consists of 30 turns of very fine gauge wire (included in the kit). It takes a while to wind this coil through the hollow core of the ferrite

bead form, but the operation went pretty smoothly (ample wire was supplied).

Final Test

After assembly, I double-checked everything to make sure I had everything in its proper place (a good idea before you power up any kit!). I mount-

ed to get this rig going. The output of the OXO should be in the neighborhood of 2 watts, depending on the band of operation you choose.

On-The-Air!

I started out on the 80 meter QRP frequency of 3.560 MHz. I hooked the OXO up to my 80 meter dipole and tried a few calls. Sure enough, a fellow from Pennsylvania came back and carried on with me for some time. He gave me an RST report of 569 and stated that my signal was nice and stable with a good sound to it. He was pretty amazed when I told him that I was running just 2 watts! It doesn't take a lot of power to communicate when interference and noise are not bad.

I tried a 40 meter crystal in the OXO on the QRP frequency of 7.030 MHz (7.035 and 7.040 MHz are other pop-

time kit builder. I particularly liked the fact that since the OXO requires no tuning, peaking or tweaking, you don't need any fancy test equipment to get it going.

Kanga Products

Kanga Products carries a fine line-up of innovative QRP kits. Quite a few of these have appeared as construction projects in the pages of *SPRAT* (The G-QRP Journal). Since a number of these projects were originally inspired by G3ROO, the name of Kanga seemed appropriate (ROO is slang for Kangaroo). In Great Britain (as well as overseas), Dick Pascoe G0BPS and partners offer the Kanga line of kits. You can reach him at the address given above. To help distribute the kits in the U.S., Bill Kelsey N8ET has offered to carry the complete Kanga line.

A catalog is available from Bill at the above address. Please enclose an SASE. I think you'll find the catalog offerings very interesting! Micro-miniature transmitters and receivers on 1-inch square circuit boards, mini-SSB transceivers, T/R switching circuits and wattmeter-SWR bridges are just a few of their many projects.

Clubs and Nets

SPRAT is a very informative journal published by Rev. George Dobbs G3RJV for the G-QRP Club. Each issue is packed full of fun QRP projects guaranteed to keep you happily building away at your workbench. Be warned that you'll be so busy building projects that you may not get a chance to actually operate for long stretches at a time. For more information about the G-QRP club and *SPRAT*, write to Rev. George Dobbs G3RJV, St. Aidan's Vicarage, 498 Manchester Rd., Rochdale, Lancs, OL11

3HE, Great Britain. You can subscribe to *SPRAT* and join the G-QRP club in the U.S. by sending \$12/year to Luke Dodds W5HKA, 2852 Oak Forest, Grapevine, TX 76051.

Another QRP group you may want to join is the QRP Amateur Radio Club, International (often referred to as ARCI). They put out a fine magazine called *QRP Quarterly* which is also packed full of great projects. Dues and subscription is \$12/yr; available from Mike Kilgore KG5F, 2046 Ash Hill Rd., Carrollton TX 75007.

The Michigan QRP club is another source of information about low power operation. Membership in their group is \$7/yr. Contact them at P.O. Box 80804, Lansing MI 48908-0804.

I think you'll enjoy your first time operating with QRP power. The most common QRP calling frequencies are 3.560, 7.030, 7.040, 14.060, 21.060 and 28.060 MHz. You'll almost always find some QRP activity in the evenings on both 3.560 and 7.030, or 7.040 MHz. There are even some QRP nets that operate periodically. One of these is the Monday evening Northwest QRP net from Washington state. Look for them around 0400 UTC (9 p.m. PDT) on 7.040 MHz. **RF**



Photo A. The OXO QRP transmitter kit.



Photo B. (L to r): Kanga U.S. rep. Bill Kelsey N8ET, George Dobbs G3RJV (editor of *SPRAT*), and Dick Pascoe G0BPS (Kanga U.K.) look over some of the latest circuits.

ular QRP frequencies). Once again, I made a number of enjoyable contacts and really had no problem maintaining contact even during fading.


Antenna switching required me to either use an antenna coax switch or quickly transfer the coax from my receiver and hook it up to the OXO each time I transmitted.

Fortunately, Kanga Products offers a T/R (Transmit/Receive) relay kit to solve this problem. If you aren't using an antenna tuner between your OXO and the antenna, you might need the optional low-pass filter board to cut down harmonics. The \$9.95 filter board is very compact and easy to assemble. It can be used with any QRP transmitter.

Impressions

I definitely had fun putting together my OXO. It's a great evening or weekend project which will produce reliable results the first time you power it up. This is the perfect kit for a first-

AEA is...



Packet...plus!

If you want the best Packet or multi-mode equipment available, look no further. These data controllers have no equal when it comes to features, performance and value.

The versatile DSP-2232 (above) is simply the most powerful multi-mode controller available to amateurs. It features Digital Signal Processing modems, dual simultaneous ports, all known amateur digital modes, Packet and AMTOR mailboxes, and much more.

The legendary PK-232MBX (top right) has long been the most popular data controller ever, and is still going strong. Includes: Chebyshev filter design, Host Mode, Signal Identification mode and more. With features like these, no wonder it's number 1.

For Packet only, the PK-88 (center) and its PC-compatible plug-in counterpart, the PCB-88 (bottom right) offer AEA's famous Host Mode, Packet maildrop, KISS mode, lithium battery-backed RAM...the list goes on and on.

When hams think of Packet, they think of AEA.

AEA is Packet...plus!


For complete information on these or any other AEA products, call the toll-free Info-Line at (800)432-8873.



**Advanced Electronic
Applications, Inc.**

P.O. Box C2160/2006 196th St. S.W. Lynnwood, WA 98036
 Technical Support (206)775-7373 FAX (206)775-2340
 Upgrade Line (206)774-1722
 CompuServe I.D. 76702,1013

All specifications subject to change without notice or obligation. ©1991 AEA, Inc. All Rights Reserved.





what next?

by Carole Perry WB2MGP

Kids Having Radiofun

Having fun in any hobby can only enhance your fulfillment and make you want to get more involved. Amateur radio offers so many opportunities for enjoyment and satisfaction that half the fun is in exploring all the possibilities. Don't be afraid to take a risk and try something new. As a new-comer to the hobby, you should make it a point to keep an open mind at all times. The more you experience and participate, the more you will begin to see why all the rest of us are so "hooked" on the adventure of ham radio.

As a teacher of teenagers, one of my greatest pleasures is helping youngsters get started in ham radio and then watching them take off in their own directions with a style all their own. The following stories feature youngsters who are having fun, learning new things, and meeting all kinds of interesting people since they got licensed. If you know of any youngsters, oldsters, or anyone in between who wants to share his or her exciting radio experiences with the rest of us, please write to me in care of this column, and let's spread the good ideas around.

Lee Kissel WA2JWR is an active ham in Staten Island, New York. It's not a surprise to learn that Lee's dad is Walter KA2YBR and his wife is Donna WA2JWQ. It's especially nice,

however, to know that his 13-year-old son is Walter KB2IOZ.

Walter Kissel KB2IOZ

I first met this charming young man when he accompanied his dad to local

the world. Walter recalled two of his memorable contacts for me. Even though he has since made several contacts with different countries in Africa, he easily remembers how excited he was with his very first contact in




Photo A. Walter Kissel KB2IOZ at the mike. His growing collection of QSL cards is on the wall to his left of his station (not shown in the photo).

club meetings. When Walter was only 11 years old and in the 6th grade, he got his ham radio license. I really loved the fact that Walter was always encouraging other children not to give up if they failed the license exam the first time.

Walter doesn't have to fight off the rest of the family to get to the radio. He has his own 10 meter rig, a Uniden HR-2600 with a Cushcraft AR-10 vertical antenna. He always loved visiting his dad's ham shack and listening in on the low bands. Working DX remains one of his favorite activities. He loves speaking with people all over

Tanzania with Thomas 5H3TW. His enthusiasm was obvious to me as he relayed the details of his contact with a ham named Zedan JY3ZH from the country of Jordan.

Two exciting experiences that Walter would like to share with others were his participation last year in the New Jersey Liberty Park Marathon, where he helped his club provide communications, and his help with the Bayonne Emergency Management Amateur Radio Club in doing an ATV (Amateur Television) demonstration at Intermediate School 72 in Staten Island.

The Kissel family recently made



Photo B. At W1AW, left to right: Burt K1OIK, Samantha KA1VBQ, KA1VBQ, and Chuck May K1MAV, who tested Samantha on the Cape.

good use of their radios on a trip to South Carolina and a vacation to Toronto, Canada. Walter had a terrific time making contacts on his 440 and 2 meter rigs. He encourages all new hams to help their family members get involved with them and join in the fun.

Samantha Fisher KA1VBQ

Samantha is a charming nine-year-old who passed her Novice exam when she was eight, and her Technician exam this year. She has worked 20 plus countries and operated W1AW for 90 minutes, handling quite a pile-up. Her dad, Burt K1OIK, tells me that, coincidentally, the person who corrected her Tech exam on Cape Cod just happened to be at W1AW when Samantha operated the ARRL station.

Among her achievements is a two-hour QSO with the Azores, in which she and a 10-year-old friend and her family talked in Portuguese to friends in the "home country." She also operated from the South Yarmouth Radio Shack during Ham Radio Day last fall.

Samantha tells me that she got interested in ham radio by hanging around her dad's shack and seeing how much fun he and his friends were having. She got on the mike as a little girl from time to time and really got caught up

in it. She loves to meet new people on the air, and has a special memory of a wonderful contact she made with a ham in Florida recently. They spoke for more than 30 minutes about everything from air-conditioning to tourist attractions to the weather. She enjoyed the idea of an adult taking so much time to speak with her on the radio.

Needless to say, Samantha and her dad take their rigs on vacation with them. She recalled how she was able to contact Burt while he was at a meeting at a convention while she remained at the pool. Like so many ham families, the Fishers are enjoying the convenience and fun of being able to stay in touch with each other when they get separated while on a trip.

When I asked Samantha what advice she would give to youngsters who are first getting into the hobby, she said, "Try to get your friends interested also, so you can have kids your own age with similar interests to talk to and plan things with."

If any of you have "beginning in ham radio" stories you'd like to share, please write me at the address below!

RF

You may write Carole Perry WB2MGP at P.O. Box 131646, Staten Island NY 10313-0006.

HELPING HAMS GET ON THE AIR! SINCE 1933

INFORMATIVE STARTER KIT INCLUDES:

- Novice and Tech Written Element Study Guide
- Practice Key and Oscillator
- Code Practice Cassette Tapes
- Theory Tapes
- FCC Rule Book
- Valuable Coupons Good Toward the Purchase of Ham Radio Equipment

PACKAGE PRICE - \$59.95

WHETHER YOU'RE AN "O.M." OR JUST A "NOVICE," QUEMENT IS SURE TO MEET ALL YOUR NEEDS!

QUEMENT ELECTRONICS

PHONE (408) 998-5900

1000 S. BASCOM AVENUE • SAN JOSE, CA 95128

FEATURING LINES BY:

ICOM

YAESU U.S.A.

ALINCO

AND THOUSANDS OF ACCESSORIES!

advertiser index

RS# Advertiser	Page	RS# Advertiser	Page	RS# Advertiser	Page	RS# Advertiser	Page	RS# Advertiser	Page
• Ace Systems	27	• Broadcast Technical Service	10	240 Jan Crystals	25	• Oklahoma Comm Center	30	250 Software Systems	25
• Advanced Electronic Application	15	184 C & S Sales, Inc.	10	2 Kawa Productions	25	• P.C. Electronics	24,25	244 Software Systems	21
				• KDC Sound	27			103 Spangler X-Pressions	21

**A
Free
Gift
from**

Radio Fun

**Use
these
money-saving
coupons on
some
great
products
from
Antennas
West**

Coupon worth \$10

toward the purchase of any AntennasWest
DX HalfSquare Antenna
at regular price (as marked on reverse side)

To redeem coupon, present it at your local ham radio store when purchasing or ordering the antenna.
If more convenient, mail your order direct to AntennasWest, enclosing coupon and check or money order. Add \$5 for shipping and handling. Allow 10 days for delivery.

coupon valid till 10/31/91

Dealer: send in coupon with your order for full value reimbursement. For details call Dealer Hotline 801 373 8425 FAX 801 375 4664

Coupon worth \$10

toward the purchase of any AntennasWest
TNT or TNT/2 Windom Antenna
at regular price (as marked on reverse side)

To redeem coupon, present it at your local ham radio store when purchasing or ordering the antenna.
If more convenient, mail your order direct to AntennasWest, enclosing coupon and check or money order. Add \$5 for shipping and handling. Allow 10 days for delivery.

coupon valid till 10/31/91

Dealer: send in coupon with your order for full value reimbursement. For details call Dealer Hotline 801 373 8425 FAX 801 375 4664

Coupon worth \$10

toward the purchase of any AntennasWest
OmniLoop Antenna
at regular price (as marked on reverse side)

To redeem coupon, present it at your local ham radio store when purchasing or ordering the antenna.
If more convenient, mail your order direct to AntennasWest, enclosing coupon and check or money order. Add \$5 for shipping and handling. Allow 10 days for delivery.

coupon valid till 10/31/91

Dealer: send in coupon with your order for full value reimbursement. For details call Dealer Hotline 801 373 8425 FAX 801 375 4664

Coupon worth \$25

toward the purchase of an AntennasWest
Bullet Tested Solar Power Supply
at regular price (as marked on reverse side)

To redeem coupon, present it at your local ham radio store when purchasing or ordering the Solar Power Supply.
If more convenient, mail your order direct to AntennasWest, enclosing coupon and check or money order. Add \$10 for shipping and handling. Allow 14 days for delivery.

coupon valid till 10/31/91

Dealer: send in coupon with your order for full value reimbursement. For details call Dealer Hotline 801 373 8425 FAX 801 375 4664

v! 12 issues for \$9.97

at the low price of \$9.97.

, call 603-525-4201).

Call

Zip

Bill me

Subscriber _____ CQ Subscriber _____

Subscription rate \$14.97.

O2M

RVICE CARD number 1991

201	202	203	204	205	206	207	208	209	210
211	212	213	214	215	216	217	218	219	220
221	222	223	224	225	226	227	228	229	230
231	232	233	234	235	236	237	238	239	240
241	242	243	244	245	246	247	248	249	250
251	252	253	254	255	256	257	258	259	260
261	262	263	264	265	266	267	268	269	270
271	272	273	274	275	276	277	278	279	280
281	282	283	284	285	286	287	288	289	290
291	292	293	294	295	296	297	298	299	300
301	302	303	304	305	306	307	308	309	310
311	312	313	314	315	316	317	318	319	320
321	322	323	324	325	326	327	328	329	330
331	332	333	334	335	336	337	338	339	340
341	342	343	344	345	346	347	348	349	350
351	352	353	354	355	356	357	358	359	360
361	362	363	364	365	366	367	368	369	370
371	372	373	374	375	376	377	378	379	380
381	382	383	384	385	386	387	388	389	390
391	392	393	394	395	396	397	398	399	400

ION

this issue of *Radio Fun* circle the
in the U.S. and possessions only.

4AWA6

GO WITH THE WORLD LEADER! The WB2OPA LogMaster HF Logging System



Now K1EA Compatible!

- Unparalleled Log Statistics.
- Auto QSO Alert Indicator.
- Auto Beam Headings.
- Auto Country, Prefix, and Zone Selections.
- Print Log Sheets, QSL Cards, and QSL Labels.
- Dual Clock Calendar.
- User Configurable.
- Search and Sort on Call Sign, Date Prefix, Country, State, CQ Zone, ITU Zone, or User Defined Fields.
- IBM Compatible.
- AND MUCH, MUCH MORE!!!

Just \$59.95 (Plus \$2.00 P & H) Complete.
(New Jersey Residents Please Include Sales Tax)


30 Day Money Back Guarantee
FREE DEMO DISK (Include \$2.00 for P & H)

Send Call and Disk Size (5.25 or 3.5) to:

Sensible Solutions

P.O. Box 474
Middletown, New Jersey 07748
(908) 495-5066
See us in Dayton at Booth 474

CIRCLE 95 ON READER SERVICE CARD



OVER 7,000 MAXCOM® STATIONS WORLDWIDE
P.O. BOX 502, FT. LAUD., FL 33302
Phone: 305-523-6369 • FAX: 305-522-8159

® MAXCOM is a registered trademark and is owned by Maxcom Electronics, Inc.
THE BOTTOM LINE: "MAXCOM WORKS"

*no how you put it
together... we are
your Best choice for
ALL FREQUENCY auto
Antennas & couplers.
novice to extra to
commercial - we
have a perfect
one for you.*

CIRCLE 101 ON READER SERVICE CARD

Radio Fun

SEPTEMBER 1991 17



what next?

by Carole Perry WB2MGP

Kids Having Radiofun

Having fun in any hobby can only enhance your fulfillment and make you want to get more involved. Amateur radio offers so many opportunities for enjoyment and satisfaction that half the fun is in exploring all the possibilities. Don't be afraid to take a risk and try something new. As a newcomer to the hobby, you should make it a point to keep an open mind at all times. The more you experience and participate, the more you will begin to see why all the rest of us are so "hooked" on the adventure of ham radio.

As a teacher of teenagers, one of my greatest pleasures is helping youngsters get started in ham radio and then watching them take off in their own directions with a style all their own. The following stories feature youngsters who are having fun, learning new things, and meeting all kinds of interesting people since they got licensed. If you know of any youngsters, oldsters, or anyone in between who wants to share his or her exciting radio experiences with the rest of us, please write to me in care of this column, and let's spread the good ideas around.

Lee Kissel WA2JWR is an active ham in Staten Island, New York. It's not a surprise to learn that Lee's dad is Walter KA2YBR and his wife is Donna WA2JWQ. It's especially nice,

however, to know that his 13-year-old son is Walter KB2IOZ.

Walter Kissel KB2IOZ

I first met this charming young man when he accompanied his dad to local

the world. Walter recalled two of his memorable contacts for me. Even though he has since made several contacts with different countries in Africa, he easily remembers how excited he was with his very first contact in



Photo A. Walter Kissel KB2IOZ at the mike. His growing collection of QSL cards is on the wall to his left of his station (not shown in the photo).

club meetings. When Walter was only 11 years old and in the 6th grade, he got his ham radio license. I really loved the fact that Walter was always encouraging other children not to give up if they failed the license exam the first time.

Walter doesn't have to fight off the rest of the family to get to the radio. he has his own 10 meter rig, a Uniden HR-2600 with a Cushcraft AR-10 vertical antenna. He always loved visiting his dad's ham shack and listening in on the low bands. Working DX remains one of his favorite activities. He loves speaking with people all over

Tanzania with Thomas 5H3TW. His enthusiasm was obvious to me as he relayed the details of his contact with a ham named Zedan JY3ZH from the country of Jordan.

Two exciting experiences that Walter would like to share with others were his participation last year in the New Jersey Liberty Park Marathon, where he helped his club provide communications, and his help with the Bayonne Emergency Management Amateur Radio Club in doing an ATV (Amateur Television) demonstration at Intermediate School 72 in Staten Island.

The Kissel family recently made



Photo B. At W1AW, left to right: Burt K1OIK, Samantha KA1VBQ, KA1VBQ, and Chuck May K1MAV, who tested Samantha on the Cape.

good use of their radios on a trip to South Carolina and a vacation to Toronto, Canada. Walter had a terrific time making contacts on his 440 and 2 meter rigs. He encourages all new hams to help their family members get involved with them and join in the fun.

Samantha Fisher KA1VBQ

Samantha is a charming nine-year-old who passed her Novice exam when she was eight, and her Technician exam this year. She has worked 20 plus countries and operated W1AW for 90 minutes, handling quite a pile-up. Her dad, Burt K1OIK, tells me that, coincidentally, the person who corrected her Tech exam on Cape Cod just happened to be at W1AW when Samantha operated the ARRL station.

Among her achievements is a two-hour QSO with the Azores, in which she and a 10-year-old friend and her family talked in Portuguese to friends in the "home country." She also operated from the South Yarmouth Radio Shack during Ham Radio Day last fall.

Samantha tells me that she got interested in ham radio by hanging around her dad's shack and seeing how much fun he and his friends were having. She got on the mike as a little girl from time to time and really got caught up

in it. She loves to meet new people on the air, and has a special memory of a wonderful contact she made with a ham in Florida recently. They spoke for more than 30 minutes about everything from air-conditioning to tourist attractions to the weather. She enjoyed the idea of an adult taking so much time to speak with her on the radio.

Needless to say, Samantha and her dad take their rigs on vacation with them. She recalled how she was able to contact Burt while he was at a meeting at a convention while she remained at the pool. Like so many ham families, the Fishers are enjoying the convenience and fun of being able to stay in touch with each other when they get separated while on a trip.

When I asked Samantha what advice she would give to youngsters who are first getting into the hobby, she said, "Try to get your friends interested also, so you can have kids your own age with similar interests to talk to and plan things with."

If any of you have "beginning in ham radio" stories you'd like to share, please write me at the address below!

RF

You may write Carole Perry WB2MGP at P.O. Box 131646, Staten Island NY 10313-0006.

HELPING HAMs GET ON THE AIR! SINCE 193

INFORMATIVE STARTER KIT INCLUDES:

- Novice and Tech Written Element Study Guide
- Practice Key and Oscillator
- Code Practice Cassette Tapes
- Theory Tapes
- FCC Rule Book
- Valuable Coupons Good Toward the Purchase of Ham Radio Equipment

PACKAGE PRICE - \$59.95

WHETHER YOU'RE AN "O.M." OR JUST A "NOVICE,"
QUEMENT IS SURE TO MEET ALL YOUR NEEDS!

QUEMENT ELECTRONICS

PHONE (408) 998-5900

1000 S. BASCOM AVENUE • SAN JOSE, CA 95128

FEATURING LINES BY:

ICOM

YAESU U.S.A.

ALINCO

AND THOUSANDS OF
ACCESSORIES!

A
Free
Gift
from

Radio Fun

Use
these
money-saving
coupons on
some
great
products
from
Antennas
West

Coupon worth \$10

toward the purchase of any AntennasWest
DX HalfSquare Antenna
at regular price (as marked on reverse side)

To redeem coupon, present it at your local ham radio store when purchasing or ordering the antenna.

If more convenient, mail your order direct to AntennasWest, enclosing coupon and check or money order. Add \$5 for shipping and handling. Allow 10 days for delivery.

coupon valid till 10/31/91

Dealer: send in coupon with your order for full value reimbursement. For details call Dealer Hotline 801 373 8425 FAX 801 375 4664

Coupon worth \$10

toward the purchase of any AntennasWest
TNT or TNT/2 Windom Antenna
at regular price (as marked on reverse side)

To redeem coupon, present it at your local ham radio store when purchasing or ordering the antenna.

If more convenient, mail your order direct to AntennasWest, enclosing coupon and check or money order. Add \$5 for shipping and handling. Allow 10 days for delivery.

coupon valid till 10/31/91

Dealer: send in coupon with your order for full value reimbursement. For details call Dealer Hotline 801 373 8425 FAX 801 375 4664

Coupon worth \$10

toward the purchase of any AntennasWest
OmniLoop Antenna
at regular price (as marked on reverse side)

To redeem coupon, present it at your local ham radio store when purchasing or ordering the antenna.

If more convenient, mail your order direct to AntennasWest, enclosing coupon and check or money order. Add \$5 for shipping and handling. Allow 10 days for delivery.

coupon valid till 10/31/91

Dealer: send in coupon with your order for full value reimbursement. For details call Dealer Hotline 801 373 8425 FAX 801 375 4664

Coupon worth \$25

toward the purchase of an AntennasWest
Bullet Tested Solar Power Supply
at regular price (as marked on reverse side)

To redeem coupon, present it at your local ham radio store when purchasing or ordering the Solar Power Supply.

If more convenient, mail your order direct to AntennasWest, enclosing coupon and check or money order. Add \$10 for shipping and handling. Allow 14 days for delivery.

coupon valid till 10/31/91

Dealer: send in coupon with your order for full value reimbursement. For details call Dealer Hotline 801 373 8425 FAX 801 375 4664

\$10 Saving on any **HalfSquare**
Present coupon at local ham radio store or send with check / money order to AntennasWest. (Include \$5 for shipping and handling. Allow 10 days for delivery.)

A Half...WHAT?

That's what he asked. Twice. I was the only DL he could hear on the band that 1st morning of the all-Asia contest. Same for another 40 JA's till the DL's with linears and quads finally got through. My 15 meter HalfSquare hung unnoticed under the eaves. Nice to be heard, not seen. Nicer to work DX without tower or amplifier. When you order add \$5 P&H.

10 M \$39.95 15 M \$44.95 20 M \$49.95 40 M \$69.95


AntennasWest

Box 50062E, Provo, UT 84605

Dealer information

801-373-8425

Dealer send coupon with order for full value redemption.



**A
Free
Gift
from**

Radio Fun

**Use
these
money-saving
coupons on
some
great
products
from
Antennas
West**

\$10 Saving on any **TNT Windom**

Present coupon at local ham radio store or send with check / money order to AntennasWest. (Include \$5 for shipping and handling. Allow 10 days for delivery.)

TNT The No-Tune Windom Antennas
complete, assembled, ready to use

No pruning. No tuning. No knobs to twist.
TNT is No-Tune on 80 cw, 40, 20, 17, 12, 10. TNT/2 is No-tune on 40, 20, 10. Work other bands w/ tuner. DX & Gain rise w/ frequency.
Ready to Use Now
Includes Custom
99 ft. RG-8x feedline

Kink-Proof
Wx-Sealed
Low Noise

No Traps or Resistors
Insulated to 3000 V
Rated 500 Watts

Dealer send coupon
with order for full
value redemption

AntennasWest

Box 50062E, Provo, UT 84605

TNT Windom \$89.95 +\$8
135 ft. long P&H

TNT/2 Windom \$79.95 +\$7
67 ft. long P&H

Dealer Hotline 801-373-8425

The TNT secret?

Feed a resonant antenna off center at a constant impedance point. Result: broad, low SWR curves, & No-tune band-switching on harmonically related bands.

New:
Custom 2KW
TNTs--add \$70

\$10 Saving on any **OmniLoop!**

Present coupon at local ham radio store or send with check / money order to AntennasWest. (Include \$5 for shipping and handling. Allow 10 days for delivery.)

In the Attic? OmniLoop™ Antennas
created by **AntennasWest**

I thought my ham days were over when we moved into the town house. But I yearned for quavery DX coming in over the pole. And I couldn't forget my old buddies on 40 SSB. Then a friend showed me his attic omniLoop. The 40 m version fits in my 40' x 30' crawl space. It hears great, and if I can hear 'em I can work 'em 40 thru 10 barefoot. When you order specify coax or balanced feed, add \$6 P&H.



20 M \$49.95 40 M \$69.95 80 M \$79.95 160 M \$99.95

Dealer send coupon with order for full value redemption. Dealer Hotline

AntennasWest Box 50062E, Provo, UT 84605 801-373-8425

\$25 Saving on **Solar Power**

Present coupon at local radio store or send with check / money order to AntennasWest. (Include \$10 for shipping and handling. Allow 10 days for delivery.)

Tough Solar Power



The \$319.95 Bullet-Tested QRV Solar Power Supply keeps your repeater on the air 'round the clock or powers your 100w HF station 60 hrs a month. Control circuit speeds charge, protects gel cells & sealed batteries. Fully assembled, QRV, portable. Easily expanded.

Dealer send coupon with order
for full value redemption

Dealer Hotline (801)373-8425

AntennasWest

Box 50062 Provo UT 84605

Subscribe
to
Radio Fun

Radio Fun

Subscribe Now! 12 issues for \$9.97

12 issues for
only \$9.97

Use this handy
order card or
Call
-800-722-7790

Get
free
information
from our
advertisers.

Send in your
free
Reader
Service Card
today!

____ YES! Send me one year (12 issues) of *Radio Fun* for the low price of \$9.97.

For instant service call toll free 1-800-722-7790 (In New Hampshire, call 603-525-4201).

Name _____ (Please print) Call _____

Address _____

City _____ State _____ Zip _____

Charge my: ☐ MC ☐ Visa ☐ Amex ☐ Payment enclosed ☐ Bill me

Card number _____ Exp. date _____

Class License _____ Year Licensed _____ 73 Subscriber _____ QST Subscriber _____ CQ Subscriber _____

Canada add \$7 plus 70¢ GST. Foreign add \$12 surface, \$36 airmail. Newsstand rate \$18. Basic subscription rate \$14.97.

O2M

Radio Fun

READER SERVICE CARD
September 1991

Name _____ Call _____

Address _____

City _____ State _____ Zip _____

Where did you get this copy of *Radio Fun*?

A ☐ Newsstand B ☐ Subscription

1	2	3	4	5	6	7	8	9	10	201	202	203	204	205	206	207	208	209	210
11	12	13	14	15	16	17	18	19	20	211	212	213	214	215	216	217	218	219	220
21	22	23	24	25	26	27	28	29	30	221	222	223	224	225	226	227	228	229	230
31	32	33	34	35	36	37	38	39	40	231	232	233	234	235	236	237	238	239	240
41	42	43	44	45	46	47	48	49	50	241	242	243	244	245	246	247	248	249	250
51	52	53	54	55	56	57	58	59	60	251	252	253	254	255	256	257	258	259	260
61	62	63	64	65	66	67	68	69	70	261	262	263	264	265	266	267	268	269	270
71	72	73	74	75	76	77	78	79	80	271	272	273	274	275	276	277	278	279	280
81	82	83	84	85	86	87	88	89	90	281	282	283	284	285	286	287	288	289	290
91	92	93	94	95	96	97	98	99	100	291	292	293	294	295	296	297	298	299	300
101	102	103	104	105	106	107	108	109	110	301	302	303	304	305	306	307	308	309	310
111	112	113	114	115	116	117	118	119	120	311	312	313	314	315	316	317	318	319	320
121	122	123	124	125	126	127	128	129	130	321	322	323	324	325	326	327	328	329	330
131	132	133	134	135	136	137	138	139	140	331	332	333	334	335	336	337	338	339	340
141	142	143	144	145	146	147	148	149	150	341	342	343	344	345	346	347	348	349	350
151	152	153	154	155	156	157	158	159	160	351	352	353	354	355	356	357	358	359	360
161	162	163	164	165	166	167	168	169	170	361	362	363	364	365	366	367	368	369	370
171	172	173	174	175	176	177	178	179	180	371	372	373	374	375	376	377	378	379	380
181	182	183	184	185	186	187	188	189	190	381	382	383	384	385	386	387	388	389	390
191	192	193	194	195	196	197	198	199	200	391	392	393	394	395	396	397	398	399	400

FREE PRODUCT INFORMATION

Reader Service: To receive more information on the products advertised in this issue of *Radio Fun* circle the appropriate number. Please allow 6 weeks for processing of inquiry. Offer valid in the U.S. and possessions only.



BUSINESS REPLY MAIL
FIRST CLASS PERMIT NO. 1 HANCOCK NH

POSTAGE WILL BE PAID BY ADDRESSEE

Radio Fun

FOREST ROAD PO BOX 278
HANCOCK NH 03449-9989



NO POSTAGE
NECESSARY
IF MAILED
IN THE
UNITED STATES



Radio Fun

READER SERVICE MANAGEMENT DEPARTMENT
PO BOX 8708
BOULDER CO 80329-8708

Place
Stamp
Here

**Subscribe
Now!**

**12 issues for
only \$9.97**

**Just mail
this card**

or

Call

1-800-722-7790

**FREE
product
information**

advertiser index

RS# Advertiser	Page	RS# Advertiser	Page	RS# Advertiser	Page	RS# Advertiser	Page	RS# Advertiser	Page
• Ace Systems.....27		• Broadcast Technical Service.....10		240 Jan Crystals.....25		• Oklahoma Comm Center.....30		250 Software Systems.....25	
• Advanced Electronic Application.....15		184 C & S Sales, Inc.....10		2 Kawa Productions.....25		• P.C. Electronics.....24,25		244 Software Systems.....21	
• Alinco.....CV2		• Cellular Security Group.....27		• KDC Sound.....27		152 Pac-Comm.....28		103 Spangler X-Pressions.....21	
194 All Electronics Corporation.....27		252 D&D Cliff Dweller Antenna.....28		234 Lentini Communications.....27		139 Palomar Telecom.....25		247 Startek.....13	
5 Antennas West.....7		• D&L Fabrication.....27		25 Madison Electronic Supply.....17		264 Palomar Telecom.....27		• Texas Bug Catcher Antenna.....8	
90 Antennas West.....8		130 Dandys.....7		101 Maxcom, Inc.....17		• Personal Database.....14		119 Tiare Publications.....25	
89 Antennas West.....12		114 E. H. Yost.....25		• Metro Printing.....17		• Quement Electronics.....16		62 TNR.....21	
107 Antennas West.....25		• Electronic Distributors.....19		• MFJ Enterprises.....5		• Radio Amateur Satellite.....8		136 Unadilla Antenna Mfg. Company.....18	
138 Antennas West.....22		193 GGTE.....18		• Michigan Radio.....7		• Radio Buffs.....27		• Universal Radio.....25	
135 Antennas West.....27		64 H & M Jewelry.....27		114 Mr Nicad.....25		279 RAI Enterprises.....17		• VIS Study Guides.....25	
• Astron Corporation.....11		23 Hart Publishing.....18		91 National Tower Company.....12		• Ramsey Electronics.....9		• Vanguard Labs.....28	
• Barry Electronics Corporation.....3		• Icom.....CV4		• New Dimension QSL's.....28		153 Satellite City.....29		14 VHF Communications.....25	
105 Battery Tech, Inc.....23		• Interflex Systems.....22		82 Ocean State Electronics.....20		95 Sensible Solutions.....17		• Yaesu Electronics Corporation.....CV3	
						294 Skyhook Supply.....21			

★ **MADISON SHOPPER** ★

ORDERS: 1 (800) 231-3057
1 (713) 729-7300 or 729-8800
FAX 1 (713) 358-0051

YAESU



FT-990
New All-Mode HF Transceiver
CALL FOR DETAILS!!



FT-470
2 Meter/440 MHz Handheld Loaded With Features
CALL FOR DETAILS!!



FT-411E
Maximum Performance
2 Meter Handheld
CALL FOR DETAILS!!

MADISON
 12310 ZAVALLA STREET • HOUSTON, TEXAS 77085

CIRCLE 25 ON READER SERVICE CARD

Budget QSLs
\$39/1000
 plus \$3.75 Shipping in U.S.

★ **RAISED PRINTED** ★
BEAUTIFUL, GLOSSY INK

Thought you couldn't afford really good QSLs? These high quality RAISED PRINTED cards can be in your hands for only 4¢ each! Your choice of 4 colors of 67 lb. bristol stock: Gray, Yellow, Blue, Ivory. We print in blue ink in the format shown. If you don't want the state outline, we can remove it and make the call sign larger to balance the card. NO EXTRA CHARGE for ARRL logo, or extra wording if we have the room. Order with confidence, these are the best value in Ham Radio today! Your satisfaction is guaranteed. Send your check or call us if you have MasterCard or Visa.

Need a custom card? Call (318) 443-7261.



DENNIS WA5QMM

NETWORK QSL CARDS

P.O. Box 13200 - Alexandria, LA 71315-3200
 (318) 443-7261 or FAX your order to:
 (318) 445-9940

High Performance Software by WA7RAI

QUICKYAGI II.....\$40.00

- 100% computer-designed yagis for non-tech users.
- Auto optimizer; optimum gain, F/B & bandwidth.
- Auto/manual modes. • 2 - 12 elements to 500 mhz.
- Fastest analyzer available; calculates gain, F/B, and impedances in seconds (instantly w/math co-proc.).
- Log or linear el. & az. polar plots w/ beamwidth.
- Easiest to use of all yagi modeling programs.
- Accuracy verified. • ARRL lab tested. • Includes 2 versions; for math co-proc. & no math co-proc.
- Req. 360k & Hercules, CGA, EGA, or VGA graphics.

These utils. are incl. in all "PLUS" pgms:

- Prog. time-zone clocks. • 200 yr calendar. • 15 min QSO timer. • DXCC d-base w/ beam-head.
- Notepad w/ auto date reminder.

These features are in all Log pgms:

- Prints mailing labels & batch QSL reports. • Scrolling log display w/ spreadsheet type data entry. • Hot keys.
- Prog. auto entries. • Search/modify files. • Tracking cell w/ sort. • Auto Call search. • Personal D-base. • Auto country entry. • QSL tracking. • On-screen help.

The following are in all "X" pgms:

- Kenwood Tx/Rx control & display. • Auto Rx log entries (log only).

The following are in all "II" pgms:

- A fully integrated CW autokiller w/ • 9 prog. TX buffers
- Macro keys. • S-40wpm. • Auto SN
- RS-232/Tx key interface incl

AUTOLOG PLUS.....\$25.00
AUTOLOG PLUS-X.....\$35.00
AUTOLOG PLUS II.....\$45.00
AUTOLOG PLUS II-X.....\$55.00
AUTOKEY PLUS.....\$30.00
AUTOKEY PLUS-X.....\$45.00
QSO MANAGER (Plus-X).....\$25.00

For PC/XT/AT and Compatible.
 5.25" & 3.5" floppies. Add \$3.00 if outside U.S. and Canada. Az. orders add 5.5% state tax.

CALL SIGN REQUIRED W/ ORDER.
 *Requires computer ready transceiver

RAI ENTERPRISES, #508 N. 48th Dr. Phoenix, AZ 85031 USA

CIRCLE 279 ON READER SERVICE CARD

GO WITH THE WORLD LEADER!
The WB2OPA LogMaster
HF Logging System



Now K1EA Compatible!

- Unparalleled Log Statistics.
- Auto QSO Alert Indicator.
- Auto Beam Headings.
- Auto Country, Prefix, and Zone Selections.
- Print Log Sheets, QSL Cards, and QSL Labels.
- Dual Clock Calendar.
- User Configurable.
- Search and Sort on Call Sign, Date Prefix, Country, State, CQ Zone, ITU Zone, or User Defined Fields.
- IBM Compatible.
- AND MUCH, MUCH MORE!!!

Just \$59.95 (Plus \$2.00 P & H) Complete.
 (New Jersey Residents Please Include Sales Tax)

30 Day Money Back Guarantee


FREE DEMO DISK (Include \$2.00 for P & H)

Send Call and Disk Size (5.25 or 3.5) to:

Sensible Solutions
 P.O. Box 474
 Middletown, New Jersey 07748
 (908) 495-5066
 See us in Dayton at Booth 474

CIRCLE 95 ON READER SERVICE CARD

MAXCOM



AUTOMATIC ANTEN FOR ALL S.S.B.

OVER 7,000 MAXCOM® STATIONS WORLDWIDE
 P.O. BOX 502, FT. LAUD., FL 33302
 Phone: 305-523-6369 • FAX: 305-522-8159

© MAXCOM is a registered trademark and is owned by Maxcom Electronics, Inc.
THE BOTTOM LINE: "MAXCOM WORKS"

no matter how you put it together... we are your Best choice for ALL FREQUENCY Antennas & couplers. novice to extra to commercial- we have a perfect one for you.



radio magic

by Michael Bryce WB8VGE

There is one mystery no one has ever solved—what is the best radio for a newcomer to the hobby to get? Pick up a magazine. Thumb through it. Ah yes, those slick color pages just make you want to jump up and buy. You're totally surrounded by specifications, features, and possibilities!

The cost of starting in any new hobby can vary. Most importantly, cost can determine if you stay with a new hobby. No one that I know of likes the idea of shelling out lots and lots of money on something they aren't sure about.

But there is another way to look at this. My favorite example is bass fishing. You can get a pole, some fishing line, sinkers and a tin of worms. Wade out in the water and have one heck of a good time. Minimum money spent with maximum fun output! On the other hand, you could spend lots of money on the best computer controlled fishing pole. Electronic fish finders, bass boat, boat trailer, and of course, a 4x4 truck to haul the entire load to the lake in.

Now, the guy with the boat might hook bigger fish than you, the guy with

the pole, but will he have more fun? And will the guy with all the fancy gear necessarily hook bigger fish? Maybe, maybe not. As the old saying goes, "All fishermen are liars except you and me, and I'm not sure about you."

What Really Counts

What does this have to do with ham radio? Plenty. It's not how much money you spend, but the FUN you get for your money. I don't know about you, but I don't like to do anything unless it's FUN.

Since money is often tight when you start a new hobby, let's take a look at some of the used gear you might find at a hamfest or store. What kind of used radios are out there? While this should not be taken as the last word on radio buying, it should give you a good idea of what to look for around the hamfest's flea markets.

Before the new codeless ticket became fact, the newcomer to ham radio was more or less forced to a CW-only transmitter or transceiver. That thinking just doesn't cut it anymore. When

looking for a used rig, go for SSB as well as a radio with good CW features.

There are several "got's to do" before starting out. First, you'll need to have a budget. Just how much money are you willing to spend? Do you have the skills needed to fix a broken radio? Do you have a certain name brand in mind? How about band coverage? The radios without the WARC bands (that's 30, 18 and 12 meters) can sometimes be cheaper to pick up than those that cover all the bands. How about any special features, such as fast QSK (full break-in) for AMTOR or packet? A separate receiver and transmitter usually cost less, but can sometimes be harder for the new ham to work than a transceiver. And what about the age of the gear?

Oldies but Goodies

Some of the older gear from the '50s and '60s are real workhorses—and weigh about as much. They're big and heavy and require a lot of juice to operate. Names like Hallicrafters, Collins, and Hammarlund were the big ones. Some of the smaller guys had names like Harvey Wells Band Master and Johnson Radio. Most of the rigs from the '50s did not work on SSB (it wasn't out at the time), but they all do a good job on CW. Some will operate AM if the mood strikes your fancy. Yes, some AM is still used on the ham bands; not much, but it's out there.

From the late '60s to the '70s, the radio gear changed dramatically. The

transistor was beginning to show up in receivers. Some manufacturers began using transistors in the early stages of the transmitter with a tube final (sometimes with more than one tube) to provide most of the power to the antenna. This is known as a hybrid design. It uses the best of both worlds: The transistor in the low power stages in both the receiver and transmitter; with tubes in the higher power stages of the transmitter.

By the middle of the '60s, SSB was becoming standard, with AM transmitter slowly going by the wayside.

In the latter part of the '70s, the transistor final became standard. Transistor finals can produce 200 watts of input power with no trouble.

Names like Drake, Ten-Tec, and Yaesu share in the spotlight along with Hallicrafters and Collins. Heathkit had a strong line of kits for the hams. Sadly, Heath dropped their entire line of ham radio equipment this year. Some of the most popular models were the DX-100 and the newer HW series. The

tubes inside of our radios disappeared, giving way to 100 percent solid state. The transceivers were also becoming much more complex. Multiple VFOs and digital readouts were jammed into little boxes. Kenwood and ICOM were becoming very popular with hams. Especially Kenwood's TS-520.

With the invention of the microprocessor, ham radio really got a boost. By the middle of the '80s, microprocessor controlled radios started to show up everywhere, from hand-held 2 meter handie-talkies to full blown HF transceivers.

Along with the microprocessors, surface mount technology (connecting components directly to foil patterns without using holes) has made repair of these marvels almost impossible for the average ham.

Who's left? ICOM, Kenwood, Yaesu, and the only American company still making amateur gear, Ten-Tec. Hammarlund is no more, and Collins went to military and government contracts. Hallicrafters tried one more time

with their FPM-300 series to compete against the imports—and lost. Drake came out with their all solid state radios, TR-7 and TR-5. Lack of sales forced Drake out of the ham business and into other fields. (On a good note, earlier this year, Drake came back with their R-8 short-wave receiver.) Of course, there are dozen of names that have come and gone over the decades. Some you'll find in the hamfest, some only in memories.

Next time we'll look at some of the specifications you should be able to understand so that you can solve some of the mysteries of buying a used ham transceiver.

RF

Write Michael Bryce at 2225 Mayflower NW, Massillon OH 44646. Please enclose an SASE.




Photo A. Old and heavy, but still able to produce a signal you'll be proud of.



Photo B. Hallicrafters receivers and transmitters with a Johnson Viking VFO comprise this setup.

Heath HW-101 can still be heard on the air today. They're not very expensive to pick up, and you can fix 'em if they're broke.

New Technology

By the end of the decade, most of

UNADILLA ANTENNA MANUFACTURING CO.
PO Box 4215 BV Andover MA 01810

(508) 474-8949 24 Hour FAX
(508) 475-7831 9-5 EST M-F

THE BIG SIGNAL
Amateur Antenna Kit

40/80 Meter Antenna Kit
For "Perfect Dipole" SWR

Quick Installation—Nothing Else to Buy

A complete kit includes:

- W2AU 1:1 Balun (all stainless steel Hardware)
- W2VS KW-40 Traps (pair)
- End-sulators™ (pair)
- #14-7 Copper Wire (125')
- Installation & Pruning Instructions

Get "perfect dipole" (low SWR) operation on both bands, plus "second resonance" operation on 10, 15 and 20 meters. Complete instructions results in a quick, accurate installation and pruning to low operating SWR.

Every component in the 40/80 meter kit is an old line, reliable UNADILLA product, time tested with hams for over 20 years.

Contact Your Local Ham Dealer Today!!!
To order direct call (508) 475-7831 or write for our informational brochure on our other fine products
Baluns-Antenna Kits-Filter-Counter Insulators-ENDsulators™-Coaxial Relays
All products come with a 30 Day Warranty

-NOTICE-
We are the **NEW** manufacturers of the original
JAMES MILLEN™ Products
(508) 975-2711 9am-5pm EST M-F

SCARED OF THE CODE?

IT'S A SNAP WITH THE
ELEGANTLY SIMPLE MORSE TUTOR
ADVANCED EDITION FOR BEGINNERS TO
EXPERTS — AND BEYOND

Morse Code teaching software from GGTE is the most popular in the world—and for good reason. You'll learn quickest with the most modern teaching methods—including Farnsworth or standard code, on-screen flashcards, random characters, words and billions of conversations guaranteed to contain every required character every time—in 12 easy lessons.

Sneak through bothersome plateaus in one tenth of a word per minute steps. Or, create your own drills and play them, print them and save them to disk. Import, analyze and convert text to code for additional drills.

Get the software the ARRL sells and uses to create their practice and test tapes. Morse Tutor Advanced Edition is approved for VE exams at all levels. Morse Tutor is great—Morse Tutor Advanced Edition is even better—and it's in user selectable color. Order yours today.

For all MS-DOS computers (including laptops). Available at dealers, thru QST or 73 or send \$29.95 +\$2 S&H (CA residents add 6% tax) to:
GGTE, P.O. Box 3405, Dept. MF,
Newport Beach, CA 92659
Specify 5" or 3" inch disk
(price includes 1 year of free upgrades)

73

NEW!

Amateur Radio
Mail Order Catalog

★ UPDATED EVERY JULY! ★

Hundreds of ham products and services you never knew existed, alphabetized in the **AMATEUR RADIO MAIL ORDER CATALOG!** Plus...In the back is a **Directory of 100+ FREE CATALOGS.** Perfect for the newcomer or veteran ham who wants **ONE SOURCE BOOK** for everything from Antennas to Wire. All listings include address, phone, fax, and detailed descriptions of the product or service.

☐ Single issue: \$6.00 + \$1.25 s&h. Mail check or money order to:

HART PUBLISHING
767 So. Xenon Court • #117
Lakewood, CO 80228

You'll use this catalog more than any other publication!

A Place to Put It All

Build this custom desk for your new station.

by Stephen W. Gibson WB4NBI

If you have spent most of your funds on your rig and the accessories, and need something to put it all on, this desk may be the answer to your problem. With a little support, you can begin your chase for a spot on the DX Honor Roll.

Designed to be made from standard-size, off-the-shelf lumber, it requires a minimum of sawing—and absolutely no soldering! For the necessary sawing, an ordinary hand saw is sufficient. You can drill the holes for the screws that hold it all together with the common 1/4" drill found in almost every toolbox.

desk surface to give me sufficient room to operate the key under the shelf. It also gives me space to keep my log and a calendar for skeds.

The top shelf, 7" up from the first shelf, takes my Argosy transceiver and power supply with ease. If you have several rigs to accommodate—lucky you!—you can put the power supplies on the lower shelf, against the floor braces.

Construction

When you have decided on the dimensions most suitable for you, cut the lumber to fit. For my desk, I got

will help the joints. You can apply glue to every mating surface before putting the screws in. Countersink the screw holes and, after the final tightening, fill them with plastic wood. If you don't have a countersink, you can use pan-head screws.

All of the corners and edges should be rounded slightly with sandpaper. Fine grade will do. Give the desk top special attention so that it will be as smooth as possible. A final sanding with extra-fine sandpaper will finish the job.

Last, you can paint the desk in the color of your choice. Or you can stain




Figure. This drawing can give you a good idea of what the finished desk looks like.

The sides and shelves are 1" x 12" shelf lumber, while the operating surface is a piece of 3/4" plywood measuring 24" x 48". You can get plywood in this size at most lumber yards in this area, and, I presume, in the rest of the country. The shelf supports and the braces at the bottom of the sides are made from 1" x 2" lumber. If the 48" width is too wide for the space available in your shack, the desk surface and the shelves can be cut to fit whatever space you have.

The distance from the surface of the desk to the floor, and the spacing between the shelves, can be varied. For me, 27" from the surface of the desk to the floor is just right, but if you are taller or shorter, you can adjust the distance to fit. Use the height of a table or desk you're comfortable at.

I positioned the first shelf 4" from the

one 8-foot-long piece of 1" x 12" lumber and sawed it in half to make the sides. Then I got two more pieces of lumber the same size, and cut them in half for the shelves and the desk top support.

The 1" x 2" supports for the shelves and the sides, probably about 11-1/2", while the supports for the desk top and the floor braces were cut to 24".

The only cutting that's not straightforward involves the notches. You will have to cut them at each end of the 1" x 12" desk top support to fit around the 1" x 2" desk top side supports for a snug fit.

You might want to put a length of 1" x 2" on the back edge of the desk top so that your pencils, papers, or key cannot slip off.

To put the operating desk together, use #8 x 1" wood screws. I spaced mine about 4" apart at every joint. Glue

it, or use one of the stain/polyurethane combinations to make it attractive.

Cost and Materials

In the fall of 1990, in the Washington DC area, knot-free Douglas fir was the most expensive wood available. Making the desk out of it would have cost about \$85, including the screws. Laminated pine, made of 1" x 2" strips glued together under pressure, lowered the cost to \$62. Plain shelf lumber, laughingly called "knotty pine," was \$48. You have to be very careful if you select lumber in this cheapest grade, of course. In particular, look out for warped boards, and boards with large knots and rough areas. The finish will add another five or ten dollars, depending on what you get, to the total cost.

RF

Stephen W. Gibson, 2130 Golf Course Dr., Reston VA 22091.



DAIWA



DAIWA'S Quality Continues...

Proven Reliability for Today's Amateur.


Cross Needle SWR/Power Meters for All Bands



CN-101

Model	Freq. Range Int. Sensor	Forward Power	Connectors
CN-101	1.8-150 mHz	15/150 W/1.5 kW	SO-239
CN-103	140-525 mHz	20/200 W	SO-239 or N
NS-660A/PA	1.8-150 mHz	30/300 W/3 kW	SO-239
NS-663BM/BN	140-525 mHz	30/300 W	SO-239 or N type

Digital SWR/Power Meters for All Bands




DP-830

Model	Freq. Range Int. Sensor	Forward Power	Connectors
DP-810	1.8-60 mHz	0-1.5 kW/0-15 W	SO-239 or N type
DP-830	1.8-150 mHz	0-1.5 kW	SO-239
DP-820	140-525 mHz	0-150 W	SO-239 or N type

Mobile/Base Cross Needle SWR/Power Meters



CN-520




CN-410M

Model	Freq. Range Int. Sensor	Forward Power	Connectors
CN-520	1.8-60 mHz	200/2000 W	SO-239
CN-410M	3.5-150 mHz	15/150 W	SO-239
CN-460M	140-450 mHz	15/150 W	SO-239
CN-465M	140-450 mHz	15/75 W	SO-239

Coaxial Switches

	CS-201 2 Position	CS-201GII 2 Position	CS-401 4 Position	CS-401G 4 Position	
Frequency:	500mHz	1.3 GHz	800 mHz	800 mHz	CS-201
Connectors:	SO-239	N type	SO-239	N type	
Isolation:	+60 dB	+60 dB	+50 dB	+50 dB	
Power Rating:	2.5 kW PEP 1 kW CW	2.5 kW PEP 1 kW CW	2.5 kW PEP 1 kW CW	2.5 kW PEP 1 kW CW	CS-401

Power Supplies



PS-304

Daiwa power supplies use the latest hi-tech circuitry and components providing reliable, regulated DC Power. Short circuit protection protects the power supply in the event of accidental shorting. Crowbar protection protects your rig in the unlikely event of power supply failure. All Daiwa Power Supplies are 120V 50/60 Hz. Also available 220V 50/60 Hz.

Model	PS120M	PS140II	PS304	RS3080	RS40X
Voltage	3-15	13.8	1-15	1-15	1-15
Current(ICS)	12A	14A	30A	33A	40A
Current(Cont.)	9.2A	12A	24A	30A	32A
Ripple(Max)	3mV	3mV	3mV	3mV	3mV
Regulation	1%	1%	1%	1%	1%
Cooling Fan	NO	NO	NO	YES	YES
Size(inches)	5x4x9	5x4x9	7x6x9	7x6x9.5	11x5.5x9
Weight(lbs.)	11	11	16	21	22

NEVADA

WB1300
Receive:
25-1300 mHz



Height: 5'6"
Weight: 2.2 lbs.
Connector: "N" Type

The ultimate wide-band omnidirectional antenna. Not only excellent, on receive it will handle up to 200 watts, 50-1300 mHz. All stainless steel for years of reliable service. Great Scanner antenna indoors.



CLP5130-1
50-1300 mHz

This high gain, wide-band VHF/UHF antenna is excellent for DXing, amateur radio, FM broadcast, scanners, VHF/UHF television, government, cellular and business band use. The forward gain is 10-12 dB, front to back ratio 15 dB, 23 elements, transmit power to 500 watts. Boom length 5.8 ft., VSWR 2.0:1 or less, max. Longest element 9.8 ft., weight 11 lbs. wind survival 90 mph. CLP5130-2, 105-1300 mHz also available. 19 Element Boom 4.6 ft. Element 4.6 ft.



High grade aluminum
Roof Towers for your
antenna requirements.
Guying is recommended
to insure safety.



Model	Height	Base Width	Max. Wind Load Ft ²	Max. Vert. Load Lbs.	Weight
CR18	5'10"	31 1/2"	21 @ 90 mph	440	18
CR30	9'10"	39"	27 @ 90 mph	1,322	33
CR45	14'9"	39"	23 @ 90 mph	881	57



Electronic Distributors Co.
325 Mill Street N.E. • Vienna • VA 22180
Ph 703-938-8105 FAX 703-938-6911
Contact Your Favorite Dealer For Details



A Buyer's and Repair Guide to Flea Market Bargain

Buy a rig for \$50 or less!

by Joel J. Levine WB2BMH

Every time I go to a hamfest I hear the same complaint from the old-timers. It goes something like this: "When I got started in this hobby, I bought my first rig with spending money from

(fill in the blank with 'paper route,' 'allowance,' or 'bottle returns') and now the cheap-est rigs cost \$1,000."

Usually I break in and tell the guys that used rigs have never been cheaper in relation to income than they are today, and give a few examples. Everybody nods in agreement, and then the topic changes to Yaesu, Kenwood, ICOM, or another of today's high-priced goodies.

I own an ICOM 730. It's a very nice unit, and I'm not knocking modern equipment; but if you are on a limited budget, or if you are like me and want a little challenge but don't have the skill or money to home-brew, you could consider some of the older SSB transceivers built in the 1960s.

The good news is that there are many bargains available at flea markets for \$50 or less. That's right—a complete SSB transceiver with good sensitivity, excellent selectivity, and an on-the-air signal which cannot be distinguished from today's highest-priced equip-

ment. The bad news is that some of this equipment needs work: usually, but not always, new tubes and alignment. If you want to be an appliance operator, this game is not for you because

most of the manufacturers are out of business. If you do not do it yourself, repair service can be hard to find and expensive. Believe it or not, in the last

two years my dad, W2RKC, and I have bought seven



Photo A. Eico 753.




Photo B. Galaxy V.

transceivers with AC or AC and DC power supplies for less than \$30 each, and put them on the air for less than \$15 in parts each. And we did not buy every "bargain" we saw. This isn't a story about the guy who bought (stole?) a mint KWM-2 from a widow for \$50.

These are standard flea market items readily available if you know what to look for and have the patience to wait and find it.

I am going to share our secrets with you and tell you which models to look for and how to determine if the equipment is a good buy, and give you some pointers in basic servicing.

What to Buy

The rigs we look for are the early SSB transceivers from Swan, National, Hallicrafters, Heath, SBE and Galaxy. These complete ham rigs have crystal or mechanical filters, providing receiver performance comparable to modern equipment, and transmitters delivering 150 to 200 watts PEP input or more. Unlike the rigs of today, these early economy jobs were quite different from each other. Some were made from kits, most are single band or triband units, and some but not all have provisions for CW.

Mechanically and electrically, they are different from a modern rig. Most are tube jobs (a few transistors pop up in the VFO and audio circuits) with mechanical dials and frequency calibration in 5 kHz increments. Integrated circuits were not yet in consumer products, so the circuits are very straightforward. Some of the chassis have printed circuit boards, but most are point-to-point wiring. These units are surprisingly compact with typical dimensions of 5"H x 15"W x 12"D.

The tribanders covered 20, 40 and 75/80, and the five-banders also covered 10 and 15 meters. Some of the five-banders have only a limited portion of 10 meters.

Table 1 lists some of the models which may be available for \$50 or less.

How to Buy It

Asking the current owner for a report on the condition of the rig is not a reliable way to select your unit. Some sellers are disposing of equipment for someone else and do not know firsthand the condition of the rig. Others have not tried their unit in years. And, unfortunately, a few scoundrels lie.

The first thing to do is inspect the equipment. Does it look like it has been tampered with? Are screws missing from the cabinet, or are the screw heads worn out from abuse? Avoid any unit that has been modified or has



Photo C. Hallicrafters SR-150.



Photo D. Heathkit HW12, 22 or 23.

parts missing. If electricity is available, plug it in and listen for a receiver signal.

If you have a dummy load, bring it with you to the flea market and park it in your car until needed.

If no power is available, carry a screwdriver and ask permission to remove the

cover. Look for signs of tampering, such as missing parts. Do not be overly concerned if the capacitors or rectifiers

in the power supply have been changed. This is a common minor repair. Look for signs of rust on the chassis. Some slight discoloration is acceptable, but you do not want a rig that looks like it was salvaged from the wreck of the *Andrea Doria*. Turn the dials and controls. They should move freely and easily.

Ask about spare tubes and manuals. If the manual is not available, think twice about the purchase since a replacement, if you can find one, may be costly. (Several vendors advertise replacement manuals in the classified ad section of ham magazines.) Also ask about a microphone. If none comes with the unit, check the seller's table. Microphones are bountiful in flea markets, and several times I have convinced sellers to throw in a mike. If no mike is provided, make certain

that you have a mike plug compatible with your unit. If not, the flea market is the place to pick one up.

Look at the power supply and determine if it is the same make as the transceiver. If it is not, it will probably work, but you may have to tinker to get the correct bias voltage.

If the power supply is home-brew, be prepared to purchase another power supply. I have seen home-made units with very unsatisfactory regulation and voltage readings.

How much should it cost? That's between you and the seller. I have seen most of the units listed in Table 1 sell for less than \$50 in flea markets in New York, New Jersey and Florida. I have also seen many of these units with asking prices far in excess of \$50, and sometimes as high as several hundred dollars. The seller has the right to ask any price, and the buyer has the right to counteroffer or decline to purchase. Last year I was offered an SBE-33 for \$125 and I declined. A few weeks later I bought one for \$15. Due to limited availability in your part of the country, you may have to pay more.

Table 1. Common Models for \$50 or Less.

Manufacturer and Model	Bands	CW	VOX	Comments
EICO 753	3	Y	Y	Nicknamed "Seven Drifty Three."
GALAXY III	3	Y	Y	Nice dual vernier dial.
V	5	Y	Y	Same as III but five bands.
HALLICRAFTERS SR150	5	Y	Y	Receiver offset tuning.
SR160	3	Y	Y	Receiver offset tuning.
SR500	3	Y	Y	Same as SR160 except 500W PEP.
HEATHKIT HW12, HW12A	20 M	N	Y	"A" models have upper and lower SSB.
HW22, HW22A	40 M	N	Y	
HW32, HW32A	75 M	N	Y	
NATIONAL NCX-3	3	Y	Y	AM capability (SSB with carrier inserted).
NCL-200	5	Y	Y	
SBE 33	80, 40, 20, 15	Y	Y	Transistorized except final amp. AC and DC supplies built in. 135W PEP. Separate models for 10-15-20-40-80. 200 or 400 Hz coverage per band.
SONAR	1	Y	Y	
SWAN 120	20 M	N	N	120W PEP.
140	40 M	N	N	120W PEP.
180	80 M	N	N	120W PEP.
240	3	Y	N	
350	5	Y	N	400W PEP, dual vernier dial, VOX option.
260 (Cygnat)	5	Y	N	Built-in AC and DC supplies.

Notes: 1. Three-band units cover 20, 40 and 75/80 meter bands. Five-band units also cover 10 and 15 meters. Some units cover only part of the 10 meter band.

2. All transmitters are 150 to 240 watts PEP input unless otherwise indicated.

3. All units were made between 1962 and 1969.

4. Other transceivers made during this period, but generally not available within the price range described: Collins KWM-2, Drake TR3, TR4, Hallicrafters SR400 and SR2000, National NCX-5, SBE 34, Heath HW100 and SB100. Some of these units sell for \$100 to \$200 and also represent an excellent value.

OCEAN STATE ELECTRONICS

MAKE CIRCUIT BOARDS THE NEW, EASY WAY WITH TEC-200 FILM

JUST 3 EASY STEPS

- Copy circuit pattern on TEC-200 film using any plain paper copier
- Iron film on to copper clad board
- Peel off film and etch

Convenient 8 1/2 x 11 size With Complete Instructions

1 SHEET \$1.55
5 SHEETS \$6.25
10 SHEETS \$10.75

DELUX CODE KEY

Adjustable, heavy duty brass base with ball bearing pivots. Designed for hard usage. 3/16" plated contacts. The perfect code key for the beginner or experienced operator

\$10.75

COAXIAL CABLE

Low Loss, High Quality 50 OHM Cable

RG8U \$59/FT
RG8X (MINI RG8U) \$30/FT
RG58 \$16/FT

Must order in multiples of 25 feet, 25 foot minimum purchase required

ANTENNA CENTER CONNECTOR

- Small, rugged, light-weight, weatherproof
- Replaces center insulator
- Handles full legal power and more
- With SO 239 connector

\$10.25

ANTENNA INSULATOR

Light-weight, durable molded tenite plastic. Dielectric strength is comparable to its ceramic predecessor without susceptibility to cracking or breakage under impact or severe temperature change. Weatherproof

\$2.00/pair

ANTENNA WIRE

The ideal wire for making antennas. Strength is achieved with copper coated steel wire, stranded for greater flexibility and ease of handling. The copper assures excellent conductivity and good soldering properties. The wire is #14 copperweld made up of 7 strands of #22 wire

\$15/foot
Must order in multiples of 25 feet, 50 foot minimum purchase required

CODE PRACTICE OSCILLATOR KIT

As appeared in premier issue of *Radio Fun*. All components, additional hardware, an etched and drilled PC board, and enclosure.

Copy of article included with kit.

THE PUBLISHERS OF *RADIO FUN* IN NO WAY ENDORSE THIS PROJECT KIT.

\$9.95

AFFORDABLE DIGITAL MULTIMETER

19 RANGES
3 1/2 DIGIT LCD DISPLAY
DCV - 1000
ACV - 750
DCA - 10A
RES - 2 MEG
DIODE CHECK

\$24.95

TO ORDER

Call 1-800-866-6626

OR WRITE
OCEAN STATE ELECTRONICS
P.O. Box 1458
Westerly, R.I. 02891

Minimum order \$10.00 • Include \$4.00 S/H
R.I. Residents add 7% Sales Tax
ORDERS RECEIVED BY 1:00 PM EST-SHIP SAME DAY!

CALL 401-586-3080 OR WRITE FOR OUR FREE 36 PAGE CATALOG.

CIRCLE 82 ON READER SERVICE CARD

Even if you pay \$75, you will still be getting a bargain for many of these units.

While you are still at the flea market, you may want to pick up spare tubes at flea market prices. Commercial tube dealers charge outrageous prices these days.

How To Fix It

If you were able to plug the unit in at the flea market, you are way ahead at this point. If you're already home with the unit, I recommend that you go slowly. Remove all the tubes, plug in the unit, and turn it on. Sniff for overheating or burning parts. If it passes the sniff test, check voltage readings off the socket which connects the power supply and transceiver. Be careful of the B+ on the finals, which will be close to 1,000 volts. As soon as the unit is turned off, bleed the B+ by shorting the final amplifier plate cap to ground.

If the voltage readings appear normal, insert all the tubes except the final amplifier tubes, then turn the unit on. Do your testing on 75 meters, since marginal circuits will work better at a lower frequency. At this point you should have normal receiver function. If not, look for easy-to-repair problems. Try headphones, for example. A ham once sold me a Yaesu FT-101 which "needs an alignment or something." When I took it home, I discovered that the internal speaker was bad. I plugged in an external speaker, and put the rig on the air.

If there are problems, check the tubes. The best way is by substituting with known tubes. If you do not have a set of tubes, find a ham with a good mutual-conductance tube tester.

Once you have the receiver working, plug in the final tubes. Remember to shut off the power and bleed the power supply. Turn the rig on and follow the manufacturer's directions for setting the bias. If you do not have a manual, a good rule of thumb is 20 mA of current for each final amplifier tube.

If the unit transmits but does not modulate, check the mike cable. Some units use the same type plug with a different pin setup, so be sure to check the hookup as described in the manual. Often mike cables fray from normal use, and the wires break internally, so check the mike cable for continuity. Repeat power output tests on the highest frequency in the unit. Weak amplifier tubes may have full output on 75 meters, but practically nothing on 10 meters. Even new tubes typically output one-third less power on 10 meters than on 75 meters.

Another consideration is the quality of the electrical and mechanical connections. This is particularly troublesome in kit units because of the variable quality of the solder joints. When a kit gives me trouble, I resolder

all the connections by removing any excess solder that caused improper cooling and unpredictable electrical contact, then I reheat all the points until the solder flows smoothly around the connection. I bought an HW-100 several years ago from a frustrated kit builder who completed the unit, meticulously retraced the placement of each part, and still could not get the box working. I resoldered everything in sight and had the HW aligned in 30 minutes.

Switches and relays can be problematic. An intermittent transmitter or receiver is often caused by dirty relay contacts. Band switches with multi-part wafers can also absorb insulating grime. It probably pays to spray clean all mechanical switches at the first sign of trouble. If the unit works on one band but not another, you can reasonably expect to find a




Photo F. SBE 34.

defective converter crystal for that band, or a dirty band switch.

Most of the time these steps will get an old unit back on the air. If the unit

still does not operate, check the voltage and resistance readings provided in any good manual. Do not rush to align the unit if it is dead or nearly so. Alignment should be the final step. If it is done on a defective unit you may significantly detune the entire transceiver, making final repairs much harder in the long run. Table 2 describes 10 common problems, gives possible causes, and suggests solutions.

By now you are probably on the air with your bargain rig. You may want to add a whisper fan to cool your unit and protect your investment, since these old tube jobs run quite hot, and few were equipped with fans. If you add a fan, try not to make any new holes in the cabinet, as they would detract from the original condition of the unit. Finish the job with cabinet paint for a couple of bucks, and your transceiver will look as good as new.

Table 2. Ten Common Problems and Solutions.

Problem	Possible Cause	Solution
1. No function, no filament voltage.	Power supply	Check fuses, switches, cables, power cord.
2. No function, filaments light.	Power supply	Power supply rectifier diodes.
3. Receives but does not transmit.	No high voltage or bad driver, final tubes	Check high voltage output and driver and final tubes.
4. Receiver is distorted.	Power supply or audio circuit	Bad filters in power supply or bad audio tube. Check bias setting.
5. Receiver OK, transmitter distorted.	Driver or final tubes	Replace bad tubes.
6. Receiver OK, no or low transmitter output.	No converter signal	Check converter crystal, and clean band switches.
7. Does not work on one band.	Bad electrical contact	Clean relays and switches, resolder joints.
8. Intermittent transmitter or receiver		
9. Transmitter power output but no modulation.	Microphone	Check microphone and mike wiring.
10. Receives all bands but power output low on high frequency.	Driver or final tubes	Replace tubes.

The Unthinkable

I have two reassuring thoughts for those of you who fear that you may ultimately fail in your efforts to repair your flea market bargain. First, if you follow the steps I have outlined here, and use a little electronic detective work, you most likely will get the rig back on the air. Second, if you finally give up, nothing is lost, because you just take it back to the flea market next year, get a tail-gating space, and post a big sign that reads: AS-IS: SSB RIG, PRICE NEGOTIABLE. **RF**

Contact Joel J. Levine WB2BMH at 38 Bamboo Lane, Hicksville NY 11801.




Photo G. SWAN 350.

NEW

from

Spangler X-PRESS

500 Cards

\$62.50

Actual Size: 5 1/2" x 3 1/2"

Custom Reverses and Overprints at No Extra Charge

QUANTITY DISCOUNTS AVAILABLE

Info Kit and Full Price List: P.O. Box 6262, Kansas City, KS 66106

Or Call Toll Free 1-800-466-1616

FULL COLOR CUSTOM QSL CARDS

CIRCLE 103 ON READER SERVICE CARD

Insulators!

If you build your own antennas, you'll love these new, high-tech designs!

TRY OUR INTRODUCTORY OFFER!

You Get:

- 15 assorted insulators
- 5 assorted standoffs
- And as a "Radio Fun" extra, we'll send you a **FREE** copy of our new guide "Easy Wire Antenna Projects for the New Ham" (a \$5.00 value!)

\$7.95

SEND CHECK OR MONEY ORDER FOR \$7.95 (plus \$1.00 shipping and handling) to: Skyhook Supply, P.O. Box 495, Battle Creek, MI 49017 - Michigan residents add 4% sales tax.

CIRCLE 294 ON READER SERVICE CARD

Why buy a TNC?

PC HF FAX + PC SWL \$119

SPECIAL COMBINATION OFFER

For a limited time, if you order PC HF FAX \$99 (see our other ad in this issue), you can add PC SWL for only \$20 instead of our regular low price of \$99.00.

PC SWL contains the hardware, software, instructions and frequency lists needed to allow you to receive a vast variety of digital broadcasts transmitted over shortwave radio. All you need is any IBM PC or compatible computer and an SSB shortwave receiver. The product consists of:

- Demodulator
- Digital Signal Processing Software
- 80 Page Tutorial Reference Manual
- World Press Frequency List
- Tutorial Audio Cassette with Samples

PC SWL automatically decodes Morse code, Radio Teletype, FEC (forward error correcting code), SELCAL (selective calling transmissions), and NAVTEX. PC SWL lets you tune in on world press services with up to the minute news, meteorological broadcasts, ham radio operators, coastal shore stations, aviation telex and much more digital action on the shortwave bands. Find all the utility station action you have been missing. PC SWL software uses the processor in your PC to do the work, why pay for another expensive box when a simple interface and your PC and do the job?

ADVANCED FEATURES:

- Tuning Oscilloscope
- Digital Waveform Presentations
- Auto Calibration and Code Recognition
- Continuously Tunable Filter Frequencies
- Variable Shift
- Adjustable CW Filter Sensitivity
- Unattended Capture and Printing

Software Systems Consulting
615 S. El Camino Real, San Clemente, CA 92672
Tel: (714) 498-5784 Fax: (714) 498-0568

CIRCLE 244 ON READER SERVICE CARD

SUBSCRIBE TO

Radio Fun

800-722-7790

ICOM BATTERY INSERTS

BP-2	7.2v	500mah	\$14.00
BP-3	8.4v	270mah	\$15.00
BP-5	10.8v	500mah	\$21.00
BP-7	13.2v	500mah	\$23.00
BP-8	8.4v	800mah	\$21.00
BP-22	8.4v	270mah	\$22.00

KENWOOD BATTERY INSERTS

PB-21	7.2v	200mah	\$12.00
PB-21H	7.2v	600mah	\$15.00
PB24 Tabs	9.6v	600mah	\$15.00
PB-25/26	8.4v	500mah	\$18.00

YAESU BATTERY INSERTS

FNB-3/3A	10.8v	500mah	\$28.00
FNB-4/4A	12v	500mah	\$27.50
FNB-10	7.2v	600mah	\$15.00
FNB-11	12v	600mah	\$30.00
FNB-12	12v	500mah	\$30.00
FNB-17	7.2v	600mah	\$18.00

MORE BATTERY INSERTS

Tempo S1 Early	270 mah	\$19.95
Tempo S2/4/5 Late	500mah	\$21.00
Standard BP-1	270 mah	\$19.95
Ten-Tec BP1	500mah	\$19.95
San-Tec #142#144 Tabs	600mah	\$22.00
Azden 300 Tabs	600mah	\$15.00
Bearcat	600mah	\$20.00
Regency MT1000 Tabs	600mah	\$15.00

ICOM PACKS 2/4SAT & 24AT

BP-83S	7.2v	750mah	\$38.00
BP-84	7.2v	1000mah	\$50.00
BP-85s	12v	800mah	\$60.00

* Add \$3.00 Shipping FREE Catalogue

THE BATTERY STORE
279 Douglas Ave., Suite 1112
Altamonte Springs, FL 32714
1-800-346-0601

CIRCLE 62 ON READER SERVICE CARD

upgrade... don't stop now!

by Gordon West WB6NOA

Morse Code Made Fun

If you joined the amateur radio hobby with your new no-code license, you will want to start learning the code to pass the 5 wpm code test. Passing the code test at 5 wpm in front of three ARRL accredited volunteer examiners will open up the following additional bands for Technician-Plus privileges:

10 meters voice:	28,300 kHz-28,500 kHz
10 meters data:	28,100 kHz-28,300 kHz
10 meters CW:	28,100 kHz-28,500 kHz
15 meters CW:	21,100 kHz-21,200 kHz
40 meters CW:	7,100 kHz-7,150 kHz
75/80 meters CW:	3,675 kHz-3,725 kHz

The 40 and 80 meter Novice CW bands are excellent for practicing your code to distant stations at night. Typical range is anywhere between 500 and 3,000 miles.

The 15 meter CW Novice subband allows you to communicate code to stations all over the world during daylight and evening hours. Ionospheric skip conditions may go until midnight for 15 meter, long-range contacts. Ten meters offers the most excitement for

Technician-Plus operators who pass the 5 wpm code test. Ten meter single sideband voice privileges give you 200 kHz of elbow room between 28,300 kHz to 28,500 kHz, where long-range daytime and early evening communications occur regularly for world-wide contacts.

That's right, you can go on the air with worldwide HF equipment on 10 meter voice from 28,300 to 28,500 kHz, and run up to 200 watts of power output. You can communicate all over the world regularly. You can also run RTTY and digital packet transmissions for worldwide contacts between 28,100 to 28,300 kHz. And you can make use of the propagation beacons between 28,200 to 28,300 kHz.

Upgrading to 5 wpm—or, for you Novice and Tech-Plus operators, to 13 wpm—is best done by listening to CW practice and communications at least three times a day. If you can't squeeze in some radio CW during lunchtime, arm yourself with a handful of code tapes. [You can order tapes from Uncle Wayne's Bookshelf or the Gordon West Radio School. Eds.]

Code tapes and live radio reception is a great way to learn the code and increase your speed for the next upgrade level.

If you don't know the code, use code tapes to assist you in learning the letters of the alphabet, the numbers, and the punctuation marks for period, comma, slant bar, and the break sign "BT." Listening to the instructions on the code cassettes will teach you to recognize the sound of the dits and dahs, and how these short and long sounds form letters and words.

But it's important to write it down, too, as opposed to simply saying the code out loud. Train your ear to tune into the code, and your hand to instinctively write down what each sound is.

If you forget a letter while copying code or taking a code test, don't stop to scribble down the dots and dashes. Just put a small tic mark on your paper for a missed letter. After you have completed

your copy session, go back and try to figure out what the missing letter might be. Chances are, you'll be able to figure it out by looking at the letters around it. What is the most likely word the letters would form? Putting down the dits and dahs would just slow you down, and might make you miss the following letter as well.

The Farnsworth Method

For the 5 wpm and 13 wpm examinations, the code characters are normally sent at a character rate of 15–18 words per minute. However, the *spacing*

between words and letters is at the 5 and 13 wpm speeds, respectively. This is called learning the code by the "Farnsworth" method. The purpose is to learn the sound of the letter, number, or punctuation mark, at the higher speed. A character at 5 wpm sounds very different from the same character at 18 wpm. By learning the sound of the character at the higher speed to begin with, it's easier to upgrade later. The slower 5–13 wpm spacing rate *between* the characters gives the beginner time to write the character down.

On ARRL code examinations, CW

is sent at the 18 wpm Farnsworth character rate. This may seem a little bit fast for your Novice test. However, some hams like this extra fast type of snappy code sending, with big spaces in between each character. If you like it this way, go for an ARRL-type code test.

The traditional way of sending code for 5 and 13 wpm is at a character rate of 15–16 wpm. This is a nice, quick sound, and there is still enough space in between each character to give you time to write down what you have copied. And if you tune in the CW off



Photo A. It's easy for no-code Techs to learn 5 wpm.

TigerTail™

Range Extender for 2 meter Handheld Radios



- Boosts Signal from Flex & 1/4 wave Antennas
- Lowers Radiation Angle
- Improves both Receive and Transmit
- Raises Low Power Performance
- Saves your Battery Pack

Patent Pending

Infopak \$1

See and Hear the Difference

7⁹⁵
ppd

CIRCLE 138 ON READER SERVICE CARD

from **AntennasWest**
Box 50062F, Provo, UT 84605
1-801 373 8425

- Easy to Use
- Snaps on Handheld
- Unobtrusive
- Easily Concealed
- Adds No Bulk or Height
- Weighs only 1/3 oz.

1-800-926-7373
Order Hotline

Get The Best

PktGOLD multimode

Advanced Digital Modes -- Software Announcement -- for PK-88, PK-232 tnc - and - MS-DOS computers

Compare PktGOLD to any other tnc program. We're waiting...

We are counting on it, on your willingness to research the options. If you do, we think you will want the reliable, user-friendly and advanced features available in PktGOLD. We challenge you to compare it to ANY other program, including the one from the hardware manufacturer. Ask our users, or better, buy PktGOLD and find out for yourself.

Look for Host Mode

If you are shopping for a tnc, no doubt you'll be told about all the modes it supports, and an array of great features. What they don't have is powerful user software. Why? Because the tnc ROM code lacks a major and important ingredient: A complete Host Mode. This does not seem like a limitation until you begin talking to PktGOLD users and find out what they can do that you cannot. What tncs have? The PK-88 and PK-232.

PktGOLD is visibly better

With PktGOLD, you can SEE what is happening. You will KNOW who else is on the air, you will know WHY you are not getting through. Or why other stations are having trouble. You can see what the others cannot see. Have multiple sessions going. It's easy. Transfer a file, cut/paste text, print, execute a DOS command shell out for a while, edit a message. It's all there.

In AMTOR (a PK-232 mode) you have on the screen information about phasing, ciling, sending, receiving. You'll KNOW what is going on at all times. Switching modes on the PK-232 is easy. You can run BAUDOT, ASCII, MORSE, NAVTEX, TDM, SIAM, and the maildrops directly.

On-line HELP System

Getting started in any new technology involves lots of buzzwords and basic information. Push [F1] and get the information you need. You'll find help on setting up the line, writing and setting audio levels. You'll learn what parameters are used in each mode and what they do. If you need information on how to operate PktGOLD, just hit the [F1] key for help.

MultiSession Support

Packet Radio allows many simultaneous sessions on the same frequency. PktGOLD doesn't just allow 10 sessions. It supports them, without confusion. People say multiconnects is confusing. With PktGOLD it is simple. For emergency communications, or supporting public service, PktGOLD is the right choice.

Conference Mode

Not only can you have multiple sessions, you can have one or more conferences going with stations all discussing something of mutual interest. For nets, emergencies, traffic, conference mode is

Network View Screen

Here you are, connected to a Packet BBS asking yourself, "What's going on?" or "Is the channel busy?" Now you can be capturing network activity continuously and display it whenever you wish or on a split screen. Monitoring while connected is helpful, and automatic.

File Transfers: Binary/Text

Do you have a database, the local club members, or a com or ops program you want to send (or retrieve)? It's easy with PktGOLD. And you can keep QSOing on the SAME connect while you are transferring a file. It even tells you the effective baud rate and time left.

Name and Callsign

How often have you said to yourself, "Gee I remember this call, but forgot the name and QTH?" or worse, you don't even remember the callsign? PktGOLD has a QSL file that allows you to save names and other information. It's there on the screen while you are in QSO. A great help.

Maildrop Support

Access to the maildrop is easy. It's just a printer or to disk for later printing. Great for emergency work, or any other event when hard copy is needed.

Brag Files

Create descriptive files about your station or anything of interest. You are not limited to just 10 files. With PktGOLD you ask for a list of BRG files, and they come up, sorted for you, and all you do is move the cursor to the one you want to send, and voila, you send it.

Cut/Paste

You can retrieve an ARRL bulletin on RTTY (if you have the PK-232), then switch to VHF packet, CUT the text to your clipboard, edit it (if you wish), then paste it into a message on your maildrop, or into a local BBS. Cut/Paste can be used to send text to other Packet sessions, or to handle text, or between modes, or to and from disk or to the printer. A very powerful feature and easy to use.

Printer Support

Print from any screen. New text, all text, to a printer or to disk for later printing. Great for emergency work, or any other event when hard copy is needed.

Saves QSO text

You can save session text automatically by callsign, and for only certain callsigns, all stations, or none. Your choice. When saved by callsign, it is easy to review ongoing QSOs, just bring up the callsign list for the station, and see each QSO, the date and time when it started, and ended, and the text.

NET/ROM Intelligence

On Packet, give PktGOLD a set of net nodes separated by the "or bar" (!) and it will do all the sequential connects automatically.

Quick Connects

Add stations to a list, and you can start packet or AMTOR connects easily.

More Features

Use only those features you need. The rest are there when you are ready. Like setting monitor modes (43/50) or colors, changing startup options, and more. It's all there.

Who uses PktGOLD?

Operators worldwide are using PktGOLD. LA County Public Works has adopted it for an emergency network. Scripps Institute (San Diego) is using it to communicate to research vessels. Emergency and public service groups use it. Many headline BBS systems carry reviews praising PktGOLD.

What should you do?

If you own an AEA tnc you need PktGOLD. Thinking about buying a tnc? Ask one of our users what they think is the best. Or better, call, fax, or write today to order your copy of PktGOLD with 75-page manual, online help, quick start & more.

To Order PktGOLD

Program & Docs 59.95
Shipping/Handling 5.00
Sales Tax ...

Total

___ VISA ___ MC ___ Check

Card

Expiration Date

Phone

Callsign:

Ship to:

Sample Exam Message

The test is preceded by a warm-up practice session which also allows for the adjustment of the tape player equipment. After the warm-up session, one of the examiners will announce that the test is about ready to begin.

VVVVVV N7TVK DE KAØDHO. BT

Tnx James. UR RST 489 489.

I am mobile in Colorado on my way to vacation at Disneyland in California. Name is Brian. Rig is a 200 watt ICOM and antenna is a 10 meter whip. I am 36 years old and my wife and kids are all General class hams. Occupation is a lawyer. The WX is freezing/cold and the temperature is 25 degrees. Must QRT to stop for some lunch. How copy? N7TVK DE KAØDHO AR SK

Code tests usually begin with a series of six V's, then the callsigns. Callsigns are sometimes hard to copy, but since they are repeated at the end, you have two chances to copy them. Try hard to get them; unlike a word, you can't guess at the missing letter in a callsign.

If you look carefully at this message, you will find that it contains all letters of the alphabet, numerals 0–9, and punctuation marks: the period, comma, question mark, sign-off signals AR and SK, the break or pause BT, and the slant bar DN. This complies with the FCC's requirements in Section 97.21(3)(b).

Typical Questions

1. What was the callsign of the sending operator? (KAØDHO)
2. What was the name of the receiving operator? (James)
3. What was the RST report given? (489)
4. What was the QTH of the sending operator? (Colorado)
5. What type of transceiver was the sending operator using? (ICOM)
6. What type of antenna was the sending operator using? (whip)
7. What was the power output in watts of the sending operator's rig? (200)
8. What were the weather conditions at the sending operator's location? (freezing/cold)
9. What was the occupation of the sending operator? (lawyer)
10. Why did the sending operator go QRT? (to stop for lunch)

the airwaves, chances are you'll hear both types of CW being sent—Farnsworth and fast Farnsworth. You choose whichever one you like the sound of best, and make sure that your test will use the same code rate for the characters.

Taking the Test

Since you are already a Technician Class operator, you must take the code test in front of three ARRL accredited volunteer examiners, or VEs. Some accredited VE teams will make up their own code tests on cassette, or they may elect to get their code test materials directly from W5YI or the ARRL. The W5YI is the National Volunteer Examiner Coordinator, or VEC.

The W5YI VEC code tests are at the 15 wpm rate, slower than the ARRL's 18 wpm rate. However, both use the Farnsworth method, with spacing down to the 13 wpm rate for General and 5 wpm rate for Novice.

The code test lasts approximately seven minutes. The volunteer examiners may be testing for all classes of amateur radio licensing. A Novice applicant who has no ham license can be tested for the 5 wpm rate by two General Class licensees. If you have elected to enter the hobby via the no-code route, you must be tested by three VEs.

The code test for both Novice and General will be a typical QSO from one station to another. See the sidebar for an example. If you look at this QSO carefully, you will see it contains every letter, every number, and the punctuation marks required by the FCC for a legal code test.

You don't have to necessarily copy




Photo B. Learning the code together in a classroom setting can be FUN!

the message 100 percent perfectly to pass. If you can get enough bits and pieces of the message, chances are that you can piece most of it together. As noted above, you can guess many words from the letters you *did* get. For example, can you fill in the missing letters in these words: _NTENN_, G_NE_AL, _ATTs?

The exam will usually consist of 10 questions based on the material you

have copied. Generally, you pass if you get at least seven of the answers correct. You may also pass the test if the examiners can find a solid line of perfect copy one minute long. That's about 26 letters for Novice, or 65 letters for General.

The code test won't be a trick message. You won't find a QSO that reads, "Temperature is 98 degrees, and it's ready to snow." Just won't happen.

Nor will there be any deliberate misspellings, either.

Some volunteer examiners will also make the code test easier by offering multiple-choice answers to their 10 questions. Just recently, the ARRL relaxed their code test requirements, and now allow ARRL VEs to make their own tests, including multiple-choice code tests.

Find out ahead of time from your

VE team leader what the code test will be like—18 wpm or 15 wpm character speed? Multiple-choice or fill-in-the-blank? Are you permitted a couple of minutes after the test to look over your answers and fill in a missed letter or two? It's important to know the rules before you actually take your upgrade code test, because each team has its own way of giving the examination.

If you are new to the Amateur Radio Service as a Technician no-code licensee, begin learning the code characters with CW code learning cassettes. Supplement the cassettes with live CW reception from a high frequency receiver. Unfortunately, there is almost no code practice on the VHF or UHF bands except here in Southern California (Monday nights, 6:30 p.m., 144.330 MHz simplex).

Live and breathe live code practice over the air before you plan to sit for your actual upgrade code test. Try to copy code sent faster than what you can write down accurately. Push yourself to get a letter here and there at speeds 6 or 7 wpm faster than what might be on the test. This way, when you sit for the actual code receiving test, it will almost sound slow!

But do learn the code as your next step in upgrading—it's the amateur's international "secret language" and a kick to know when all those little dits and dahs finally begin to form a real message coming out of your pen or pencil. If you practice 20 minutes in the morning, 20 minutes at noon, and 20 minutes in the afternoon, your coming upgrade will be an easy pass. Good luck!

RF

BATTERIES

REPLACEMENT BATTERIES (ALL NEW—MADE IN USA)

ICOM

7S 13.2v 1200 mah \$59.00
8S 9.6v 1200 mah \$59.00
BP7 13.2v 600 mah \$59.00
BP8 8.4v 1000 mah \$59.00
SA/SAT
BP82, BP83
BP83A 7.2v 750 mah
BP84 7.2v 1000 mah
BP85A 9.6v 600 mah
BP85B 12v 600 mah



KENWOOD



PB1 12v 1000 mah \$59.00
KNB4 7.2v 2200 mah \$59.00
PB6 7.2v 750 mah \$46.00
PB7 7.2v 1500 mah \$55.00
PB8 12v 750 mah \$55.00

MOTOROLA

HT300 7.2v 1600 mah \$45.00
HT90 12v 600 mah \$34.00
HT440 12v 600 mah \$39.00
MT500 15v 500 mah \$39.00

RADIUS
P-10 500 mah \$28.00

SABER
7.2v 1100 mah \$59.00

CAMCORDER

JVC
PANASONIC
PVB8088 12v 2.3 amps

RCA/HITACHI
Full size
VHS-C

SONY
NP22
NP55/77
ALL BRANDS AVAILABLE

NEW

ALINCO
10N 7.2v 700 mah \$32.00
12N 12v 700 mah \$47.00

YAESU
FNB4 12v 750 mah 4" \$41.00
FNB4A 12v 1000 mah 4" \$55.00*
FNB3A 9.6v 1200 mah 4" \$45.00
BASE CHARGE ONLY

YAESU

FNB-2 v 500 mah \$21.00
FNB-2 v 600 mah \$23.00
FNB-4A
FNB-10
FNB-10S 7.2v 1000 mah \$43.00
FNB-12
FNB-12S 12v 600 mah \$45.00



SPECIALS

ICOM
2SAT, 4SAT, 24AT
720 Charger \$75.00
with
BP-84 (EQUIV) 3" high
7.2v 1000 mah \$110.00
or
BP-85B (EQUIV) 3" high
12v 600 mah \$140.00

INSERTS

ALINCO 10N, 12N
AZDEN 3000, 4000
ICOM BP-2, 3, 5, 7, 8, 7S, 8S
KENWOOD PB-21, 21H, 26, 26
REGENCY MT1000, HX1200
SANTEC 142, 144
STANDARD BP-1
TEMPO S-1, 2, 4, 5, BP-15, S-15
TENTEC 2991, 2591
UNIDEN (BEARCAT)
CALL FOR LOWEST PRICES

CELLULAR

MITSUBISHI \$50.00
NEC \$45.00
NOVATEL \$45.00
PANASONIC \$45.00
Bag Phone Kits
MOTOROLA
"FLIP" \$60.00



BATTERIES FOR:

WATCHES
CALCULATORS
LAPTOP COMPUTERS
CORDLESS PHONES

SEND FOR
FREE CATALOG

DEALER INQUIRIES
WELCOME

*ALL BATTERY PACKS—GUARANTEED TO HAVE THE ADVERTISED CAPACITY

BATTERY-TECH, INC.

28-25 215 PLACE, BAYSIDE, N.Y. 11360 FAX 718-461-1978
800-442-4275 — N.Y.S. 718-631-4275



VISA



MASTER CARD



try something new

by Bill Brown WB8ELK

Amateur Satellites

Orbiting the earth are over a dozen satellites that are very unique (currently 14 in operation if you count the *Mir* space station). These are amateur radio satellites put up as piggyback payloads during commercial launches. They are called OSCAR (Orbiting Satellite Carrying Amateur Radio). Some allow two-way communications using the satellite in much the same way as a repeater. Others send back telemetry, voice messages, or pictures. There are even a few that operate as an orbiting packet BBS (bulletin board system). You can leave a message on one of these satellite BBSs and someone on the other side of the world can read the message at a later time.

What Equipment is Needed?

Some of these satellites require you to have a fairly extensive array of equipment to get the most out of them. For example, to use the highest satellites (OSCARs 10 and 13), you would need an all-mode (SSB, CW and FM) transceiver or transverter (which converts an HF radio to VHF and UHF) capable of operation on 2 meters and the 70 cm band (435-438 MHz). A good antenna system (with preamp) which you can steer in elevation as well as azimuth (Az-El mount) will make it possible to track these satellites. Some of the new Microsats also require you to add a PSK modem and a packet TNC to your station. That way you can receive the telemetry in-

formation and picture transmissions (in the case of WEBERSAT), and also use the orbiting packet BBS systems.

The thrill of being able to talk to anyone over a large portion of the world, with the knowledge that you can reliably communicate at precise times, makes this well worth the effort. You no longer have to depend on a chancy ionosphere to talk around the world. Contacts are possible that would rarely occur on the HF bands. For example, let's say you're located in New York. You could talk to Japan, Europe, California, Vermont and Pennsylvania all at the same time. Not only that, all stations would be pretty much the same signal quality and everyone would hear all sides of the conversation. Just try to do that on 10 meters!

Easy-to-Receive Satellites!

OK, it takes some effort to put together a fully capable OSCAR ground station. Don't let this discourage you. Some satellites are ridiculously EASY to hear and track. Using nothing more than a 2 meter HT (handie-talkie), a 2 meter FM home station, or a 10 meter HF rig, you can impress your friends by receiving signals directly from space!

UOSAT

The University of Surrey in England has quite an impressive curriculum which allows their students to design and build their own satellites. They now have three of their satellites cur-

rently orbiting the Earth (UO-22 was launched just this past July). Their UOSAT-11 has an output on 145.825 MHz FM. It is in a low polar orbit and comes over several times a day. You can receive its signals for as long as 20 minutes during each pass. Although it usually outputs 1200 baud ASCII telemetry signals, they sometimes have it talk using an onboard voice talker module. Nothing like a talking computer from space to thrill visitors to your shack!

DOVE

As part of the Microsat program, Junior Torres de Castro PY2BJO of BRAMSAT (the Brazilian AMSAT group) proposed a very unique satellite to help stir the imagination of students all over the world. The DOVE (Digital Orbiting Voice Encoder) satellite was designed to transmit down on the same frequency as the UOSAT bird. It currently sends down packet telemetry on 145.825 MHz FM and can be received on just about any 2 meter FM station (or scanner for that manner). The only interface needed to receive the telemetry is a standard packet TNC and a computer to display the information.

You can watch the voltage on the solar panels change with varying sun angles during its orbit, look at temperature readings in several locations inside the satellite, and look at the output of dozens of sensors. It is really quite fun to watch the solar panel voltage change when the satellite crosses over into night. One nice display program for the IBM PC that allows you to show all of the telemetry in an informative real-time display is called WHATS-UP (see the table).

One other feature that is sure to be popular when it comes on-line is the onboard voice talker. Voice messages from students all over the world will be selected periodically and uplinked via packet to the satellite by the DOVE control station. In addition, voice bulletins will be issued. These high quality voice messages will play back during each orbit, and can be easily received worldwide.

Easy Soviet Satellites

The Soviets have put up a number of easy-to-use amateur radio satellites (the RS series). Three of these are particularly suited to the satellite beginner: RS-10/11, RS-12/13, and RS-14. Usually requiring only a 10 meter HF receiver and a 2 meter all-mode transceiver (you might be able to use your FM transmitter as a CW signal), they are a great way to start getting your feet wet in the world of two-way satellite communications. There is also a fourth satellite—the *Mir* space station (more on that later).

RS-10/11

To receive the downlink signals from the RS-10/11 satellite, listen be-

tween 29.360-29.400 MHz (SSB or CW). You can hear the CW telemetry downlink on 29.357 MHz. You transmit up to RS-10 (uplink) between 145.860 and 145.900 MHz (SSB or CW). You can use your 2m FM transmitter as a CW transmitter if you disconnect your microphone and key the PTT (Push-to-Talk) line. Be warned that some rigs will sound chirpy when keyed this way. Since these are low-orbiting satellites, you don't need a lot of signal to transmit through them. It only takes about 10 to 25 watts of power to a simple antenna to work through one of the RS satellites. Good results can be obtained with an omnidirectional antenna, a turnstile antenna, or a small beam. A dipole or turnstile will work well for your 10 meter receive station (a preamp will help in some situations).

RS-12/13

This Soviet satellite usually is set up in what is known as mode K or KT. RS-12/13 can be heard between 29.410-29.450 MHz. The CW beacon is on

29.408 MHz. To help out those satellite enthusiasts with no VHF equipment, the RS-12/13 uplink is on 15 meters between 21.210-21.250 MHz! Occasionally RS-12/13 will be on mode KT, which provides an additional downlink between 145.91-145.95 MHz.

Talk to an Orbiting Robot

One neat feature of the RS satellites is the robot operator. You can hear the RS-10/11 "robot" on 29.403 MHz. Just transmit CW up to the robot on 145.820 MHz at about 17 wpm. For example, if you were WA5ZIB, you would send the following as perfectly as you can: RS10 de WA5ZIB AR. If the robot hears you, it will call you and give out a serial number! The RS-12/13 satellite also has a robot with an uplink on 21.129 MHz (the Novice band). The robot transmits down on 29.454 MHz.

Mir

Here's your chance to link up to a live cosmonaut in the orbiting *Mir*
Continued on page 30

information sources

The following is a list of satellite groups, publications, and equipment manufacturers that will help you get into the world of satellites:

AMSAT-NA

850 Sligo Ave., #600
Silver Spring MD 20910-4703
Tel. (301) 589-6062
FAX: (301) 608-3410
Dues \$30/yr.

Membership entitles you to the *AMSAT Journal* (bi-monthly) as well as discounts to a wide array of software and books.

Satellite Operator

R. Myers Communications
P.O. Box 17108
Fountain Hills AZ 85269-7108
\$33/yr. monthly publication

Oscar Satellite Report

R. Myers Communications
P.O. Box 17108
Fountain Hills AZ 85269-7108
\$29/yr. bi-weekly

\$56 for both Satellite Operator and OSR

Satellite related software:

InstantTrak 1.0—tracking software for IBM PC (EGA or better); available from AMSAT-NA.

Quiktrak 4.0—tracking software for the IBM PC (monochrome or higher); available from AMSAT-NA.

Whats-Up—Real-time display of DOVE telemetry (and other Microsats). Available for \$35 from Joe Kasser G3ZCZ, P.O.Box 3419, Silver Spring MD 20918.

Books:

Satellite Experimenter's Handbook; available from AMSAT-NA, Uncle Wayne's Bookstore, and the ARRL.

A Beginner's Guide to Oscar 13; available from AMSAT-NA.

PACSAT Beginner's Guide; available from AMSAT-NA.

Decoding Telemetry from the Amateur Satellites; available from AMSAT-NA.

Weather Satellite Handbook; available from AMSAT-NA, Uncle Wayne's Bookstore, and the ARRL.

HF Information nets:

East Coast AMSAT net—Every Tuesday evening at 9 p.m. Eastern on 3.840 MHz.

Central States AMSAT net—Tuesday evening at 9 p.m. Central on 3.840 MHz.

West Coast AMSAT net—Tuesday evening at 9 p.m. Pacific on 3.840 MHz.

International AMSAT net—Sundays at 1900 UTC on 14.282 MHz.


AMSAT net—18.155 MHz at 2300 UTC on Sundays.

Phone line BBSs with satellite info:

DRIG (Dallas Remote Imaging Group)—(214) 394-7438.

Celestial BBS—(513) 427-0674.

AMATEUR TELEVISION



**TVC-4G
only \$89**

SEE THE SPACE SHUTTLE VIDEO


Many ATV repeaters and individuals are retransmitting Space Shuttle Video & Audio from their TVRO's tuned to Satcom F2-R transponder 13. If it is being done in your area on 70 CM, all you need is one of our TVC-4G ATV 420-450 MHz downconverters, add any TV set to ch 3 and 70 CM antenna. Others may be retransmitting weather radar during significant storms. Once you get bitten by the ATV bug - and you will after seeing your first picture - show your shack with the TX70-1A companion ATV transmitter for only \$279. It enables you to send back video from your camcorder, VCR or TV camera. ATV repeaters are springing up all over - check page 411 in the 90-91 ARRL Repeater Directory. Call for a copy of our complete 70, 33 & 23 CM ATV catalog.

(818) 447-4565 m-f 8am-5:30pm pst.
P.C. ELECTRONICS
2522 S. Paxson Ln Arcadia CA 91007

Visa, MC, COD
Tom (W6ORG)
Maryann (WB6YSS)

AMATEUR TELEVISION

SMILE! YOU'RE ON TV



Only
\$329

Designed and
built in the USA
Value + Quality
from over 25 years
in ATV...W6ORG

With our all in one box TC70-1 70cm ATV Transceiver you can easily transmit and receive live action color and sound video just like broadcast TV. Use any home TV camera or VCR by plugging the composite video and audio into the front VHS 10 pin or rear phono jacks. Add 70cm antenna, coax, 13.8 Vdc and TV set and you are on the air...it's that easy!

TC70-1 has >1 watt p.e.p. with one xtal on 439.25, 434.0 or 426.25 MHz, runs on 12-14 Vdc @ .5A, and hot GaAsfet downconverter tunes whole 420-450 MHz band down to ch3. Shielded cabinet only 7x7x2.5". Transmitters sold only to licensed amateurs, for legal purposes, verified in the latest Callbook or with copy of license sent with order.

Call or write now for our complete ATV catalog including downconverters, transceivers, linear amps, and antennas for the 70, 33, & 23cm bands.

(818) 447-4565 m-f 8am-5:30pm pst.

Visa, MC, COD

P.C. ELECTRONICS


2522 Paxson Ln Arcadia CA 91006

Tom (W6ORG)

Maryann (WB6YSS)

MULTIPLE REPEATER - LINK - REMOTE BASE CONTROLLER

Finally a controller that has solved control and audio interconnect problems between multiple radios. Your radio system can grow to multiple sites and stretch for hundreds of miles - and yet any radio can be fully controlled from any designated input.



The RBC-700 Repeater Controller is designed to support Repeater systems that require multiple radios connected together at a site. The RBC-700 utilizes a true 7 x 7 audio matrix switch which allows several conversations between ports at the same time. In the illustration above the 733 model is supporting a Repeater, 3 Duplexed Links to different sites, and 3 Remote Bases. Using simple commands, a user could tie the Repeater and a Remote Base to one Link, while the other Links are communicating through your site, holding separate conversations. Or, connect all of the ports together - like a big party line !!

Several models are available and are software configurable to support up to 3 Repeaters, 5 Duplexed Links, and 4 Remote Bases. A group or club can start with the basics and expand their controller anytime by simply adding boards and software. Free software upgrades for one year after delivery. Finally, a real controller for the Linked system operator !

Multiple Independent Repeater control
Up to 5 Duplexed Links
Up to 4 different Remotes
Recorded Natural Speech Telemetry
Programmable Macros
Connect / Disconnect multiple Ports
Internal Receiver Squelch processing

Easy servicing
Integrated Autopatch
Expand at any time
Programmable Scheduler
+10v to +14v Supply
Standard 5.25" Rack Mount
Card-Cage design

Palomar Telecom, Inc.

300 Enterprise St. Suite E • Escondido, Ca. 92025 • (619) 746-7998 • Fax (619) 746-1610

CIRCLE 139 ON READER SERVICE CARD

JAN Crystals

your reliable source for a world
of crystal clear communication



- Commercial Two-Way
- MicroProcessors
- Amateur/Experimental
- Scanners/Monitors/Pagers
- Satellite-Telemetry
- Plus custom applications

EXPEDITED ORDER SERVICE!

FOR FREE CATALOG, CALL OR WRITE:



JAN CRYSTALS

P.O. Box 06017 Ft. Myers, FL 33906



TOLL FREE 1-800-526-9825

(813) 936-2397 FAX ORDERS: 1-813-936-3750

CIRCLE 240 ON READER SERVICE CARD

MORSE CODE MUSIC?

Finally, a code tape is available that makes the code enjoyable and fun. Play this tape on your stereo or at your ham party and dance to the beat of "the rhythm of the code"!

Order this cassette single hit today!

Send \$5.95 check or money order
(postage paid) to:



Kawa
P.O. Box 319

Weymouth, MA 02188

Mass Residents please add 5% sales tax.

CIRCLE 2 ON READER SERVICE CARD

G5RV All-Band QuickKits™

created by AntennasWest

Box 50062F, Provo, UT 84605

- Fast & Easy to Build
- Fail-Safe visual instructions
- No measuring or cutting
- Everything included
- Finish antenna in minutes

- Quality Components
- Presoldered Silver Fittings
- Kinkproof QuietFlex wire
- Fully insulated, wx sealed, no-corrode, low noise design

Tune All Bands incl WARC
Build your own from scratch. Order
TechNote #124-C \$5.95 ppd USA
Call 801-373-8425 for Tech advice.

- Double Size G5RV \$59.95
204 ft 160-10 Dipole
- Full Size G5RV \$35.95
102 ft 80-10 Dipole
- Half Size G5RV \$25.95
51 ft 40-10 Dipole
- Quarter Size G5RV \$21.95
26 ft 20-10 Dipole
- Marconi Adapter kit \$11.95
converts any dipole to Marconi
- 200' Dacron 250# line \$11.95

Order Hot-Line: Add \$5 P&H

1-800-926-7373

CIRCLE 107 ON READER SERVICE CARD



Watch 'QSO
Amateur Radio'
Monday nights
9 pm to 12 on
Spacenet-1,
Transponder-15

VHF COMMUNICATIONS

9:00 am - 5:30 pm
weekdays

Weekends and evenings
by appointment.

280 Tiffany Avenue
Jamestown, New York 14701

Western New York's finest amateur radio dealer.
PH. (716) 664-6345
(800) 752-8813 for orders only

CIRCLE 14 ON READER SERVICE CARD

World Ham Net Directory

Lists over 600 special interest ham nets. Tune in or work stamp collectors, airline people, missionaries, DXers, rag chewers, dozens more. Listed by interest, frequency, meeting time. \$9.95 + \$2 s/h (\$3 foreign)

The Basic Guide to VHF/UHF Ham Radio

Propagation, equipment, antennas, repeaters, contesting, awards & more. \$6.95 + \$2 s/h (\$3 foreign)

The Scanner Listener's Handbook How to Hear More on Your Scanner Radio

Explore 25-2000 MHz! Band allocations and users, scanners, antennas, accessories, listening laws, equipment, information sources, more. \$14.95 + \$2 s/h (\$3 foreign)

Order now from your radio book dealer or



Tiare Publications
PO Box 493W
Lake Geneva, WI 53147

Catalog \$1, free with order

Visa/MasterCard

CIRCLE 119 ON READER SERVICE CARD

BATTERIES

Nickel-Cadmium, Alkaline, Lithium, Sealed Lead Acid For Radios, Computers, Etc. And All Portable Equipment

YOU NEED BATTERIES?
WE'VE GOT BATTERIES!

CALL US FOR FREE CATALOG




E.H. YOST & CO.

7344 TETIVA RD.
SAUK CITY, WI 53583
(608) 643-3194
FAX 608-643-4439

CIRCLE 114 ON READER SERVICE CARD

WEFAX To The Max



PC GOES/WEFAX 3.0 \$250

PC GOES/WEFAX 3.0 is a professional fax reception system for the IBM PC. It includes an AM/FM demodulator, software, cassette tutorial and 325 page manual. Check this partial list of our advanced features:

- Res. up to 1280x800x256 APT Lat/Lon. Grids
- Unattended Operation
- Colorization
- Zoom, Pan, Rotation
- Contrast Control
- Tuning Oscilloscope
- Photometry/Histograms
- Orbital Prediction
- Frame Looping
- PCX & GIF Export
- Grayscale Printing
- Infrared Analysis
- Variable IOC & LPM

PC HF FACSIMILE 5.0 \$99

PC HF Facsimile 5.0 is a complete shortwave FSK fax system for the IBM PC. It includes an FSK Demodulator, software, 250 page manual and tutorial cassette. Call or write for a complete catalog of products.

Software Systems Consulting

615 S. El Camino Real, San Clemente, CA 92672
Tel: (714) 498-5784 Fax: (714) 498-0568

CIRCLE 250 ON READER SERVICE CARD

QUICK, EASY, & COMPACT

Flash cards * NOVICE thru EXTRA * theory Key words underlined. Over 1000 sets in use! For beginner, OMs, XYLs & kids.

NOVICE	\$11.95
TECHNICIAN	\$10.95
GENERAL	\$9.95
ADVANCED	\$15.95
EXTRA	\$14.45
Shipping 1 -	\$3.00
2 or more	\$4.00
CLUB DISCOUNTS	

Order Today!

from

VIS STUDY CARDS

P. O. BOX 16646

HATTIESBURG, MS 39402

HUGE NEW CATALOG

Call or write Universal today to receive your free 92 page catalog with prices!

- Communications Receivers
- Portable Receivers
- Amateur Transceivers
- Amateur & SWL Antennas
- Scanners
- RTTY and FAX Equipment
- Books and Manuals
- All major lines: Kenwood, Icom, Yaesu, Alinco, MFJ, Japan Radio, AEA, Sony and Sangean.

This catalog is available FREE by fourth class mail, or for \$1 by first class mail.



Universal Radio

1280 Aida Dr. DEPT. RFUN
Reynoldsburg, OH 43068

- ◆ Tel. 614 866-4267
- ◆ Tel. 800 431-3939
- ◆ FAX 614 866-2339

Universal-quality equipment since 1942!

Watts 'n' SWR

Stop guessing. Build this no-nonsense VHF/UHF wattmeter and save your hard-earned cash.

by Peter Putman KT2B

Here's a project everybody can use—a cheap, reliable wattmeter that can be used anywhere from 50 to 500 MHz. It uses an etched-line circuit for coupling and has two power ranges. Additionally, it can be calibrated to measure SWR!

The idea for this project grew out of discussions the Split Rock ARA had back in 1980 concerning a possible club project. Among the many ideas kicked around was one for such a wattmeter, although at the time an unrealistic figure of \$15.00 for the total cost was anticipated. The project never got off the ground.

I stuck with the concept, and over the years tinkered with various designs. Somewhere in the past I had stumbled upon a circuit that used an etched transmission line and coupler, so a trip to the technical archives in the attic revealed what I needed. The big problem was that the etched line was nowhere near 50 ohms! This wouldn't do at all. After all, what good is a 500 ohm wattmeter?

Additional research revealed that the dimensions of a 50 ohm stripline etched on G-10 epoxy board were close to 1/10 inch in width, with any length usable. After confirming this with Steve Katz WB2WIK, I began carefully etching test boards in the darkroom using precision rulers and masking material cut with an X-acto knife.

After about four prototypes, I had a board which, when connected between two BNC connectors (using the unetched side of the board as a ground plane), exhibited no reflected power on a Bird Model 43 wattmeter connected in series and terminated at 50 ohms. I had done it! Now to the nuts and bolts of the circuit!

I should clarify any additional comments by saying that this unit is really a bi-directional coupler. As such, it can be used to measure SWR or power—whichever you prefer. It samples a small amount of RF on the transmission line through a coupling line which is terminated in the middle. At either end, type 1N60 diodes are used to rectify this small sampled voltage. Add a few switches, pots, and a meter. And that's it!

As I just mentioned, RF energy traveling on the 50 ohm section from input to output is sampled by the -30 dB coupler—sort of like winding a link coupling at HF frequencies. D1 and D2 can be almost any kind of point-contact diode, but the best choice would be a 1N60, due to the bet-

ter performance characteristics at VHF/UHF.

The sampled, rectified DC voltage

ferent readings will be evident on different bands for the same power level measured.




Figure 1. PC board overlay for parts (except where indicated, all parts are soldered to the top side).




Figure 2. Master art for PC board (use a double-sided circuit board).

is then routed to R2 or R3 via SPDT switch S1. These two potentiometers set power ranges or can be used to set frequency ranges. Note that as with most wattmeters that use coupling lines, the degree of coupling rises with the frequency chosen and decreases with a lower frequency, so that dif-

Also note that while the actual power measurement and its relation to the meter scale is a function of a logarithm, the relation between decades of measurement is a linear function. This allows the use of one meter scale on any band. Power levels up to 500 watts can be measured accurately with this unit—typically within 10% of a Bird 43 wattmeter—but I haven't tried anything higher. Teflon board would be a better choice for higher power levels.

R1 on the sampling line functions as a termination, and you may have to tinker with it a bit to determine coupling characteristics. I found a value of 27–33 ohms to be fine. C1 and C2 function as RF bypass capacitors. The best way to mount the PC board is to suspend it between two connectors, either type SO-239 or a BNC female.

parts list

D1,D2	1N60-type diode or similar	Mouser # 333-1N60
R1	33-ohm, 1/4-watt resistor	Mouser #29SJ250-33 or Radio Shack
R2,R3	15-turn, 3/4-watt, 500k pot	Mouser # 594-43P503
S1,S2	SPDT Miniswitch	Mouser # 10TC510 or Radio Shack
C1,C2	2 disk capacitors, 0.001 50V	Mouser # 21RX510 or Radio Shack
J1,J2	SO-239 (or BNC) female chassis mount connectors	Mouser # 16SO239 (SO-239) or ME164-93094N (BNC), Radio Shack or Nema Electronics
M1	50 μ A movement	A.R.E. # 6500003
Case	LMB TF-780 case	Mouser # 537-TF-780 or Radio Shack equivalent
P.C. Board		See note below

Note: Mouser parts can be ordered from (800) 346-6873. The meter is available from A.R.E., 15272 S.R. 12E, Findlay, OH 45840. (419) 422-1558.

A blank PC board is available for \$4.50 + \$1.50 shipping from FAR Circuits, 18N640 Field Court, Dundee IL 60118.



Photo A. Front view of the wattmeter.

with all components as shown in Figure 1, along with appropriate lengths of wire to connect to each switch. Install the side connectors of your choice along with about 1" of braid or finger stock for the ground connection. Finally, install the completed PC board by suspending it between the center pins on the connectors, and then soldering the center pins to the 50 ohm etched line. Solder the braid to the back of the double-sided board.

Calibration can be achieved with use of a known, accurate bridge or wattmeter, such as a Bird 43. Set the unit up to the ranges you desire by adjusting the 10-turn pots, R2 and R3. For example, you may wish to measure the output of two mobile rigs; one with 25 watts at 146 MHz and one with 10 watts at 440 MHz. Or, if you wish, you can add additional trimpots for additional ranges.

I have included in Figure 3 a template for a wattmeter scale that can be used instead of the 50 μ A scale on the meter. Remove the meter face carefully, using a screwdriver to pry it off. Next, using extreme care not to bend the meter movement, work a small knife or screwdriver under the metal scale on the unit. Pry gently around the corners until it pops free, then slide it out. Use this metal scale as a template to cut the supplied scale to size. Use double-sided tape on the face to hold in your new scale. Snap the cover back on and you're in business.

As was stated before, accuracy has been measured to within 10% or better of a Bird 43 on the desired frequency. If you want, you can remove the meter and remote it, leaving the coupling unit in its own box. This could be handy for mobile installations! **RF**

You may reach Pete Putnam KT2B at 3353 Fieldstone Dr., Doylestown PA 18901.

This article originally appeared in the September 1984 issue of 73.



Figure 3. Meter scale for 50 μ A meter.





Figure 4. Schematic.



Call Sign Jewelry Shows Your Pride

14 Karat Gold jewelry and gifts with your Call Sign. Collar pins, necklaces, tie pins, lavalieres, charms, Operator Rings, Call Sign Watches. Look great! Quality craftsmanship. Send for free catalog:

KB2MB, HAM Jewelry, 26 Edgecomb Road, Binghamton, NY 13905-4017. 800-285-8587.

CIRCLE 64 ON READER SERVICE CARD

1-800-666-0908

YAESU ICOM ALINCO SR STANDARD

AEA, CUSHCRAFT, KANTRONICS, ASTRON, DIAMOND, Etc.
FACTORY AUTHORIZED DEALER—LOW DISCOUNT PRICES
FULL LINE OF ACCESSORIES—MONTHLY SPECIALS

LENTINI COMMUNICATIONS

21 Garfield St., Newington, CT 06111

New equipment pricing and orders 1-800-666-0908 Out of State.
Tech questions, used gear, info 203-666-6227.

Hours: Mon-Fri, 10-6. Sat, 10-4

WE SHIP UPS
C.O.D.s
WELCOME

MODIFICATION BIBLE

NEVER BEFORE IN IT'S TIME,
SO COMPLETE!

KDC SOUND
5 Pine
Meadow
Conroe,
TX 77363

DISCOUNT CATALOG

FROM PLL TO CRYSTALS;
Over 50 complete synthe-
sized crystal charts
Over 20 precalculated
modification charts
Over 60 PLL diagrams
Over 100 modifications
for PLL C.B.'s
Over 100 ham radio mod-
ifications
Scanner modification
Ten meter modification

CB to Ham/Phones
to Scanner/Ant.'s
to Radar Detectors
ELECTRONICS AT
DISCOUNT PRICES!!
CATALOG \$ 2.00
Deductible from
first purchase.
call: TOLL FREE
TX. 1-800-392-7020
OTHER 1-800-231-8829
PRICE: \$ 29.95 • AFTER YOUR DIAL 532


Courteous Service • Discount Prices • Fast Shipping

ALL ELECTRONICS

P.O. Box 567 • Van Nuys, CA 91408

HIGHEST QUALITY METAL CASSETTES (ERASED)

Premium quality metal tape in C-60 and C-90 cassettes (30 or 45 min. per side). One of the finest "brand-name" tapes on the market, in durable, clear plastic transport mechanisms. Recorded and bulk erased, the record-protect tabs have been removed and therefore, need to be taped over to re-record. Audiophiles will appreciate the wide dynamic range of this tape. If your cassette deck has a "metal" setting you will hear the difference. A real bargain! 60 min. tape - CAT# C-60M \$1.25 each • 10 for \$10.00 90 min. tape - CAT# C-90M \$1.65 each • 10 for \$15.00



CASSETTE STORAGE CASE

Black, unbreakable plastic audio cassette storage case. CAT# CBOX 5 for \$1.00 100 for \$15.00



HALL EFFECT SENSOR

Sprague # UGN3075LT
Operates on 4.5 - 24 Volts
Can sink 10 ma. With suitable output pull up, can be used directly with bipolar or CMOS logic circuits. Especially suited for electronic commutation in brushless D.C. motors using multiple ring magnets. Very tiny surface mount package 0.175" X 0.09" X 0.06" thick.
CAT# HESW-5 2 for \$1.00
100 for \$45.00 Large quantities available



SWITCHES

Pushbutton Switch

SMK Manufacturing
0.47" square black pushbutton.
SPST normally open. 4 p.c. pins
for mounting. Ideal for low current
switching applications. CAT# PB-29
5 for \$1.00 • 100 for \$15.00



Rotary BCD Switch

ECCO # 2310-02G - BCD 10 position
rotary switch. DIP configuration fits in
standard 8 pin I.C. socket. Right angle
style. Screwdriver actuation. 0.42" cube. CAT# RDIP-2
\$1.75 each • 10 for \$16.00 • 100 for \$145.00



FLASH ASSEMBLY

This NEW compact flash
assembly comes from a
U.S. manufacturer of cameras.
Unit operates on 3 Vdc
and measures 2 1/2" X 1 1/4".
Ideal for use as a strobe, warning light or attention get-
ter. Complete with instruction on how to wire.
CAT# FSH-1 \$3.75 each 10 for \$35.00



Special New Reduced Price PHOTOFLASH CAPACITOR

Rubicon CE photoflash capacitor.
0.79" dia. X 1.1" high. These are
new capacitors that have been
prepped with 1.4" black and
red wire leads soldered to the terminals.
210 Mfd 330 Volt CAT# PPC-210
\$1.25 each • 10 for \$11.00 • 100 for \$100.00



TOLL FREE ORDER LINES

1-800-826-5432

CHARGE ORDERS to Visa, MasterCard or Discover

TERMS: Minimum order \$10.00. Shipping and handling
for the 48 continental U.S.A. \$3.50 per order. All orders
including AK, HI, PR or Canada must pay full shipping.
All orders delivered in CALIFORNIA must include state
sales tax (6 % 6 1/2 % 7 %). Quantities Limited.
NO C.O.D. Prices subject to change without notice.

Call or Write For Our
FREE 64 Page Catalog
(Outside The U.S.A. Send \$2.00 Postage)
ALL ELECTRONICS CORP.
P.O. Box 567 • Van Nuys, CA • 91408

CIRCLE 194 ON READER SERVICE CARD

Ace Systems

OPTO Keyer

- Safe OPTO Isolated output • Built-in side tone
- 2 1/4" speaker • Battery or DC powered • Positive
- keying to 30 volts max. • Unique "POWER/LOGIC"
- LED • One Year Ace Systems Warranty

- See Your Ace Dealer -

- Amateur Electronics Supply
- Barry Electronics
- KJI Electronics
- Madison Electronics
- Oklahoma Comm. Center
- R. F. Enterprises
- R & L Electronics
- Rivendell Electronics

Ace Systems • RD 1 • Box 83 • Wilcox, PA 15870
(814) 965-5937

STILL ONLY 39.95!

The Best Value

PACKET RADIO • REPEATERS • PORTABLE

READY-TO-GO - Pre-assembled &
pre-tuned • RUGGED - Stainless steel
& lightwt. • DEPENDABLE - Water &
corrosion-proof • PROVEN DESIGN -
From ARRL Handbook, highest qly.
materials and workmanship.

Only \$29.95 Free shipping (cont. USA)
Money back guarantee.
Specify MAX146,
MAX220, or MAX440

MAX System™

GROUND PLANE ANTENNAS

CK-MO-MC-VISA Accepted (MA add 5% sales tax)

Send payment to: Cellular Security Group,
4 Gerring Rd., Gloucester, MA 01930
Or charge by phone. (508) 281-8892

CIRCLE 234 ON READER SERVICE CARD

NextDay™ QSLs

Two-Color Rainbow Assortment

Call Today & We Ship NextDay 2nd Day ASAP

Quantity	100	200	400	500	1000
Baraboo, Wisconsin	\$29.95	\$39.95	\$49.95	\$54.95	\$99.95
Sauk County	\$24.95	\$34.95	\$44.95	\$49.95	\$89.95
K9ZZ	\$19.95	\$29.95	\$39.95	\$44.95	\$79.95

Info \$1

Antennas West

1-800-926-7373

All orders ppd air mail USA. Canada add \$2
For overnight air delivery USA add \$10.
Box 50062-F, Provo UT 84605

CIRCLE 135 ON READER SERVICE CARD

Subscribe to Radio Fun

call 1-800-722-7790

in New Hampshire call (603) 525-4201

D & L FABRICATION

Antennas by: MAXRAD INC. and AUSTIN ANTENNA LTD.

MAXRAD CHROME COIL SERIES		
MHB-5800	5/8 wave 3dB 144-174 MHz	24.64
MUF-4305	5/8 over 1/2 wave 430-450 MHz 5dB	26.08
MD1444	146/446 Dual Band unity 5dB	31.95
MAXRAD MOLDED COIL SERIES		
MHB-150	5/8 wave 144-174 MHz 3dB Economy model	22.96
BMHB-150	5/8 wave 3dB 144-174 MHz all black	28.24
MUF-430	5/8 over 5/8 wave 430-450 MHz 5dB	24.40
BMUF-430	5/8 over 5/8 wave 430-450 MHz 5dB black	29.78
MOUNTS		
M	3/4" body mount with coax and PL259	10.95
T	Trunk lip mount with coax and PL259	15.08
G	Chrome magnet mount	19.11
RG	Chrome magnet mount with rubber boot	20.50
BG	Black magnet mount	20.98
RBG	Black magnet mount with rubber boot	22.38
AUSTIN ANTENNA LTD.		
500C	144/446 Dual band	29.95
Suburban	144/223/446 tri-band base station	69.95
Triplexer	144/223/446 MHz	130.00
DF Q'er	144 MHz Fiberglass base station	64.95
	440 MHz Fiberglass base station	59.95

Antennas From 50MHz through 1.3GHz. We support 220 MHz
Phone Hours: Monday through Thursday 06:00 to 08:00 PM CST
Order Line: 1-800-533-5160 Information: 1-913-677-4766
D & L FABRICATION, P.O. BOX 6784, LEAWOOD, KS 66206
Shipping extra

Natural Voice Playback Board

DataVoice - DV-64

Add a Recorded Natural Voice to your system or equipment.
Voice vocabularies or multiple phrases up to 1 minute in a
Natural Voice is saved in Non-Volatile E-Prom memory. (If
power is removed the recordings will not be lost). We'll record
your message(s) in a male or female voice - or - you can record
the library by using the optional SDS-1000 development board
on an IBM or compatible computer.

- Repeater Identifiers
- Contest Stations
- Site Alarms
- Remote Telemetry
- Weather Stations
- Multiple Languages
- Emergency Announcements

Parallel Input Word Select 8 ohm Audio output
500 ma Keyline Output 600 ohm Audio output
32 Kb sampling rate +9v to +14v Supply
Multiple Modes Size: 4.00" x 4.25"
30 sec - 30 minute Timers Connectors Included

Price \$ 169.00 Single Qty (programmed)

Palomar Telecom, Inc.
300 Enterprise St. Suite E
(619) 746-7998

CIRCLE 264 ON READER SERVICE CARD

Radio Buffs

1-800-828-6433

4400 Hwy 19-A • Mount Dora FL 32757

AUTHORIZED America's Best JRC DEALER

PARAGON • OMNI V
DELTA II
ARGONAUT II

AUTHORIZED JRC DEALER

JST-135 HF Transceiver

PT 2500 Amplifier

DJ-560T

ALINCO

DR-590T

Radio Buffs

N4EDQ Amateur Radio Sales

4400 Hwy 19-A • Mount Dora, FL 32757

- Communications Receivers
- Portable Receivers
- Amateur Transceivers
- HT's & Mobile Transceivers
- Amateur & SWL Antennas
- Scanners
- Books, Manuals & Accessories

1-800-828-6433

Find out why thousands of customers have switched to us
We Stock ALL Major Brands

WAØWCX

\$39.95

AMERICAN RAINBOW

Unique dimensional designs printed in a red and blue rainbow blend on white 30lb Vellum Bristol. Send S.A.S.E. with 2 stamps for samples or order 1000 now by sending a check for \$39.95 along with all your particulars. Minnesota residents please add 6% sales tax. Please make checks payable to Denny Johnson and allow 2 weeks for delivery. We guarantee that you'll be pleased!

New Dimension QSL

4600 Lucia Lane, Minneapolis, Minnesota 55432 (612) 871-5881

coming soon...

D & D Cliff Dweller Antennas

"the best way to communicate"

antennas & tower components

look for more info in coming issues of "73's" and *Radio Fun* or write:

The Nicholsons
P.O. Box 5114
Dover, NH 03820
Donna KA1TAW & Dave KA1STT

CIRCLE 252 ON READER SERVICE CARD

SPY ON THE EARTH

See on your computer screen what 6 or more U.S., Russian and Japanese satellites see. Make money many ways. Makes a terrific science project. We manufacture and sell all the equipment you need. In business since 1956.

For complete details dial our electronic bulletin board anytime. 300-2400 baud. Modem configuration: 8 bits, 1 stop, no parity: (718)-740-3911. Voice 8AM-1PM: (718)-468-2720.

Or send \$10 for fantastic 5 disk program set for your IBM-PC.

Vanguard Labs

196-23 Jamaica Ave., Hollis NY 11423

Common "Q" Signals

"Q" abbreviations become questions only when they are followed by a question mark. Taken in context, shades of meaning can occur.

QRG Will you tell me my exact frequency (or that of...)? Your (or that of...) exact frequency is...

QRH Does my frequency vary? Your frequency varies.

QRI How is the tone of my transmission? The tone of your transmission is (1, 2, 3, 4, or 5—bad, poor, fair, good, excellent, respectively).

QRL Are you busy? I am busy (with); Please do not interfere.

QRM Is my transmission being interfered with? Your transmission is being interfered with.

QRN Are you troubled by static? I am troubled by static.

QRO Shall I increase power? Increase power.

QRP Shall I decrease power? Decrease power.

QRQ Shall I send faster? Send faster (...wpm).

QRS Shall I send more slowly? Send more slowly (...wpm).

QRT Shall I stop sending? Stop sending.

QRU Have you anything for me? I have nothing for you.

QRY Are you ready? I am ready.

QRW Shall I inform...that you are calling him on...kHz? Inform...I am calling him on...kHz.

QRX When will you call me again? I will call you again at...

QRY What is my turn? Your turn is numbered...

QRZ Who is calling me? You are being called by...(on...kHz).

QSA What is the strength of my signals (or those of...)? The strength of your signals (or those of...) is (1, 2, 3, 4, 5—weak to very good, respectively).

QSB Are my signals fading? Your signals are fading.

QSD Is my keying defective? Your keying is defective.

QSG Shall I send...messages at a time? Send...messages at a time.

QSK Can you hear me between your signals, and can I break in? I can hear you, break in on my transmission.

QSL Can you acknowledge receipt? I am acknowledging receipt.

QSM Shall I repeat the last message I sent you, or some previous message? Repeat the last message which you sent me (or message number(s)...).

QSN Did you hear me (or...) on...kHz?

QSO Can you communicate with...? I can communicate with...

QSP Will you relay to...? I will relay to...

QST General call preceding a message addressed to all amateurs and ARRL members. This says in effect, "CQ ARRL."

QSU Shall I send or reply on this frequency (or on...kHz)? Send or reply on this frequency (or...kHz).

QSV Shall I send a series of V's on...kHz? I am going to send a series of V's on this (or...kHz) frequency.

QSW Will you send on...kHz? I am going to send on...kHz.

QSX Will you listen to...on...kHz? I am listening to...on...kHz.

QSY Shall I change frequency? Change frequency to...kHz.

QSZ Shall I send each word or group more than once? Send each word or group twice (or...times).

QTA Shall I cancel message number...? Cancel message number...

QTB Do you agree with my word count? I don't agree. I will repeat the first letter or digit of each word or group.

QTC Messages to send? I have...messages to send.

QTH What is your location? My location is...

QTR What time is it? The time is...

Radio Fun flea market

Turn your old ham and computer gear into cash now. Sure, you can wait for a hamfest to try and dump it, but you know you'll get a far more realistic price if you have it out where 100,000 active ham potential buyers can see it, rather than the few hundred local hams who come by a flea market table. Check your attic, garage, cellar, and closet shelves and get cash for your ham and computer gear before it's too old to sell. You know you're not going to use it again, so why leave it for your widow to throw out? That stuff isn't getting any younger!

The *Radio Fun Flea Market* costs you peanuts (almost)—comes to 10 cents a word for individual (noncommercial) ads, and 70 cents a word for commercial ads. Don't plan on telling a long story. Use abbreviations, cram it in. But be honest. There are plenty of hams who love to fix things, so if it doesn't work, say so.

Make your list, count the words, including your call, address and phone number. Include a check or your credit card number and expiration. If you're placing a commercial ad, include an additional phone number, separate from your ad.

This is a monthly magazine, not a daily newspaper, so figure a couple of months before the action starts; then be prepared. If you get too many calls, you priced it too low. If you don't get many calls, too high.

So get busy. Blow the dust off, check everything out, make sure it still works right, and maybe you can help make a ham newcomer or retired old-timer happy with that rig you're not using now. Or you might get busy on your computer and put together a list of small gear/parts to send to those interested.

Send your ads and payment to *Radio Fun Flea Market*, Sue Colbert, Forest Road, Hancock NH 03449 and get set for the phone calls.

PL 259 SILVER; TEFLON USA MADE, 100 PIECES, \$79.00. SATELLITE HEADQUARTERS, (804) 239-7585. RF231

HOBBY/BROADCASTING/HAM/CB/SURVEILLANCE transmitters, amplifiers, cable TV, science, bugs, other great projects! Catalog, \$1.00. PANAXIS, Box 130-R9, Paradise CA 95967. RF232

EASY RADIO KITS: Neophyte Receiver with tuning capacitors--\$25.00, new Cubic Incher Transmitter--\$17.00. Catalog--SASE; 624 KITS, 171 Springlake Drive, Spartanburg SC 29302. (803) 583-1304. RF261

JUST IMAGINE YOUR OWN BLUE RIDGE MOUNTAIN TOP 25-acre QTH in the cool, green mountains, only \$975 per acre. Wonderful view, wild game, privacy, road frontage, small stream, ideal for hamming, retirement or summer home. Financing available. KK4WW, Floyd VA. (703) 763-3311. RF262

AMATEUR RADIO CLASSIFIED Quality Buy/Sell/Trade publication. Twice monthly. Inexpensive, easiest to read. Subscriptions: \$12/year. Ads: 25 cents/word. FREE SAMPLES. POB 245-S, Jonesboro GA 30237. RF263

PREMIUM QSL CARDS Unique colorful designs, starting at \$75 for 250. Send \$1.00 for catalog and samples. BVE Professional Printing, 2023 Chicago Avenue, Suite B13-3, Riverside CA 92507. RF264

WANTED: Yaesu FT-23R-HT and pre-1980 microcomputers for museum. KK4WW, (703) 231-6478/763-3311. RF265

AMIGA, MCINTOSH, ATARI XL/XE/ST Amateur radio public domain software for \$4.00 disk. SASE for catalog. Specify computer! KD Hamsoft, Box 1646, Orange Park FL 32067-1646. RF266

WANTED: Manual or instructions for a "COMMUNICATOR IV" 2 meter, Model 3341, Ser#A1234. Made by Gomset Division, Young Spring & Wire Corp., Burbank CA. Ralph Noll, 190 Nob Hill Ln., Ventura CA 93003. (805) 642-2024. RF267

FREE FLYER OF ELECTRONIC GOODIES. Call (800) 779-1761 and leave your address. RF268

REPOSSESSED VA & HUD HOMES available from government from \$1 without credit check. You repair. Also S&L bailout properties. Call 1 (805) 682-7555, ext. H-5079 for repo list your area. RF269

SEIZED CARS, trucks, boats, 4wheelers, motorhomes, by FBI, IRS, DEA. Available your area now. Call 1 (805) 682-7555, ext. C-4546. RF270

HOME-BREW COMPONENTS: MPF-102 4/\$1.00 NE602AN \$1.95 ea. T-50-6 4/\$1.00, over 400 bargains, catalog LSASE. KA7QJY, Box 7970, Jackson WY 83001. (1-307-739-1634, evenings.) RF271

QSL T-SHIRTS Your QSL card enlarged to approximately 8x10 and transferred to 100% cotton T. \$17.00 or 50/50 sweatshirt \$22.00. SM-XXL. Add \$3.50 for shipping. Satisfaction guaranteed. Laurelwood Designs, (RF)2728 South East Laurelwood Dr., Milwaukie OR 97267. RF272

NEW!! NEW!! NEW!! NEW!! SPEAK TO THE WORLD Amateur radio language guide •Written especially for the ham radio operator •Hundreds of phrases •Volume 1—Spanish, German, French, Polish, and Japanese. •Volume 2—Swedish, Italian, Portuguese, Croatian, and Norwegian •Send \$10.00 per book (postage paid); ROSE, P.O. Box 796, Mundelein IL 60060-0796. RF273

SATELLITE RECEIVERS used, good for experiments, \$29.00. Motor controls, \$19.00. LNAs, \$10.00. Satellite Headquarters, (804) 239-7585. RF274


QRP FUN!! Five watt, 40 meter QRP transmitter! Easily modified for 30 meters! Assembled and tested—only 24.95 postpaid! DWM Enterprises, 1709 N. West, Dept. 103, Jackson MI 49202. RF299

LAMBDA AMATEUR RADIO CLUB International amateur radio club for gay and lesbian hams. On-air skeds, monthly newsletter, and annual gathering at Dayton. (215) 978-LARC. P.O. Box 24810, Philadelphia PA 19130. RF812

CONNECTORS UHF, VHF, BNC, TNC, TV. We have them all, lowest prices to everyone. For catalog, send \$2.00, refundable on first order to: Satellite Headquarters, 98310 Timberlake Rd., Lynchburg VA 24502. (804) 239-7585. RF959


FREE Ham Gospel Tracts, SASE, N3FTT, 5133 Gramercy, Clifton Hts. PA 19018. RF960

CONNECTICUT'S FAVORITE HAM STORE Rogus Electronics, 250 Meridenwby Turnpike, Southington 06489. (203) 621-2252. RF994



HandiPacket PORTABLE PACKET CONTROLLER

"One of PacComm's Handipackets is Aboard the MIR Space Station Listen for U2MIR on 145.55 MHz"



PacComm

- Advanced Technology
- Enduring Value

3652 W. Cypress Ave., Tampa, FL 33607-4916
(813) 874-2980 Fax: (813) 872-8696 (800) 223-3511

Leading Provider of Packet Equipment for Amateur Radio

Broad selection including the following features:

- Portable
- VHF and HF Models
- Internal Cards for PCs
- Amateur Satellite Modems
- High Speed
- Low Cost

Ham Stories

Responses to Wayne's request for exciting moments in ham radio.

Carty Ellis KA2Y (ex K2OES), Rochester NY You wanted to know about some of the more exciting moments in ham radio. There have been enough exciting moments to keep me involved in this hobby for 30 plus years ... from age twelve to my current 45. The toughest part of that challenge you pose is zeroing in on my most exciting or memorable moment.

There are many aspects to the excitement this hobby provides: my fascination with technology and gadgets, the escape that was provided a young person with bad asthma in a small town, covering the world on the air waves, that perennial need to be the biggest kid on the block, or the fastest gun (bug) in the West, and the general love of learning I have always had. I pray I keep going till I pass on to the big station in the sky.

Where do I begin? My first contact? My first exposure to ham radio? The first time I felt 800 volts in my arm (or the second—who says we learn from our mistakes!)? Hearing Barry Goldwater's station running phone patches to Southeast Asia in 1967? Coming home from a hamfest last summer with a Collins S-line station under my arm (who was a ham in the sixties that didn't drool over a Collins S-line station)?

Or maybe I should start with my first AMTOR contact or packet connect; then there's the day I passed my Novice exam, and the times I upgraded to Technician; General; Advanced; Extra. And how about the day I sat in my car with 10 watts, 2 meter FM in Rochester, New York, and chatted through a Detroit repeater? The day I accessed a local remote base with my 2 watt handheld from the car and chatted with a station in the Netherlands?

Or the day I delivered my first MARSGRAM to a lonely wife? The day my son KS2Z got his first license, or the day he got his Extra? The day I sat down and had a QSO using a station as old as I was—a Collins 75A1 receiver and a Collins 32V1 transmitter? Listening to the 3898 Gator Traders Net on a National SW-3 receiver. For those of you who don't know, that receiver has three tubes and was "top shelf" in the mid '30s.

These last two items led me to many fascinating and fun visits, which the XYL enjoyed too, such as a trip to the Antique Wireless Museum in Holcomb, New York, where I actually heard a syncro-spark transmitter on the air.

I could go on and on because I have such a magical treasure chest in my mental attic that is fun, and yes, sometimes melancholy, to open and rummage through, and maybe that is why I always turn to your editorials first, Wayne. You too have some great memories of people and places and experiences. Some I even share, like hearing W2OY "No kids, No Lids, No Space Cadettes, No Phonies, etc.," calling CQ on 75 phone. I heard him when I was a Novice here in upstate New York, in a little town called Penn Yan on beautiful Keuka Lake, with a

Knight Kit Ocean Hopper regenerative receiver that I built from a kit (with the gentle help and guidance of Paul Durham, now a Silent Key. Paul was my Uncle's Elmer, too—in 1934) and a 75 watt oscillator using a 6146 as an oscillator from the 1957 *ARRL Handbook*, when they had stuff real people could put together ...

As I look back over this quick list, I think I have found my most important moment. My Uncle Woody (George Wagstaff W8AZW of Willowick, Ohio) came to visit my mother and me one summer evening in 1957. He was then K6JZN, living in Hayward, California. I can see my mother and aunt standing beside the car, while Uncle Woody started the engine and turned on his Morrow Twins. People were talking TO EACH OTHER! Uncle Woody picked up the microphone off the dashboard, and called a station, where I do not remember, but the voice in the radio said hello to ME! This was probably the most magical moment I ever had. And then when he said I could do that too ... I don't think I came down for about two days. Someday I am going to own a pair of Morrow Twins, too.

A few weeks later, after he had returned to California, he sent me some books on how to get started in amateur radio. Going through those books was spellbinding. It was way back then that I knew that someday I would have that Amateur Extra Class ticket. Uncle Woody sure is owed a lot for the years of fun (and all the money I've spent) that he started me on.

Douglas Byrne G3KPO, Ryde, Isle of Wight, England Reference your "biggest thrill" request in the January 1991 issue of 73. Doubtless you will get some fantastic, wonderful, and right-out-of-this-world replies. The one that sticks in my mind is so mundane that I hardly think it's worth writing about. And yet, it will always remain one of my happiest memories of 35 years in hamming.

Some few years ago, I was idly tuning round the then quite new Novice band when I heard a very weak, very slow, and extremely hesitant CQ call. Returning the call at the same speed, I eventually found the young apprentice was a 13-year-old girl, who was right-over-the-moon because I had gone back to her call from faraway England—for her *first ever* QSO outside the states. It had obviously made her day, as it did mine, and the kid followed it up with a lovely little letter and QSL card.

Rene Matthijssen VE6WCA (ex PAØYS), Edmonton, Alberta, Canada It must have been around 1965. I had just received my ham radio license, and I was very proud of my call: PAØYS. My good friend Jeroen was also very much interested in the hobby, so he and I quite often worked together on projects.

The newspaper was full of rumors that we were to get a commercial pirate TV station. It was to be built on an old oil drilling platform just off the coast of Holland, with a power of 120 kW and an antenna height of 300 feet. It was financially supported by selling one million shares to the Dutch public at 25 guilders (\$10 dollars) per share. Everyone was excited about it since Holland only had one government TV station that broadcast three hours per day and not on Mondays!

Jeroen and I quickly built a solid state test pattern generator (checkerboard!) and a 10 watt transmitter on TV chan-

nel 11, and put it on the air. Immediately, the papers were full of people claiming that they had seen the pirate TV station (wrong pirate). Orders started pouring in for outside TV antennas. We installed 90 of them in a few weeks! Nobody noticed the difference when the pirate TV station, called REM, finally came on the air. Of course, some of the antennas had to be turned around, since they were pointing in the wrong direction. We lived in the middle of Holland, while REM was in the North Sea. Everyone accepted this as normal "fine tuning" of the antenna.

We had a lot of fun doing this—until the Dutch government shut REM down.

Another memorable event was in the late '50s, when foxhunting was done on 80 meters. My father helped me build a "portable" radio. It consisted of a battery tube-type super het-

erodyne receiver with a loop antenna. The high voltage was 135 volts. The cabinet was made out of steel plate.

Very shortly after the receiver was completed, during one of the foxhunts, one of the high voltage wires touched the filament wire. The tubes glowed brightly for a split second!

The receiver was built like a battle ship, and one day it fell down the stairs in an apartment building. After falling down three stories, the antenna was slightly bent. But it still worked.

Everything was fine until it started to rain. Since the headphones were directly connected to the plate circuit, a full 135 volt DC was applied to the ears! Try that while hanging onto a metal cabinet.

The answer was to find a transformer and a 50 ohm headphone. That solved the "curly" hair problem. **RF**



PETER COUPE.
98UKO



Oh, sure, I can send and receive
C.W. at 36 words a minute—it's the other
24 letters I just can't seem to get!

You Bet

Minnesota

ICOM • YAESU



Satellite City

2663 County Road I, Moundsview, MN 55112

The
Minnesota
Ham
Store

National 1-800-426-2891 Local 1-612-786-4475 Super MN WATTS 1-800-279-1503

try something new

Continued from page 24

space station! They now have a 24-hour packet BBS in operation on 145.55 MHz. If you're already on packet radio, no additional equipment is needed. Just tune into 145.55 MHz during one of the passes and try to connect to U5MIR-1 (for the BBS), or try to hook up live with one of the cosmonauts (use U5MIR without the extension). The signals are very strong, and you only need a modest station to connect up to the station. Say hello to the cosmonauts as they zip along

overhead. By the way, if the *Mir* station is passing over at one-half to one hour or so after sunset or before sunrise, you have an excellent chance to actually spot them visually in the sky! *Mir* appears as a bright fast-moving spot of light that will fade out as it hits the earth's shadow. I've actually seen the sun reflect off of *Mir*'s solar panel array in just the right angle to produce a spectacular bright flash.

RS-14/OSCAR-21

Although requiring some additional equipment for the 70 cm band (435-438 MHz SSB or CW), you'll

find this to be an excellent satellite because of its exceptionally strong signal. There have been numerous reports of mobile or portable operation using minimal antenna systems and average power. The uplink is between 435.102-435.022 MHz with a downlink between 145.852-145.932 MHz. The CW beacon is on 145.822 MHz, and is a good place to start looking for this satellite. Another transponder is used a lot with slightly different frequencies: 435.123-435.043 MHz uplink, 145.866-145.946 MHz downlink. The CW beacon is on 145.948 MHz.

How to Find Satellites

You should use a computer tracking program to predict when a particular satellite will be in range of your location. The two most popular ones for IBM compatibles at this time are InstantTrak 1.0 and Quiktrak 4.0. You need to input Keplerian elements into these programs and some information about your location. You can then predict very accurately when satellites are coming over and where to point at them in the sky. Both of these programs are available from AMSAT-NA (see the address in the sidebar).

These satellite element sets are available from local packet BBSs as AMSAT bulletins, phone line BBSs such as DRIG (Dallas Remote Imaging Group) at (214) 394-7438, the Celestial BBS at (513) 427-0674, or from the several weekly HF AMSAT nets (see the table for net times and frequencies). The DRIG BBS carries all of the AMSAT bulletins as well.

Another excellent source of information can be found each month in 73 in the Hamsats column by Andy MacAllister WA5ZIB.

The Final Frontier

It is really quite a thrill to hear signals from space. It never ceases to amaze me that I can hear a satellite with just my 2 meter HT. With the array of satellites currently in orbit, you have a wide variety of modes and capabilities. Depending on which satellite you want to operate, your ground station could be just a 2 meter HT or something resembling NASA mission control! Several new satellites with even more amazing modes are in the works. Give a listen to some of these satellites. I think you'll like tuning in to the final frontier.

RF

You may contact Bill Brown WB8ELK at 73 Magazine, Forest Road, Hancock NH 03449.

easy to use satellites

The following is a list of the easiest satellites to operate (only the most commonly used frequencies are listed):

RS-10/11

Mode A

Downlink: 29.360-29.400 MHz, SSB or CW

Uplink: 145.860-145.900 MHz, SSB or CW

Beacon: 29.357 MHz

RS-12/13

Mode K

Downlink: 29.410-29.450 MHz, SSB or CW

Uplink: 21.210-21.250 MHz, SSB or CW

Beacon: 29.408 MHz

Mode KT is activated occasionally and adds a 145.91-145.95 MHz downlink in addition to above.

RS-14/OSCAR 21

Transponder 1

Downlink: 145.852-145.932 MHz, SSB or CW

Uplink: 435.102-435.022 MHz, SSB or CW

Beacon: 145.822 MHz

Transponder 2

Downlink: 145.866-145.946 MHz, SSB or CW

Uplink: 435.123-435.043 MHz, SSB or CW

Beacon: 145.948 MHz

Note: These are inverting transponders. When you go up in frequency on the uplink, you will be relayed on a lower frequency on the downlink. This helps to reduce Doppler shift.

DOVE

Downlink: 145.825 FM, packet telemetry and digitized voice messages.

Mir

Up and Down: 145.550 MHz, packet BBS and occasional voice contacts. Callsign currently is U5MIR-1 for BBS and U5MIR for direct contacts.

**One man's junk
is another man's treasure!**

Even if your old ham equipment doesn't work, someone will want it.

Advertise in *Radio Fun* Flea Market and find out who!

See page 28 for details!

HUSTLER

rfconcepts

ARRL

PC Electronics

YAESU TEN-TEC ALINCO

Larsen Antennas Ameco

Outbacker Antennas Cushcraft CORPORATION W5YI MFJ DIAMOND ANTENNA

AEA Nye-Viking Kantronics M² ENTERPRISES

Ramsey Kits TELEX hy-gain Bug Catcher COMET

SPECIAL

SPECIAL

CALL

CALL TOLL
FREE

**1-800-70K-HAMS
1-800-765-4267**

For This Month's Special-Buy
Some Quantities Are Limited

FREE SHIPPING UPS SURFACE (except towers/antennas)

9500 Cedar Lake Ave., Suite 100
Oklahoma City, Oklahoma 73114
Local & Info (405) 478-2866 FAX (405) 478-4202

Hours of Operation
M-F 10-6
Sat 10-3



C.O.D.





Simplicity.

Why complicate your life when the simple things work so well? The FT-26/76 handhelds from Yaesu make your life simple. All the features you will ever need • Wide band receiver coverage on 2 meters FT-26 130–174 MHz/RX (140–150 TX), FT-76 430–450 MHz TX/RX • 53 memory channels • FT-26 available in 2 and 5 watt versions • Four user-programmable power levels (with FNB-27) • Built-in Vox • Built-in DTMF calling for selective or group calling • Backlit display and front buttons • Direct 12-volt operation with E-DC-5 adaptor • Key, PTT and Dial locking • Automatic Repeater Shift (ARS) built-in for 2 meters • User selectable channel-only display, simple operation for new Hams • Automatic Battery Saver (ABS) • Automatic Power Off (APO) • Selectable Channel Steps. Accessories and Options: A selection of batteries and leather cases. • Desktop quick charger (NC-42 1 hour) • CTCSS encode/decode unit (FTS-17A) • DC Adaptor with noise filter (E-DC-5) • Mobile Mounting Bracket (MMB-49).

Easy to use. The FT-26/76 is designed to fit comfortably in your hand. Weighing in at just one pound, the FT-26/76 lets you travel light.

Isn't it time to simplify? For complete details on the FT-26/76, contact your nearest Yaesu dealer or call 1-213-404-2700.

(Shown Actual Size)

One-Year Limited Warranty on all Amateur Radio Products
© 1991 Yaesu USA, 17210 Edwards Road, Cerritos, CA 90701.
Specifications subject to change without notice.
Specifications guaranteed only within amateur bands.

YAESU
Performance without compromise.™



IC-24AT
Dual Band
Transceiver

IC-W2A
Dual Band
Transceiver

ACTUAL SIZE

Icom continues to dominate the industry with exceptional product design and innovation. The IC-24AT firmly established Icom as the leader in dual band technology. Now the IC-W2A gives you the advantage of choosing the dual bander best suited for your needs.

The new IC-W2A dual band handheld sets the pace with its sleek design and superior characteristics. Designed for the user who demands the finest features available, the IC-W2A boasts simultaneous dual band receive. Listen to one band while talking on the other! Three tuning systems, high speed scanning with priority watch and 60 memory channels add to the luxurious IC-W2A.

Both the IC-W2A and IC-24AT give you full operation on the two-meter and 440MHz amateur bands with outstanding wideband receive capability.


Each unit features up to five watts of power, programmable scanning, priority watch, a battery saver, DTMF pad for memory channel autopatching, 24 hour clock with timing system, multi-function LCD readouts...the list is infinite. See the IC-W2A and the IC-24AT today at your authorized Icom dealer.

SETTING THE PACE IN DUAL BAND DESIGN

For full details and specifications on the IC-W2A and IC-24AT, call the Icom Brochure hotline at 1-800-999-9877.

CORPORATE HEADQUARTERS
ICOM America, Inc., 2380-116th
Ave. N.E., Bellevue, WA 98004
Customer Service Hotline
(206) 454-7619
CUSTOMER SERVICE CENTERS
18102 Sky Park South, Suite 52-B,
Irvine, CA 92714
1777 Phoenix Parkway, Suite 201,
Atlanta, GA 30349
3071 - #5 Road, Unit 9, Richmond,
B.C. V6X 2T4 Canada

All stated specifications are subject to change without notice or obligation. All ICOM radios significantly exceed FCC regulations limiting spurious emissions. W2A691.

 **ICOM**